

CANARE®



PRODUCT CATALOG
International edition 23A

Canare,

offering value-added products to meet your needs
for today and tomorrow.



Canare Building in Nagoya

Five-point Product Development Goal

1 Responsive

Fulfilling the needs of the industry through custom solutions.

2 Unique

Incorporating valuable features not offered by competitors.

3 Cutting-edge

Devoted to meeting the requirements for emerging technologies.

4 Enduring

Concentrated on products with long-term value.

5 Global

Focused on niche markets as well as universal products.

Corporate Profile


- Name: Canare Electric Co., Ltd.
- Incorporated: February 1974 (commenced operation 1970)
- Capital: 1.04 billion yen
- Activities: Manufacture and sale of audio-video cables, connectors, assemblies, converters and related products for professional audio and video industry.

Company Locations

- Japan Headquarters (Overseas Department)
WN Bldg., 2-4-1 Shin-Yokohama, Kouhoku-ku, Yokohama-shi,
Kanagawa, 222-0033 Japan
Phone: +81-45-470-5674 Fax: +81-45-470-5676
- Sales office in Japan: Yokohama, Nagoya (Sales and Warehouse),
Osaka, and Fukuoka

Subsidiary Companies

- Canare Corporation of America www.canare.com
- Canare Corporation of Korea www.canare.co.kr
- Canare Corporation of Taiwan www.canare.com.tw
- Canare Electric Corporation of Tianjin www.canare.com.cn
- Canare Singapore Private Ltd. www.canare.com.sg
- Canare Electric India Private Ltd. www.canare.in
- Canare Electric (Shanghai) Co., Ltd.
- Canare Harness Co., Ltd (Japan)
- Canare System Works Co., Ltd (Japan)
- Canare Tech Corporation (Japan)



CONTENTS

Fiber-Optic Systems

- 2 Overview
- 7 EO/OE Converters, Repeater
- 12 Mux/Demux, Optical Splitter
- 13 Platform, SFP Transceiver
- 14 HFO Transmission Devices
- 16 HFO Camera Cables
- 20 HFO Camera Connector Panels
- 20 HFO Camera Connector Panels, Splice Enclosures
- 22 HFO Camera Cable Checkers
- 23 Fiber-optic Cables

Connectors

- 26 Overview
- 27 Active BNC
- 28 75Ω DIN Connectors
- 29 75Ω Multichannel Coax Connectors
- 30 75Ω BNC Connectors
- 36 75Ω N Connectors
- 37 75Ω Triaxial Connectors
- 38 RCA Connectors
- 39 F Connectors, Phone Plugs
- 40 50Ω BNC Connectors
- 41 50Ω TNC, N, SMA Connectors
- 42 Cable Stripper, Crimp Tools
- 45 Impedance Transformers

Cables

- 46 Q&A
- 48 Star Quad Microphone Cables
- 51 Two-conductor Shielded Cables
- 55 AES/EBU Digital Audio Cables
- 56 Speaker Cables
- 58 OFC Line, DMX, RS422 Cables
- 59 Ethernet Cables
- 60 75Ω Coaxial Cables
- 61 75Ω Coaxial Cables, 75Ω Triaxial Cables
- 62 75Ω Multichannel Coaxial Cables
- 63 A/V Composite Cables, 50Ω Coaxial Cables
- 64 Technical Note
- 65 Nominal Attenuation

Connector Panels and Patchbays

- 66 75Ω Video Patchbays
- 67 75Ω Mid-size Video Patchbays
- 68 Video Plugs
- 69 Ordering Information
- 70 Unloaded Video Jack Panels, RS422 Patchbays
- 71 Connector Panels
- 73 Audio Patchbays

Multichannel Systems

- 75 Overview
- 76 Snake Trunks, Cable Reel Snakes
- 77 Fantails, Junction Boxes
- 78 Pin Assignments
- 79 Reels

Cable Assemblies

- 80 BNC, DIN
- 81 RCA (video), Triax, Video Patch, RS422, DMX
- 82 Ethernet
- 83 XLR, Phone
- 84 RCA (audio), Speaker, Audio Patch
- 85 Digital Audio, Analog Audio
- 86 HDMI
- 87 DVI, VGA
- 88 VGA, RCA



3G-SDI EO Converters

75Ω Active BNC Receptacles



75Ω Mid-size Video Jacks



Ethernet Cable



Cable Reel Snake

Cable Assemblies



Trunk Lines at the Moment

Migrating to Fiber Optics

Trunk lines carry many different kinds of signals—video, synchronization, audio, control, power supply—and consequently they're usually comprised of numerous different types of cables. As a result, conduits, electrical pits, and ladders tend to overflow with cabling, leaving hardly any room when lines must be added to upgrade or expand the system.

But, converting these disparate signals into optical signals and transmitting them using fiber optic cables greatly reduces the need for so many specialized cables. Converting trunk lines to fiber optics makes it much easier to design and upgrade equipment and systems, because once laid these lines can be used with considerable flexibility. Fiber optic cables also have smaller diameters, meaning they take up less space, a clear advantage in alleviating some of the problems of today's cable-stuffed broadcasting facilities.

Sending HD Signals Everywhere


HD-SDI signals can be transmitted only about 100 meters over standard coaxial cables (5C-FB). This means that when wiring rooms and buildings with coaxial cables, it's sometimes difficult to achieve an optimal layout or position equipment where it will be most convenient and useful.

Further, signal transmissions often need to cover unexpectedly long distances, and fiber optic cables, with their transmission distance measured in tens of kilometers, win hands-down over coaxial cables. This flexibility alleviates much of the conventional worry about cable routing and allows the equipment itself to take center stage.

The cost of optical signal converters has dropped radically, too—most can be had for a few hundred dollars—making it difficult these days to find reasons not to introduce fiber optic systems!


Cable Diameters

Even with 100 cores (lines), a fiber optic cable has an external diameter of just 11.5 mm. Compare that to a typical coaxial cable and the difference is clear.



Example of an Optical Fiber Trunk Line

Fiber optic systems are used in signal transmissions within a single broadcast station, or between a main building and an annex building.




Diversified Needs for Optical Conversion

It is not just the HD-SDI signal

It is not just the HD-SDI signal that is converted into optical signals. For example, there is a case in which the HD-SDI signal is converted into optical signals along with the control signal to transmit video images during recording in a studio. Converting various signals into optical signals allows them to be transmitted through fiber-optic cables, eliminating the necessity of separately preparing metal cables.

Advantages of Fiber Optic Transmission in the Field

With it now so easy to convert transmissions into optical signals, fiber optic systems are better suited than ever to field recording applications. Newly developed extra-strong, extra-bendable optical fibers have finally reduced past concerns about cable durability, meaning that in applications like remote broadcasting, video, audio and other signals can all be transmitted on a single cable, one of the inherent merits of fiber optic systems.



Tough & Flexible HFO Camera Cable



(See page 18)

Important Fiber Optic Line Considerations

■ Minimum Light Receiving Power

In optical transmission, transmission quality is evaluated by the relationship between “light receiving power” and “error rate.” Error rate is dependent upon the signal to noise ratio (S/N), but since the noise level is thought of as being at a set level independent of the signal strength, the strength of the signal (light receiving power) at the receiver influences S/N considerably, in turn affecting the error rate. Therefore, to maintain a specified transmission quality, it is necessary to design light receiving power to be above the minimum light receiving power of the receiver.

The graph at right shows the light receiving power and error rate within the combination of the EO-100B and OE-151. From this graph, we can estimate that to get an error rate of 2×10^{-18} (to ensure a probability of 1 for transmission errors during 10 years of continuous operation), the light receiving power of the OE-151 must be set greater than -24.3dBm assuming the signal source and EO-100B are connected by a coaxial cable 1 meter in length (SMPTE connection standard). If the signal source and EO-100B are connected by a coaxial cable 190 meters in length, then the OE-151 light receiving power must be more than -23.6dBm, from which we can see that the light receiving power deteriorates by about 1dB as compared with the connection standard.

■ Loss Budget (LB)

Loss budget is the difference between the optical power output (P1) from the EO converter and the light reception sensitivity (P2) of the OE converter.


LB = P1-P2

Example) If the optical power output $P_1 = -3.5\text{dBm}$ and the reception sensitivity $P_2 = -24\text{dBm}$:




$$\text{LB} = -3.5\text{dBm} - (-24\text{dBm}) = 20.5\text{dB}$$

In EO/OE system design, 1) cable attenuation loss, 2) connector insertion loss, 3) fusion splice connection loss, and 4) Mux/Demux insertion loss have to be calculated so that they are less than the loss budget (LB) of the optic link. For HD/SD-SDI system, since the Mux/Demux loss is greater than that of the fiber attenuation loss, it would be essential you to consider such loss elements when you configure the system.



Loss Budget Diagram




Loss Attenuation

	Loss Factor	Value
①	Connector Insertion Loss	0.5dB/Point
②	Mux/Demux	2~3dB/Point
③	Fiber Cable	0.3dB/km(*)
	Splitter	0.5dB/Main 10dB/Branch
	Divider	3dB/Point
	Fusion Splice Loss	0.2dB/Point
	System Margin	2~6dB

* 0.5~1.0dB/km for Dark fiber

EO/OE Converter Line-up

Canare's EO/OE product line-up has expanded. A large variety of signals can be sent over fiber-optic cables with a simple set-up. Canare EO/OE will break your system free from distance limitations, signal delays, and noise problems.




Platforms (page 13)



Welcome to a Canare EO/OE Stadium

Please take a look at how a Canare EO/OE system fits perfectly in a modern stadium that handles variety of signal formats such as 3G-SDI/HD-SDI, RS-422/232, 100BASE-TX, and analog audio.



Canare EO/OE products offer smart solutions to stadium or arena AV systems which require broadcast quality video, audio, and data signals. Plug-and-play modular style optical converters can be easily installed. Fiber optic cable based distribution has many advantages, such as long distance transmission, low latency, noise free, and much more!

Wavelength Multiplexing Systems

Multiplexing

"Multiplexing" is a technology that allows multiple signals with different wavelengths to be transmitted together over a single optical fiber. Three general types of multiplexing — WDM, CWDM and DWDM — offer increasing signal-carrying capacities, as described below.

Wavelength Division Multiplexing (WDM)


WDM is the simplest form of multiplexing and uses two wavelengths of 1310nm and 1551nm. Unlike when using an optical divider, insertion loss can be kept below 0.5dB.

Coarse Wavelength Division Multiplexing (CWDM)

CWDM systems use 8 wavelengths (20nm grid) primarily between 1471nm and 1611nm. To these it is also possible to add 8 more between 1271nm and 1451nm to allow a maximum of 16 wavelengths to be carried as a single multiplexed transmission. An ultra-thin membrane filter on the optical multiplexer/demultiplexer (mux/demux) keeps insertion loss at just 2-3dB.
*CWDM standardized through ITU G695.

Optical Converter (TX for CWDM)

Canare's CWDM optical converter uses a DFB laser, which offers a much tighter spectrum than FP lasers. Up to 16 different wavelengths fall within 1271nm and 1611 nm in 20nm intervals. The wavelengths in the 20nm grid between 1391nm and 1411nm are not used because their proximity to the water peak results in too much attenuation.



Optical Multiplexer/Demultiplexers

The optical signals output from the optical converter (TX) are combined into a single signal by the multiplexer (mux) and transmitted along a single optical fiber. At the receiving end, these combined optical signals are demultiplexed (demux) to split them back into their original component 8 signals.

Optical mux/demuxes are bi-directional, so the same model can be used for transmitting and receiving on each end. It's also possible to use 4 wavelengths out of the 8 for transmitting and the remaining four for receiving. Both 8-wavelength and 16-wavelength models are available, and combining these with an optical converter allows a variety of system constructions with many uses.


Optical Converter (RX)

Canare's optical converter (RX) converts an optical signal comprised of 8 different wavelengths into electrical signals. This converter is common to all wavelengths and one converter is required for each wavelength.


Once optical fiber cables have been laid, multiplexing the transmissions carried on them eliminates the need to purchase and install new cables when more transmission lines are needed.

Eight Canare optical converters and an FCWDM-8B mux/demuxer can be installed compactly on a single 161UPSC 1RU-size platform, effectively allowing an 8-wavelength transmission system to be achieved in just 1RU of space.

Multiplexing (CWDM)




8-wavelength CWDM system example



TX

EO converter
for CWDM
EO-100A-**

Mux/Demux
FCWDM-8B



RX

Mux/Demux
FCWDM-8B

OE converter
OE-101B

x 8

Note: Please use with Canare platform.

EO/OE Converters

3G-SDI EO/OE Converters

Canare EO3G/OE3G series, the new line of 3G-SDI capable optical converters are ideal for applications that require the signal quality and integrity to be at its best over long distance transmissions such as in mobile productions, event venues, and within or between broadcast facilities.

■ Electric to Optic Converter (TX)

Model	Wavelength	Emission	Monitor Out	Occupancy
EO3G-100	1310 nm	-5 dBm	No	1 slot
EO3G-200			Yes	2 slots
EO3G-100A-**	1271-1611 nm for CWDM*	+2.5 dBm	No	1 slot

*Refer to the following information to specify the wavelength and the model number.

■ Optic to Electric Converter (RX)

Model	Wavelength	Sensitivity	Monitor Out	Occupancy
OE3G-101	1200-1620 nm	-22 dBm	No	1 slot
OE3G-201			Yes	2 slot

Key Features and Benefits

- Multi format - 3G-SDI, HD-SDI, SD-SDI, and DVB-ASI
- EO3G-200 and OE3G-201 are equipped with Monitor output port.
- Super low-latency
- Compact size
- Easy to use; requires no complicated settings.
- Supports pathological test pattern
- Cost effective

■ Specifications

Model	EO3G-100	EO3G-200	EO3G-100A	OE3G-101	OE3G-201
Convertibility	Electric to Optic			Optic to Electric	
Optical Connector		1 x LC (output)			1 x LC (input)
Fiber Type			Single Mode		
SDI Input	1 x 75 Ω BNC	1 x 75 Ω BNC	1 x 75 Ω BNC	N/A	N/A
SDI Output	N/A	1 x 75 Ω BNC (no-reclocked)	N/A	1 x 75 Ω BNC	2 x 75 Ω BNC
Dimensions (mm)	17 x 43.4 x 78.4	35.5 x 43.4 x 78	17 x 43.4 x 78.4	17 x 43.4 x 78.4	35.5 x 43.4 x 78
Weight (approx.)	100 g	150 g	95 g	100 g	150 g
Typical Compliances			SMPTE 259M, 292M, 297-2006, 424M, EN50083-9		

3G-SDI Repeater

Equalizes and reclocks 3G/HD/SD-SDI signals to extend the transmission distance over a coaxial cable.

Model	Support Formats/Rates	Occupancy
EE3G-100	3G-SDI, HD-SDI, SD-SDI, DVB-ASI	1 slot


Key Features and Benefits

- Typical cable equalization: 100 m of L-5CFB in 3G-SDI
- Supports 3G/HD/SD-SDI and DVB-ASI
- Passes embedded audio
- Allows for efficient use of existing cable infrastructure.

■ Specifications

I/O Connector	2 x 75 Ω BNC
Typical Compliances	SMPTE 424M, 292M, 259M, EN50083-9

Example of Use



EO3G-100
(TX)



EO3G-200
(TX with Monitor Output)



OE3G-101
(RX)



OE3G-201
(RX with Monitor Output)



EO3G-100A-**
(TX)

Ordering Information for EO3G-100A-**

EO3G-100A-	27	Wavelength
	27	1271 nm
	29	1291 nm
	31	1311 nm
	33	1331 nm
	35	1351 nm
	37	1371 nm
	43	1431 nm
	45	1451 nm
	47	1471 nm
	49	1491 nm
	51	1511 nm
	53	1531 nm
	55	1551 nm
	57	1571 nm
	59	1591 nm
	61	1611 nm



EE3G-100

Dimensions : 17 x 43.4 x 78.4 mm
Weight : 85g

Note: Platform (power supply) is required to use Canare converters (see page13).

Fiber-Optic Systems

EO/OE Converters

HD-SDI EO/OE Converters

■ Electric to Optic Converters (TX)

Model	Wavelength	Emission	Reclocker	Occupancy
EO-100B	1310 nm	-3.5 dBm	Yes	1 slot
EO-160		N/A		
EO-100A-**	1271-1611 nm for CWDM*	-2.5 dBm	Yes	

*Refer to the following information to specify the wavelength and the model number.

■ Optic to Electric Converters (RX)

Model	Wavelength	Sensitivity	Reclocker	Occupancy
OE-101B	1200-1620nm	-24 dBm	Yes	1 slot
OE-151			N/A	

Key Features and Benefits

- Multi format - HD-SDI (up to 1.485 Gbps), SD-SDI and DVB-ASI
- Embedded audio capable
- Handles pathological test pattern
- No-reclocker models support wide bit rate range.
(50 Mbps to 1485 Mbps)
- Compact design - Maximum 16 modules within 1RU
- Hot swappable
- Cost effective
- Easy to use - BNC and SC-type connector.

■ Specifications

Model	EO-100B, EO-160	EO-100A-**	OE-101B, OE-151
Convertibility	Electric to Optic	Optic to Electric	
Fiber Type	Single Mode		
Optical Connector	1 x SC (output)	1 x SC (input)	
SDI Connector	1 x 75 Ω BNC (input)	1 x 75 Ω BNC (output)	
Dimensions	17 x 43.4 x 78.4 mm		
Weight	77 g	58 g	77 g
Typical Compliances	SMPTE 259M, 292M, 297-2006, EN50083-9		



EO-100B

EO-160



Ordering Information for EO100A-**

EO-100A- [47]

	Wavelength
27	1271nm
29	1291nm
31	1311nm
33	1331nm
35	1351nm
37	1371nm
43	1431nm
45	1451nm
47	1471nm
49	1491nm
51	1511nm
53	1531nm
55	1551nm
57	1571nm
59	1591nm
61	1611nm

EO-100A-**

OE-101B



OE-151



OE-701

Analog Video Optical Converters

Model	Wavelength	Emission	Sensitivity	Occupancy
EO-700	1310 nm	-3.5 dBm	N/A	1 slot
EO-700A-**	1471-1611 nm for CWDM*	-2.5 dBm	N/A	
OE-701	1200-1620 nm	N/A	-26 dBm	

*Refer to the following information to specify the wavelength and the model number.

Key Features and Benefits

- Supports both NTSC and PAL video signals.
- Tri-level sync can be transmitted.
- SNR: 60 dB, Bandwidth: 6 MHz

Specifications

Model	EO-700, EO-700A	OE-701
Convertibility	Electric to Optic (TX)	Optic to Electric (RX)
Fiber Type	Single Mode	
Optical Connector	1 x SC (output)	1 x SC (input)
Video Connector	1 x 75 Ω BNC (input)	1 x 75 Ω BNC (output)
Dimensions	17 x 43.4 x 78.4 mm	
Weight	84 g	
Typical Compliances	SMPTE 170M, ITU-R BT.470	

Ordering Information for EO-700A-**

EO-700A- [47] — Wavelength

47	1471 nm
49	1491 nm
51	1511 nm
53	1531 nm
55	1551 nm
57	1571 nm
59	1591 nm
61	1611 nm

Note: Platform (power supply) is required to use Canare converters (see page13).

EO/OE Converters


AES 3id Optical Converters

Model	Wavelength	Emission	Sensitivity	Occupancy
EO-500-**	1471-1611 nm for CWDM*	-3 dBm	N/A	5 slots
OE-501	1200-1620 nm	N/A	-26 dBm	

* Refer to the following information to specify the wavelength.

Key Features and Benefits

- Multiplex and optically convert AES signals from up to 8 ports (16 audio channels) to allow them to be transmitted over long distance.
- Supports 8 wavelengths CWDM; enables max. 64 ports (128 audio channels) signals to transmit over a single optical fiber.
- AES-3id-1995 and SMPTE 276M
- Fully asynchronous multiplex transmission.
- Word clock can be transmitted (30kHz to 50kHz).
- Dolby-E compatible



Specifications

Model	EO-500-**	OE-501
Convertibility	Electric to Optic	Optic to Electric
Fiber Type	Single Mode	
Optic Connector	1 x SC (output)	1 x SC (input)
AES I/O Connector	8 x 75Ω BNC (input)	8 x 75Ω BNC (output)
Dimensions	91 x 43.4 x 76.2 mm	
Weight		174 g
Typical Compliances	AES-3id-1995, SMPTE 276M	



EO-500-55

OE-501

Ordering Information for EO-500-**

EO-500- **47** — Wavelength

47	1471 nm
49	1491 nm
51	1511 nm
53	1531 nm
55	1551 nm
57	1571 nm
59	1591 nm
61	1611 nm

Analog Audio Optical Converters


Model	Wavelength	Occupancy	Remark
TRM-540	1310 nm		Work with TRM-541.
TRM-541	1550 nm		Work with TRM-540.
TRM-540A-**	1471-1611 nm for CWDM (*1)	5 slots	Work with TRM-540A-** of a different wavelength (*2).

*1) Refer to the following information to specify the wavelength and the model number.)

*2) TRM-540A-** does not work with TRM-540 or TRM-541.

Key Features and Benefits

- Enables line level audio signals to transmit long distance over a fiber-optic cable.
- 8 channel transmission (4-channel inputs/4-channel outputs)
- Maximum input/output voltage: +24 dBu (balanced)
- Supports 600 ohm input by each channel with selector switches.



Block Diagram of TRM-540 and TRM-541

Specifications

Model	TRM-540, TRM-541	TRM-540A-**
Fiber Type	Single Mode	
Optic I/O Connector	1 x SC	2 x LC
Audio I/O Connector	1x D sub 25 pin (F)	
Frequency Response	20 Hz - 40 kHz (-3 dB, +0.1 dB)	
Dimensions	91 x 43.4 x 78.4 mm	
Weight	265 g	



TRM-540

TRM-541

Ordering Information for TRM-540A-**

TRM-540A- **47** — Wavelength

47	1471 nm
49	1491 nm
51	1511 nm
53	1531 nm
55	1551 nm
57	1571 nm
59	1591 nm
61	1611 nm

Note: Platform (power supply) is required to use Canare converters (see page13).

1000BASE-T Optical Converters


Model	Wavelength	Occupancy	Remark
TRM-300-G31	1310 nm	2 slots	Work with TRM-300-G55.
TRM-300-G55	1550 nm		Work with TRM-300-G31.
TRM-300A-G**	1471-1611 nm for CWDM (*1)		Work with TRM-300A-G** of a different wavelength (*2).

*1) Refer to the following information to specify the wavelength and the model number.

*2) TRM-300A-G** does not work with TRM-300-G31 or TRM-300-G55.

Key Features and Benefits

- Media converters for Gigabit Ethernet 1000BASE-T*
- *No backwards compatibility with other Ethernet standards such as 100BASE-TX.
- Super-low latency: less than 1 micro-second.
- Extends communications up to 20 km (condition: line loss 0.5 dB/km)
- Bi-directional optical communication



Block Diagram of TRM-300-G31 and TRM-300-G55

Specifications

Model	TRM-300-G31, TRM-300-G55	TRM-300A-G**
Fiber Type	Single Mode	
Optic I/O Connector	1 x SC	2 x LC
Ethernet I/O Connector	1 x RJ45	
Dimensions	35.5 x 43.4 x 76 mm	
Weight (approx.)	150 g	
Typical Compliances	IEEE 802.3ab (1000BASE-T)	



TRM-300-G31



TRM-300-G55

Ordering Information for TRM-300A-G**

TRM-300A-G	47	Wavelength
	47	1471 nm
	49	1491 nm
	51	1511 nm
	53	1531 nm
	55	1551 nm
	57	1571 nm
	59	1591 nm
	61	1611 nm

100BASE-TX Optical Converters


Model	Wavelength	Occupancy	Remark
TRM-210, TRM-211			Single Mode
TRM-210	1310 nm		Work with TRM-211.
TRM-211	1550 nm		Work with TRM-210.
TRM-210A-**	1471-1611 nm for CWDM (*1)		Work with TRM-210A-** of a different wavelength (*2).

*1) Refer to the following information to specify the wavelength and the model number.

*2) TRM-210A-** does not work with TRM-210 or TRM-211.

Key Features and Benefits

- Media converters for Fast Ethernet 100BASE-TX*
- *No backwards compatibility with other Ethernet standards such as 10BASE-T.
- Auto MDI/MDX
- Extends communications up to 30 km (condition: line loss 0.5 dB/km)
- Bi-directional optical communication



Block Diagram of TRM-210 and TRM-211

Specifications

Model	TRM-210, TRM-211	TRM-210A-**
Fiber Type		Single Mode
Optic I/O Connector	1 x SC	2 x LC
Ethernet I/O Connector	1 x RJ45	
Dimensions	35.5 x 43.4 x 76.2 mm	
Weight (approx.)	103 g	110 g
Typical Compliances	IEEE 802.3u (100BASE-TX)	



TRM-210



TRM-211

Ordering Information for TRM-210A-**

TRM-210A-	47	Wavelength
	47	1471 nm
	49	1491 nm
	51	1511 nm
	53	1531 nm
	55	1551 nm
	57	1571 nm
	59	1591 nm
	61	1611 nm

Note: Platform (power supply) is required to use Canare converters (see page13).

RS-422/RS-232 Optical Converters


Model	Wavelength	Occupancy	Remark
TRM-220	1310 nm	3 slots	Work with TRM-221.
TRM-221	1550 nm		Work with TRM-220.
TRM-220A-**	1471-1611 nm for CWDM (*1)		Work with TRM-220A-** of a different wavelength (*2).

*1) Refer to the following information to specify the wavelength and the model number.

*2) TRM-220A-** does not work with TRM-220 or TRM-221.

Key Features and Benefits

- TIA-422, SMPTE 207M, RS-232
- Usable in a case of RS-422 <=> RS-232
- Extends communications up to 30 km (condition: line loss 0.5 dB/km)
- Bi-directional optical communication



Block Diagram of TRM-220 and TRM-221

Specifications

Model	TRM-220, TRM-221	TRM-220A-**
Fiber Type	Single Mode	
Optic I/O Connector	1 x SC	2 x LC
Serial I/O Port	1 x Dsub 9 pin (F)	
Max. Data Rate	RS-422: 10 Mbps, RS-232: 1 Mbps	
Dimensions	54 x 43.4 x 76.2 mm	
Weight (approx.)	110 g	120 g
Typical Compliances	TIA-422, SMPTE 207M, RS-232C	


Ordering Information for TRM-220A-**

TRM-220A-	47	—Wavelength
	47	1471 nm
	49	1491 nm
	51	1511 nm
	53	1531 nm
	55	1551 nm
	57	1571 nm
	59	1591 nm
	61	1611 nm

More Converters


Model	Occupancy
TRM-100	3 slots
TRM-101	

Multiplex and optically convert HD-SDI and RS-485 signal to transmit long distance over a fiber-optic cable. Suited for HD surveillance camera system.




Model	Occupancy
TRM-400	3 slots
TRM-401	

Multiplex and optically convert analog video, stereo audio, RS-422, and contact signals to transmit long distance over a fiber-optic cable.



Model	Occupancy
TRM-230	3 slots
TRM-231	

Multiplex and optically convert 7 of each input/output contact signal and RS-422/232 signals to transmit long distance over a fiber-optic cable.



Note: Platform (power supply) is required to use Canare converters (see page13).

Fiber-Optic Systems

Mux/Demux, Splitter

CWDM Mux/DeMux

Slot-in Module Types

Model	Ch.	Wavelengths	Occupancy
FCWDM-8B	8	1471-1611 nm	8 slots
FCWDM-8B-13	8	1271-1451 nm	


Rack Mount Types

Model	Ch.	Wavelengths	Size
FCWDM8/1A	8	1471-1611 nm	1RU
FCWDM8/1A-13	8	1271-1451 nm	
FCWDM8/2A	2 each of 8	2 each of 1471-1611 nm	
FCWDM8/2A-13	2 each of 8	2 each of 1271-1451 nm	
FCWDM16A	16	1271-1611 nm	

Key Features and Benefits

- Bi-directional 8 or 16 wavelengths.
- Passive and stand-alone products.
- Easy to use - Just plug in SC-type connectors.
- FCWDM-8B(-13) can be loaded into 161UPSC; enables 8-wavelength CWDM within 1RU frame.

<Loading example (rear view of 161UPSC)>



Specifications

Model	FCWDM-8B (-13)	FCWDM8/1A (-13)	FCWDM8/2A (-13)	FCWDM16A
Connectors	SC			
Passband	+/- 6.5 nm (ITU-T G.695)			
Min. Passband Ripple	0.5 dB			
Max. Insertion Loss*	2.0 dB		3.3 dB	
Min. Isolation	30 dB			
Dimensions (mm)	146 x 43.4 x 94.2	482.6 x 44 x 362.3		
Weight (approx.)	210 g	1700 g	1800 g	1890 g
Wavelengths Details (nm)	1271-1451: 1271/1291/1311/1331/1351/1371/1431/1451 1471-1611: 1471/1491/1511/1531/1551/1571/1591/1611			

* Insertion loss includes ripple, PDL, and connector loss


Optical Splitter

Model	Wavelength	Description
FDM-2	1261-1611nm	1x2 Splitter for Single Mode Fiber
FDM-4		1x4 Splitter for Single Mode Fiber

Key Features and Benefits

- Divides single optical input into multiple optical output.
- Passive and stand-alone products.
- Can be loaded into platform for Canare plug-in unit.
- Easy to use - Just plug in SC-type connectors.
- Low insertion loss.

Insertion Loss



FDM-2



FDM-2
(Rear View)



FDM-4
(Rear View)



FDM-4
(Rear View)



FDM-2

Slot Occupancy : 3 slots
Dimensions : 54 x 43.4 x 82 mm
Weight : 83g



FDM-4

Slot Occupancy : 4 slots
Dimensions : 72 x 43.4 x 82 mm
Weight : 110g


Platform , SFP Transceiver

Platform

Power supply for Canare plug-in modules. The robust 1RU rack mountable and space efficient portable types are available.

Model	Description	Number of Slots
161UPSC-**	1RU rack mount type	16
6PSC-**	Portable type	6
2PSC	Palm size	2
PSM2-**	Redundant power supply module for 161UPSC	N/A

* Please fill in the ** using the following Region Code.



* Please contact us for more detail.

Key Features and Benefits

- Compact design - Maximum 16 modules within 1RU
- Hot swappable
- 161UPSC can be output 4 types of alarm signals via Dsub 9P (F).
- 161UPSC will require a PSM2 for power supply redundancy.

Specifications

Model	161UPSC	6PSC	2PSC
Number of Slots	16	6	2
AC Input Voltage	100 to 240V 50/60Hz	0.35A	N/A
DC Input Voltage	N/A	10 to 18V	10 to 18V
Max Power Consumption (exclusive of modules)	22W	4.5W (AC) 2.2W (DC)	2.2W
Power Connector	AC3P Jack	AC3P Jack (AC) XLR4 Male (DC)	XLR4 Male
Supply Voltage to Module	DC 5V		
Operating Temperature	-10 to 40°C		
Typical Compliance	CB, CE, UL/cUL, KC (161UPSC-K, 6PSC-K, PSM2-K), FCC15B Class A, RoHS		
AC Power Cord Plug Type	(AU), (EU), (GB), (JP), (UC), (N)	N/A	N/A

3G-SDI SFP Optical Transceiver

The Small Form-factor Pluggable transceiver module specified by MSA (Multi-Source Agreement). TRP-300 improves 3G/HD-SDI camera quality through its superior performance in wide range temperature.

Model	Wavelength	Emission	Sensitivity
TRP-300-LN13	FP-LD 1310nm	-5 dBm	-23 dBm

Please contact us for ordering lot.

Key Features and Benefits

- Supports 3G/HD/SD-SDI
- Canare's exclusive "TC Tech" (Temperature-Compensation Technology)
- Log scale optical power monitoring
- Internal status monitoring via I2C bus

Specifications

Number of I/O ports	Input: 1, Output: 1
I/O Connector	LC
Fiber Type	Single Mode
Extinction Ratio	9 dB
Transmission Rate	50 Mbps to 2.97 Gbps
Pin Assignment	SFP MSA Compatible
Supply Voltage	3.3 V
Current Consumption	200 mA
Operating Temperature	-25 to 85 deg C
Compliance	SMPTE 259M, 292M, 297-2006, 424M BTA S-004B, SFP MSA FDA 21 CFR Part 1040.10, 11 with Laser Notice No.50, IEC 60825-1: 2007, UL/cUL, DEMKO, CE, RoHS



161UPSC-**

Dimensions : 434 x 44 x 340 mm
Weight : 4500g



6PSC-**

Dimensions : 210 x 44 x 165 mm
Weight : 650g



2PSC

Dimensions : 90 x 44 x 110 mm
Weight : 200g

10-slot portable platform is also available.



10PSA-JP

Dimensions: 210 x 44 x 280 mm
Weight: 1200 g



TRP-300-LN13

Dimensions: 13.9 x 11.85 x 56.5 mm
Weight: 22g

HFO Transmission Device

3G-SDI HFO Transmission Device

NEW

Transmit 4 channels of 3G-SDI signals over a HFO camera cable.

Model	HFO Connector	V-plate
FCBA4-FF5W1	FCFRA (Female)	No
FCBA4-FF5W1-PV	FCFRA (Female)	Yes
FCBA4-FM5W2	FCMRA (Male)	No
FCBA4-FM5W2-PV	FCMRA (Male)	Yes

FCBA4-FM5W2



FCBA4-FF5W1




FCBA4-FM5W2-PV

Key Features and Benefits

- All-in-one solution 3G-SDI EO/OE modules and power unit.
- The best solution for Quad-link 3G-SDI outside broadcasting.
- Supports 3G-SDI/HD-SDI/SD-SDI and DVB-ASI
- Maximizing existing HFO camera assemblies.
- Flexible configuration for 3G-SDI EO/OE modules.
- AC and DC input redundancy
- Uses one fiber in the HFO camera cable to transmit 4 of 3G-SDI signals, and the other fiber can be utilized by SC throughout connector.

<Example of Use>



Specifications

Model	FCBA4-FF5W1	FCBA4-FF5W1-PV	FCBA4-FM5W2	FCBA4-FM5W2
EO/OE Config	4 x OE3G-101 (RX)		E03G-100A-47 (TX) E03G-100A-49 (TX) E03G-100A-51 (TX) E03G-100A-53 (TX)	
HFO Connector	FCFRA (Female)		FCMRA (Male)	
SDI I/O Connector	2 x 75 ohm BNC		2 x 75 ohm BNC	
EXT connector	XLR5-31F77 (Female)		XLR5-32F77 (Male)	
Optical connector			SC (for optional use)	
AC Connector			AC 3P Jack	
DC Connector	XLR4-32F77 (Male)	XLR4-32F77 (Male) IDX V-plate	XLR4-32F77 (Male)	XLR4-32F77 (Male) IDX V-plate
Power Requirement			AC 100–240 V DC 10–18 V	
Power Consumption			Max. 5 W	
Operating Temp.			-10 to 40 deg C	
Dimensions (mm)			210 x 42 x 240	
Weight (approx.)	1800 g	1850 g	1800 g	1850 g

Note: UL standards cannot be supported because of its structure.

HFO Transmission Device

HD-SDI HFO Transmission Device

Features Hybrid Fiber-Optic (HFO) camera connector interface with HD-SDI EO/OE modules inside.

Model	HFO Connector	V-plate
FCBA-FF3W1	FCFRA (Female)	No
FCBA-FF3W1-PV	FCFRA (Female)	Yes
FCBA-FM3W2	FCMRA (Male)	No
FCBA-FM3W2-PV	FCMRA (Male)	Yes

FCBA-FM3W2



FCBA-FF3W1




FCBA-FM3W2-PV

Key Features and Benefits

- All-in-one solution HD-SDI EO/OE modules and power unit.
- Ideal for HD-SDI outside broadcasting.
- Supports HD-SDI/SD-SDI and DVB-ASI
- Maximizing existing HFO camera assemblies.
- Flexible configuration for EO/OE modules.
- AC and DC input redundancy

<Example of Use>




Specifications

Model	FCBA-FF3W1	FCBA-FF3W1-PV	FCBA-FM3W2	FCBA-FM3W2
EO/OE Config	EO-100B (TX) OE-101B (RX)			OE-101B (RX) EO-100B (TX)
HFO Connector	FCFRA (Female)			FCMRA (Male)
SDI I/O Connector	2 x 75 ohm BNC			2 x 75 ohm BNC
EXT connector	2 x XLR3-31F77 (Female)			2 x XLR3-32F77 (Male)
AC Connector			AC 3P Jack	
DC Connector	XLR4-32F77 (Male)	XLR4-32F77 (Male) IDX V-plate	XLR4-32F77 (Male)	XLR4-32F77 (Male) IDX V-plate
Power Requirement			AC 100–240 V DC 10–18 V	
Power Consumption			Max. 5 W	
Operating Temp.			-10 to 40 deg C	
Dimensions (mm)			210 x 42 x 240	
Weight (approx.)	1200 g	1250 g	1200 g	1250 g

Note: UL standards cannot be supported because of its structure.

Hybrid Fiber-optic Camera Cables (SMPTE 311M)

Type	Model	Sales Units (m)	Nom. O.D. (mm)	Weight kg/100m	Outer Jacket	Overall Shield	Tension Tolerance (N)	Strength Member O.D. (mm)	Min. Bend Radius	Temp. Range (deg C)	Channel Unit		
											Fiber	Aux. (Power)	Signal (Control)
 L-2SM9N Jacket color : black	LF-2SM9N	Call	9.2	12.0	Abrasion-resistance PVC	9/24/0.10TA 91%	700	2.6	6 x Nom. O.D.	-40 to +75	2 x SM 9/125 (low-water-peak) Unit O.D. 0.9 mm	4 x 20 AWG 21 / 0.18TA Unit O.D. 1.7 mm	2 x 25 AWG 7 / 0.18TA Unit O.D. 1.2 mm
	LF-2SM9				Smooth PVC								
	LF-2SM16		16	29.0	Double PVC								

LF-2SM9N

- For general use.
- Abrasion-resistance Jacket enhance the adaptability to all studio and outside broadcast applications.
- Cost effective


LF-2SM9

- For fixed installation.
- Smooth PVC Jacket brings stress-free cabling.



LF-2SM16

- For studio use.
- O.D. 16mm Double Jacket prevents the cable from being jammed under a camera pedestal dolly.

Cross Section



Cable Assemblies

Type	Model	Length (m)
 Jacket color : black	FCC10N	10
	FCC20N	20
	FCC25N	25
	FCC35N	35
	FCC50N	50
	FCC100N	100
	FCC150N	150
	FCC200N	200
 Jacket color : black	FCC30A-WJ	30
	FCC50A-WJ	50
	FCC100A-WJ	100

- Standard and widely-used models.
- Heat shrink tubes help in labeling.
- FCC**A-WJ prevents the cable from being jammed under a camera pedestal dolly by its O.D. 16mm double jacket.
- 7-color connector rings included.

* TAJIMI compatible type (Canare OC series) is also available. Please contact us for more information.




FCFA



FCMA



Color Rings



Wiring Diagram

HFO Camera Cables

Slim Hybrid Fiber-optic Camera Cable

Type	Model	Sales Units (m)	Nom. O.D. (mm)	Weight kg/100m	Outer Jacket	Overall Shield	Tension Tolerance (N)	Strength Member O.D. (mm)	Min. Bend Radius	Temp. Range (deg C)	Channel Unit		
											Fiber	Aux. (Power)	Signal (Control)
	LF-2SM7N	Call	7.1	7.3	Abrasion-resistance PVC	8/24/0.10TA 91%	300	1.4	6 x Nom. O.D.	-40 to +75	2 x SM 9/125 (low-water-peak) Unit O.D. 0.9 mm	2 x 20 AWG 21 / 0.18TA Unit O.D. 1.7 mm	2 x 25 AWG 7 / 0.18A Unit O.D. 1.2 mm

Jacket color : black


LF-2SM7N

- O.D. 7 mm of slim profile and approx. 40% lighter than LF-2SM9N.
- Best fit for mobile applications.
- The power transmission distance is approx. twice as long as the previous model LF-2SM7R.




Note: The power transmission distance is shorter than typical HFO camera cables (approx. 50% of LF-2SM9N). Please contact us for more information.

*Multichannel cables, LF-2SM7N-3P and LF-2SM7N-5P, are also available.

Cross Section



Cable Assemblies

Type	Model	Length (m)
 Jacket color: black	FCC10-7N	10
	FCC20-7N	20
	FCC30-7N	30
	FCC50-7N	50
	FCC100-7N	100
 Jacket color: black	F3-FCC10-7N	10
	F3-FCC20-7N	20
	F3-FCC30-7N	30
	F3-FCC50-7N	50
	F3-FCC100-7N	100
 Jacket color: black	F5-FCC10-7N	10
	F5-FCC20-7N	20
	F5-FCC30-7N	30
	F5-FCC50-7N	50
	F5-FCC100-7N	100

- Equipped with slim and lightweight cable.
- FCC100-7N is approx. 5 kg lighter than typical 100m HFO camera cable as FCC100N.
- Heat shrink tubes help in labeling.
- 7-color connector rings included.

Note: The power transmission distance of FCC**-7N is approx. half of that of the FCC**N.

* TAJIMI compatible type (Canare OC series) is also available. Please contact us for more information.




FCF7A



FCM7A



Color Rings



FCC**-7N



F5-FCC10-7N

HFO Camera Cables

Tough & Flexible HFO Camera Cable

NEW

Thermoplastic polyurethane type jacket offers amazing flexibility and superior mechanical properties; Crush Resistance, Impact Resistance and Cyclic Flexing exceed that of MIL.

Type	Model	Sales Units (m)	Nom. O.D. (mm)	Weight kg/100m	Outer Jacket	Overall Shield	Tension Tolerance (N)	Strength Member O.D.	Min. Bend Radius	Temp. Range (deg C)	Channel Unit		
											Fiber	Aux. (Power)	Signal (Control)
	LF-2SM9T	Call	9.2	9.8	TPU + PVC	N/A	1500	1.8 mm + Tensile strength fiber	Equal to Nom. O.D.	-40 to +75	2 x SM 9/125 (low-water-peak) Unit O.D. 0.9 mm	4 x 20 AWG 102 / 0.08A Unit O.D. 1.75 mm	2 x 25 AWG 24 / 0.08A Unit O.D. 1.2 mm
Jacket color : black													
	LF-2SM7T	Call	7.1	5.3	TPU + PVC	N/A	1000	0.63 mm + Tensile strength fiber	Equal to Nom. O.D.	-40 to +75	2 x SM 9/125 (low-water-peak) Unit O.D. 1.7 mm	2 x 23 AWG 60 / 0.08A Unit O.D. 1.4 mm	2 x 26 AWG 30 / 0.08A Unit O.D. 1.1 mm
Jacket color : black													

LF-2SM9T

- Heavy-duty yet Flexible.
- Ideal for remote broadcast applications.
- Minimum bend radius: 9.2 mm.

LF-2SM7T


- Flexible, Slim, Lightweight, and moreover, Heavy-duty.
- Ideal for short-distance remote broadcast applications of up to 200 meters.
- O.D. 7.1mm and weighing only 5.3 kg/100 m, it's so easy to carry around.
- Minimum bend radius: 7.1 mm.
- Fiber units include tensile strength fiber.

Note: The power supply distance of LF-2SM7T is shorter than other HFO camera cables. (approx. 30% of LF-2SM9N)

LF-2SM7T requires a special technique during a connector assembly, so you can buy the cable assemblies shown below.

LF-2SM7T cannot be assembled with TAJIMI type connector including Canare OC series.

Cross Section

LF-2SM9T	LF-2SM7T
	





Key:

 	: Fiber
 	: Signal (Control)
 	: Aux (Power)
 	: Ground
	: Strength Member
#	: Tensile Strength Fiber

Key:

 	: Fiber + Tensile Strength Fiber
 	: Signal (Control)
 	: Aux (Power)
	: Ground
	: Strength Member
#	: Tensile Strength Fiber

Cable Assemblies

Type	Model	Length (m)
	FCC10-9T	10
Jacket color : black		
*Tajimi compatible type is also available.		
	FCC20-9T	20
Jacket color: black		
*Tajimi compatible type is NOT available.		
	FCC30-9T	25
	FCC50-9T	35
	FCC100-9T	50
	FCC150-9T	100
	FCC200-9T	150
	FCC10-7T	200
	FCC20-7T	10
	FCC30-7T	20
	FCC50-7T	30
	FCC100-7T	50
	FCC150-7T	100
	FCC200-7T	150
	FCC100-7T	200

- Tough & Flexible cable
- Fit for mobile applications in harsh environments.
- Heat shrink tubes help in labeling.
- 7-color connector rings included.

Note: The power transmission distance of FCC**-7T is quite shorter than typical HFO camera cables.



FCC**-7T




FCFA, FCF7A




FCMA, FCM7A



Color Rings



Wiring Diagram



Wiring Diagram

HFO Camera Cables

HFO Camera Cable Assemblies (Flanged Type)

Type	Model	Length (m)
FCFRCA Heat Shrink Tubes LF-2SM9 Heat Shrink Tubes FCMA Jacket color : black IU-FCF-SET included	FCC05A-FRCM	5
	FCC10A-FRCM	10
FCFA Heat Shrink Tubes LF-2SM9 Heat Shrink Tubes FCMRCA Jacket color : black IU-FCM-SET included	FCC05A-FMRC	5
	FCC10A-FMRC	10

* TAJIMI compatible type (OC series) is also available. Please contact Canare for more information.

- HFO camera cable with the flange for panel mounting.
- SMPTE 304M, 311M, and ARI BTA S-1005B compliant.
- Return loss: 45dB or greater ($\lambda = 1.3\mu m$).
- Insertion loss: 0.5dB or less ($\lambda = 1.3\mu m$).
- Connector body material is stainless steel.
- Color rings and insulation plates included.



Color Rings



IU-FC*-SET



FCFRCA



FCMRCA


HFO Camera Receptacle Cables

Type	Model	Length (m)
FCFRA Braid Tube 2 X SC, Nylon connector L Jacket color : black IU-FCF-SET included	FCS015A-FR	1.5
FCMRA Braid Tube 2 X SC, Nylon connector L Jacket color : black IU-FCM-SET included	FCS015A-MR	1.5

* TAJIMI compatible type (OC series) is also available. Please contact Canare for more information.

- Ideal for connecting wall terminal panels to splice enclosures, etc.
- Return loss: 45dB or greater ($\lambda = 1.3\mu m$).
- Insertion loss: 0.5dB or less ($\lambda = 1.3\mu m$).
- Connector body material is stainless steel.
- Insulation plates included.



Wiring Diagram



FCFRA



FCMRA



IU-FC*-SET

Insulation Plate

Ideal for perfect insulation between individual connector and panel.

Model	Suitable Connector
IU-FCM-SET	FCMRA, FCMRCA
IU-FCF-SET	FCFRA, FCFRCA

- Material: Bakelite (phenolic resin)
- Mounting screws included.

Extraction Tool

Extraction tool helps easy to clean Canare HFO connectors.

Model	Suitable Connector
ASPT-1	FCFA, FCF7A, FCFRA, FCFRCA

- Tool to be used to release the alignment sleeve unit when cleaning HFO connectors.

* Use the CLETOP 2.5/2.0 (100) cleaning stick to clean fiber-optic camera connectors.



ASPT-1



Quick-release

US Patent No.7241055B2
JP Patent No.4340186

Hybrid Fiber-optic Camera Connector Panels

Pre-terminated HFO camera connector panel with built-in splice enclosure box provides easy and quick installation between HD camera system and terminal panel or rack. By combining the unit and frame, HFO camera connector panel enables a variety of layouts depending on the system design.

■ COPS-F Series (SMPTE)


Model	Panel Size	HFO Connectors* (Assembly)
COPS-FF3	Wall Mount Type 3RU Height, W:197.6mm	2x FCFRA (FCS003A-FR)
COPS-FM3		2x FCMRA (FCS003A-MR)
COPS-FF2	Wall Mount Type 2RU Height, W:197.6mm	2x FCFRA (FCS003A-FR)
COPS-FM2		2x FCMRA (FCS003A-MR)
COPS3-FF3	Rack Mount Type 3RU	6x FCFRA (FCS003A-FR)
COPS3-FM3		6x FCMRA (FCS003A-MR)
COPS3-FF2	Rack Mount Type 2RU	6x FCFRA (FCS003A-FR)
COPS3-FM2		6x FCMRA (FCS003A-MR)

* Each HFO connector is pre-terminated. (length: 0.3m)

* TAJIMI compatible type (OC series) is also available. Please contact Canare for more information.



Key Features and Benefits

- Exclusive “5-directional Wiring”
- Convenient to build I/O interface between HD facilities and HD OB vans
- Variety of choice of 2RU/3RU and wall/rack mount
- Pre-terminated HFO connectors reduce installation time dramatically.
- Cost effective




5-directional Wiring
JP Patent No.4388540


■ Wiring Diagram



COPS-FF3



COPS-FF2



COPS3-FM3

Accessories:

Fiber-optic cable w/SC connector (2m), grounding cable, nylon connector, pin contact, socket contact, tie-band, fusion splice protection sleeve, splice holder, color-coded tube, mounting screw, laser warning label.


[NOTE] A separately available dedicated tool is required to assemble nylon connectors.

HFO Camera Connector Panels, Splice Enclosures


■ Individual Units and Parts

Model	Panel Height	Description
COUS-FF3	3RU	Connector Unit w/ 2x FCFRA (FCS003A-FR)
COUS-FM3	3RU	Connector Unit w/ 2x FCMRA (FCS003A-MR)
COUS-FF2	2RU	Connector Unit w/ 2x FCFRA (FCS003A-FR)
COUS-FM2	2RU	Connector Unit w/ 2x FCMRA (FCS003A-MR)
COU-BP3	3RU	Blank Panel
COU-BP2	2RU	Blank Panel
COF-13	3RU	Frame for 1 Unit
COF-12	2RU	Frame for 1 Unit
COF-33	3RU	Frame for 3 Unit
COF-32	2RU	Frame for 3 Unit

* Each HFO connector is pre-terminated. (length: 0.3m)
* TAJIMI compatible type (OC series) is also available. Please contact Canare for more information.



<Example of Use>



Hybrid Fiber-optic Splice Enclosures



The fiber-optic splice enclosure was designed specifically for use with hybrid fiber-optic camera cables. The enclosure is used to protect fusion splice connection parts after installation.

Model	No. of cables	Fusion splice tray No.	Adapter	
			SC	Nylon connector
FCE-2	2	1	4	2
FCE-4	4	2	8	4
FCE-6	6	3	12	6

- The enclosure is designed specifically for the hybrid fiber-optic camera cable (LF-2SM9), making installation and operation very easy.
- The enclosure can be installed on walls or placed flat. Mounting bracket (connector protection cover) can be detached from the box when installing in limited space.
- The enclosure is designed with two configurations, the top-bottom split design (FCE-2, FCE-4) and the removable panel design (FCE-6). Both designs enable easy installation of cables.
- The connection with hybrid fiber-optic receptacle cable is done by use of connectors, thus enabling easy interchanging of lines after installation.
- The tension member is insulated from the chassis.


Note :
The following special tools are required for installing the nylon connectors.
Models: AMP91529-1 (26 to 22 AWG) and AMP91536-1 (20 to 16 AWG)

■ Wiring Diagram (Canare standard)



FCE-2

Accessories:
Fiber-optic cable w/SC connector (2m), splice holder, fusion splice protection sleeve, nylon connector, pin contact, socket contact, tie band, grounding cable, color-coded tube.



HFO Camera Cable Checkers

Hybrid Fiber-Optic Camera Cable Checker

Canare Cable Checker allows fast, easy confirmation of HFO cables in the field. No heavy equipment to drag around. The compact design features a backlight digital display to measure optic loss/power and electrical continuity. Small and light, Canare Cable Checker helps make mobile installations smooth, secure and constant.

Kit Model	Individual Model	
	Measuring Unit	Loop-back Unit
FCT-FCKIT	FCT-FC	FCT-FCLB

* TAJIMI compatible type (OC series) is also available. Please contact Canare for more information.

Key Features and Benefits

- Compact, hand-held design
- Measured optical loss and power in addition to electrical signals
- 2x AA, 20 hours battery life
- The kit includes a storage case, carrying cases, AA Batteries, and cleaning sticks

Specifications

Kit Model	FCT-FCKIT
Connector	SMPTE/ARIB (Canare FC Series)
LD	FP-LD
Wavelength	1310nm
Output Power	-2.5dBm
Sensitivity	-24 to -2dBm
Maximum Length	3.5km (Canare LF-2SM9N)
Optic Lines	Two Lines: Power and Loss
Copper Lines	Power, Control, and Shield: Connectability
Battery/Life	2pcs of AA/ Approx. 20hours
Operating Temperature	-10 to 60°C
Dimensions	FCT-FC: 46x 46x 150mm FCT-FCLB: 46x 46x 65mm
Weight	FCT-FC: 380g FCT-FCLB: 170g
Accessories	Storage case, carrying cases, AA Batteries, and cleaning sticks


CE, FCC, FDA registered
US Patent No.7113678
JP Patent No.4155979



Carrying Cases



Storage Case




Technical Note

Maintaining Hybrid Fiber-Optic Camera Connectors

The connector sections to be cleaned are the key parts, including the tips and sides of ferrules, the interior walls of alignment sleeves and the interior and exterior of connector shells. Note that scratches and particles of foreign matter on the tip of the ferrule can have a disabling effect on fiber-optic transmission. The following procedures should be used when cleaning hybrid fiber-optic camera connectors.

- For Plugs, the interior surfaces of alignment sleeves and the tips of ferrules are to be cleaned with the non-alcohol treated cleaning stick using a gentle stroking action. Canare FCFA and FCFRA enhance easy cleaning procedure for its innovative alignment sleeve and insulator detachable design.

US Patent: No.7241055B2, JP Patent: No.4340186



- For Jacks, it is important to clean both the tips and sides of the completely protruding ferrules with the cleaning stick.
- Both the male and female connector shells tend to attract dust and metal particles, so it is important to clean both the insides and outsides using cotton gauze or similar material.



Before cleaning



After cleaning

Cleaning Stick

Model: CLETOP 2.5/2.0

- Compact and disposable
- Allows cleaning both the tips and sides of ferrules
- Manufactured by NTT-AT

Cleaning stick
CLETOP 2.5/2.0

IBC Brand Cleaner M-20
Model: 14347 CLEANER

- Easy “one-push” cleaner
- Allows cleaning the tips of ferrules without removing alignment sleeve
- Manufactured by US Conec


IBC Brand Cleaner M-20
14347 CLEANER



Fiber-optic Cables

Tactical Fiber-optic Cable

Particularly rugged multichannel fiber-optic cable designed for mobile applications.


Type	Model	No. of ch.	Sales Units (m)	Nom. O.D. (mm)	Weight kg/100m	Tension Tolerance (N)	Strength Member	Min. Bend Radius	Temp. Range (deg C)	Fiber-optic Unit		
										Fiber	Attenuation	Unit O.D.
	LF-SM2T-4C	4	100 200 500	7.8	4.9	1400	Aramid yarn	Equal to Nom. O.D.	-55 to +85	SM 9/125 (low-water-peak)	1.6 dB/km @1310 nm	2.0 mm including aramid yarn

Jacket: TPU


LF-SM2T-4C

- Heavy-duty and high flexibility
 - * Crush resistance: 2,000 N/cm
 - * Impact resistance: 300 impacts
 - * Cycle flexing: 20,000 cycles
- Single-mode
- Color-coded breakout type unit
- Thermoplastic polyurethane jacket
- Aramid yarn strength member
- 4-channel cable best suited for Quad-link 3G-SDI signals.

Cable Assemblies


Type	Model	Length (m)
	4FS50T-SS	50
	4FS100T-SS	100
	4FS150T-SS	150
	4FS200T-SS	200
	4FS50T-LS	50
	4FS100T-LS	100
	4FS150T-LS	150
	4FS200T-LS	200
	4FS50T-ST	50
	4FS100T-ST	100
	4FS150T-ST	150
	4FS200T-ST	200

Single-mode Fiber-optic Cables (Multichannel)

Type	Model	No. of Ch.	Sales Units (m)	Nom. O.D. (mm)	Weight kg/100m	Outer Jacket	Tension Tolerance (N)	Min. Bend Radius	Temp. Range (deg C)	Fiber-optic Unit		
										Fiber	Attenuation	Unit O.D.
	LF-SM2-2C	2	Call	7.4	5.4	PVC	290	10 x Nom. O.D.	-40 to +75	SM 9/125 + Aramid yarn + PVC jacket	0.5 dB/km @1310nm	2.0 mm including aramid yarn
	LF-SM2-4C	4		7.4	5.5		290					
	LF-SM2-6C	6		9.0	7.3		300					
	LF-SM2-8C	8		10.0	10.4		780					
	LF-SM2-12C	12		12.8	14.2		780					
	LF-SM2-16C	16		14.7	16.3		780					
	LF-SM2-24C	24		15.0	18.3		780					

- Smooth PVC Jacket
- Including a central strength member and a rip cord.


Cross Section



Key: F : Fiber + Aramid Yarn
: Aramid Yarn

Fiber-optic Assemblies (Single/Dual Channel)

■ Single mode

Type	Model	Length (m)
SC - SC 	FS3C002-S	0.2
	FS3C003-S	0.3
	FS3C005-S	0.5
	FS3C01-S	1.0
	FS3C015-S	1.5
	FS3C02-S	2.0
	FS3C03-S	3.0
	FS3C05-S	5.0
	FS3C10-S	10.0
	FS3C15-S	15.0
	FS3C20-S	20.0
	FS3C30-S	30.0
Jacket color: yellow		
SC - SC 	2FSZ3S02-S	2.0
	2FSZ3S03-S	3.0
	2FSZ3S05-S	5.0
Jacket color: yellow		


■ Multi mode

Type	Model	Length (m)
SC - SC GI50/125 	FG53C02-S	2.0
	FG53C03-S	3.0
	FG53C05-S	5.0
	2FG5Z3S02-S	2.0
	2FG5Z3S03-S	3.0
	2FG5Z3S05-S	5.0
	FG63C02-S	2.0
	FG63C03-S	3.0
	FG63C05-S	5.0
	2FG6Z3S02-S	2.0
	2FG6Z3S03-S	3.0
	2FG6Z3S05-S	5.0
Jacket color: orange		

- Flexible cable with reliable bellcore boots
- UPC polishing; Return loss $\geq 50\text{dB}$ for single mode and $\geq 25\text{dB}$ for multi mode
- Transmission loss 0.5dB at $\lambda = 1.31\mu\text{m}$ and 0.4dB at $\lambda = 1.55\mu\text{m}$ for single mode
- Transmission loss 3.0dB at $\lambda = 0.85\mu\text{m}$ and 1.0dB at $\lambda = 1.30\mu\text{m}$ for multi mode

Fiber-optic Assemblies (Multichannel Fantails)


■ Single mode

Type	Channel	Model	Length (m)	Fiber Optic Cable		
				Part Number	Unit O.D. (mm)	Nom. O.D. (mm)
SC - SC 	2	2FS10-S	10	LF-SM2-2C		7.4
		2FS20-S	20			
		2FS50-S	50			
	4	4FS10-S	10	LF-SM2-4C		
		4FS20-S	20			
		4FS50-S	50			
	6	6FS10-S	10	LF-SM2-6C		9.0
		6FS20-S	20			
		6FS50-S	50			
	8	8FS10-S	10	LF-SM2-8C		10.0
		8FS20-S	20			
		8FS50-S	50			
	12	12FS10-S	10	LF-SM2-12C		12.8
		12FS20-S	20			
		12FS50-S	50			
	16	16FS10-S	10	LF-SM2-16C		14.7
		16FS20-S	20			
		16FS50-S	50			
	24	24FS10-S	10	LF-SM2-24C		15.3
		24FS20-S	20			
		24FS50-S	50			
Jacket color: yellow						

- Flexible cable with reliable bellcore boots
- Adjustable fantail length with peel-off string

- UPC polishing; Return loss $\geq 50\text{dB}$ for single mode
- Transmission loss 0.5dB at $\lambda = 1.31\mu\text{m}$ and 0.4dB at $\lambda = 1.55\mu\text{m}$

6-channel Fiber-optic Snakes

Type	Model	Length (m)
	OM6C10	10
	OM6C20	20
	OM6C25	25
	OM6C35	35
	OM6C50	50
	OM6C100	100
	OM6C150	150
	OM6C200	200

Jacket color : black



OM6PA



OM6JA



- Ruggedized multichannel fiber-optic assemblies with robust 6-fiber connector
- Single-mode, ITU-T G.657.A2 low bending loss and low water-peak fiber
- Abrasion-resistance cable jacket
- Tensile strength: 700 N or less
- Return loss: 45 dB or greater ($\lambda = 1.3 \mu\text{m}$)
- Insertion loss: 0.5 dB or greater ($\lambda = 1.3 \mu\text{m}$)
- 7-color connector rings included.
- Blue dust cap makes it easier to distinguish OM6 from HFO camera connectors that have similar appearance.





* Canare OM6 connectors are NOT compatible with other multichannel/hybrid fiber-optic connectors.


* IBC brand "one-push" cleaner M-20 is highly recommended for cleaning OM6 connectors.
(see page 17, model: 14347 CLEANER)



Color Rings

6-channel Fiber-optic Fantails

Type	Model	Length (m)
	OM6S003-PR	0.3
Jacket color : yellow IU-FCM-SET included		
	OM6S015-PR	1.5
Jacket color : yellow IU-FCM-SET included		
	OM6S003-JR	0.3
Jacket color : yellow IU-FCM-SET included		
	OM6S015-JR	1.5
Jacket color : yellow IU-FCM-SET included		



- OM6 receptacle with 6 SC single-mode fiber cord (2.0mm).
 - Return loss: 45 dB or greater ($\lambda = 1.3 \mu\text{m}$)
 - Insertion loss: 0.5 dB or greater ($\lambda = 1.3 \mu\text{m}$)
 - Blue dust cap makes it easier to distinguish OM6 from HFO camera connectors that have similar appearance.
- * Canare OM6 connectors are NOT compatible with other multichannel/hybrid fiber-optic connectors.
- * IBC brand "one-push" cleaner M-20 is highly recommended for cleaning OM6 connectors.
(see page 17, model: 14347 CLEANER)

3G Transmission Design

3G-SDI Popularity

3G-SDI (3Gb/s Signal/Data Serial Interface) is a transmission format (1080p) that provides twice the data transmission capacity (bandwidth) of today's widely used HD-SDI (1080i), and its use has seen rapid expansion in recent years. The data format was standardized as SMPTE 424M in 2006, and was revised as the SMPTE ST 424 Standard in 2012, including a change in typical cable loss recommendations (from 20dB to 30dB).

Dual-link 3G-SDI and Quad-link 3G-SDI provide reasonable solutions for meeting the production requirements of HDR HDTV, 2K/4K D-Cinema and UHDTV-1.

Signal Attenuation in 3G Transmission Lines

In order to keep overall transmission line attenuation below the 30dB loss budget, it is necessary to calculate attenuation amounts individually for each section in the system. In the system shown below, the losses occurring within each transmission line have been calculated and entered into a level diagram. From this it is possible to see the differences in transmission distances possible with HD-SDI and 3G-SDI when using a coaxial cable (L-7CHD). If this shows that attenuation will surpass the specified loss budget, then it will be necessary to change to cables with less attenuation,

SMPTE Requirements


Format	HD-SDI SMPTE ST 292	3G-SDI SMPTE ST 424	12G-SDI SMPTE ST 2082-1
Bit Rate	1.485 Gb/s	2.97 Gb/s	11.88 Gb/s
Impedance (Z_0)		75Ω	
Cable Loss	20 dB @ 750 MHz (@ 742.5 MHz)	30 dB @ 1.5 GHz (@ 1.485 GHz)	40 dB @ 6 GHz (@ 5.94 GHz)
Return Loss	5 M–1.5 GHz 1.5–3 GHz 3–6 GHz 6–12 GHz	15 dB - - -	15 dB 10 dB - 4 dB

or to revise the circuit and/or equipment layout to compensate. It is also recommended that these calculations include a 2–3dB design margin.


12G-SDI

In 2015, SMPTE released ST 2082-1 12G-SDI, a standard for UHD-SDI (4K 2160p), as the next-generation of the single-link SDI format. 12G-SDI makes possible transmission of as much as eight times the data volume of HD-SDI (2K 1080i), and as much as four times the data volume of 3G-SDI (2K 1080p) over a single coaxial cable. At the same time, high performance is also required of both cables and connectors (refer to the table above), and Canare has already commenced efforts to meet these requirements.

<System Example>



<Level Diagram>



System Attenuation

Format	Connector/Cable	① L-2.5CHD	② DVJB-W	③ L-4.5CHD	④ BCJ-JR	⑤ L-7CHD	⑥ BCJ-JR	⑦ L-4.5CHD	⑧ BCJ-JR	⑨ L-2.5CHD	Sub Total	Margin	Total Amount
HD-SDI	m or pcs	2	1	6	1	125	1	6	1	2	17.6 dB	2.4 dB	20.0 dB
	Loss (dB/m)	0.3	0.9	0.2	0.2	0.1	0.2	0.2	0.2	0.3			
	Loss (total) (dB)	0.6	0.9	1.2	0.2	12.5	0.2	1.2	0.2	0.6			
3G-SDI	m or pcs	2	1	6	1	105	1	6	1	2	27.7 dB	2.3 dB	30.0 dB
	Loss (dB/m)	0.4	0.9	0.3	0.2	0.2	0.2	0.3	0.2	0.4			
	Loss (total) (dB)	0.8	0.9	1.8	0.2	21.0	0.2	1.8	0.2	0.8			


75Ω Active BNC Receptacles

Small BNC connector incorporates either a cable equalizer or a cable driver. Active BNC makes innovation in your 3G-SDI PC board layout.

Model	Description	Built-in IC
BCA-TL	TX, Right Angle	Cable Driver
BCA-RL	RX, Right Angle	Cable Equalizer
BCA-TS	TX, Straight	Cable Driver
BCA-RS	RX, Straight	Cable Equalizer

• Standard package (5pcs)

- BNC connector integrated with a cable equalizer or a cable driver, and yet keep the connector size to a minimum.
- Supports 3G-SDI, HD-SDI, SD-SDI and DVB-ASI
- Offers an excellent return loss performance without designing 75 ohm I/O block
- Simplifies PCB design process dramatically and will reduce entire development cost
- PCB space saving and help to downsize devices
- Easy to distinguish TX from RX by color-coded insulation





Specifications

Model	TX BCA-TL, BCA-TS	RX BCA-RL, BCA-RS
Supply Voltage	DC 3.3V	
Current Consumption	50mA	70mA
Operating Temperature	-25°C to +85°C	
Output Signal Amplitude	800mVpp	—
Equalizing Cable Length	3G-SDI 120m w/L-5CFB	
Compliant	SMPTE 424M, 292M, 259M, BTA S-004C, EN50083-9, RoHS	
Weight	Approx. 9.0g	

US Patent No.: 8251721 B2

JP Patent No.: 4837715



	BCA-TL	BCA-RL	BCA-TS	BCA-RS
Panel Hole Dim.				
PCB Hole Dim.				

Note: The darker shaded area will come into contact with the connector body.

75Ω DIN Connectors

75Ω DIN1.0/2.3 Connectors

Mini coax connectors IEC61169-29 and DIN 47 297 compatible.

■ DCP-C Series (Crimp Plugs)

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set	VSWR 1.2@ 3GHz
	Canare	Others					
DCP-C25HD	L-2.5CHD, L-2.5CHLT	1855A, VDM230	BN1148	BN7136	—	TCD-D253F	
DCP-C3F	L-3CFB	—	BN1148	BN7003A	—	TCD-D253F	
DCP-C4F	L-4CHD, L-4CFB	1505A, VPM2000	BN1158	BN7015A	—	TCD-D534F	
DCP-C53	L-4.5CHD	1694A, VSD2001	BN1157	BN7138	—	TCD-D534F	

• Standard package (20pcs/100pcs)


- Our unique ball-locking mechanism offers smooth and reliable mating.
- Canare crimp design ensures quick and reliable installation.
- Elongated body design enables stable finger grip.
- Return loss: 20 dB or greater up to 3GHz
- Extraction tool : BET-DIN (see page 38)

US Patent No.: 8764473 B2


Be sure to use Canare crimping tool for installing connectors on cables




DCP-C25HD




Rerun Loss for DCP-C25HD




DCJ-LR




DCJ-LR/1




DCJ-FEM



DCJ-JR



BCJ-DCJ



BCP-DCJ



NDT-DIN

■ Adapters

VSWR 1.1 @ 3GHz


Model	Description	Panel Mount	Nut Driver Bit
DCJ-JR	Jack to Jack	Yes	NDT-DIN
BCJ-DCJ	BNC Jack to DIN1.0/2.3 Jack	Yes	N/A
BCP-DCJ	BNC Plug to DIN Jack	No	N/A

• Standard package (20 pcs)


- Return loss: 26 dB or greater up to 3 GHz.

Note: Nut driver bit NDT-DIN is required for DCJ-JR

<Panel Hole Dim.>



<PCB Hole Dim.>



■ Nut Driver Bit

Model	Description
NDT-DIN	6.35mm (1/4") hex shank

75Ω Multichannel Coax Connectors

4K-DIN Coax Connectors


Canare unique “4K-DIN” allows you to connect or disconnect 4 of 3G-SDI signals in one easy step.

Crimp Plugs


Model	Suitable Cable	Die Set	Description
MDM-V4C25HW	V4-2.5CHW	TCD-D253F	Male
MDF-V4C25HW	V4-2.5CHW	TCD-D253F	Female



MDM-V4C25HW



MDF-V4C25HW



MDF-V4JRU


Flush-mount Receptacle

Model	Description
MDF-V4JRU	Jack to Jack


- 75Ω 4-channel coax connector with push-pull locking mechanism.
- Compact, solid, and lightweight nylon resin (PA 66) body
- Return loss: 20 dB @ 3 GHz
- MDF-V4JRU accepts MDM-V4C25HW and also DIN 1.0/2.3 plugs.

* Replacement crimp units also available:
DCP-C25HW-ML for MDM
DCJ-C25HW-ML for MDF

<Connection Example>



Be sure to use the Canare crimping tool for installing connectors on cables.



75Ω Multi-pin Coax Connectors

Handles five 75Ω coaxial connections.

Model	Suitable Cable	Die Set	Description
MCM-V5C3	V5-3C	TCD-35CA	Plug
MCF-V5C3	V5-3C, L-3C2V, L-3C2VS	TCD-35CA	Receptacle

Model	Description
DCM01	Dust Cap for MCM-V5C3
DCF01	Dust Cap for MCF-V5C3



- 1.2 or less VSWR up to 1.5GHz.
- Crimp system ensures quick and reliable installation.

* Replacement unit also available. MCM-V5C3: BN9078A MCF-V5C3: BN9079B

Be sure to use the Canare crimping tool for installing connectors on cables.



MCM-V5C3



Panel Hole Dimensions
(Mounting screw M3 x 4 pcs)



Replacement Unit BN9078A



Replacement Unit BN9079B

75Ω BNC Connectors

75Ω BNC Crimp Plugs

Canare True 75 Ω BNC Connectors has been widely used in the world with quick and reliable crimp design, and outstanding performance. The high-end model BCP-B series are specially designed for particular coax cables, and minimize return loss at 3 GHz.

■ BCP-B Series


VSWR 1.1@ 3GHz

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Others				
BCP-B25HD	L-2.5CHD, L-2.5CHLT	VDM230	B11015E	BN7129	CB02	TCD-35CA
BCP-B25HW	V4-2.5CHW	—	B11015E	BN7143	CB02	TCD-35CA
BCP-B26	—	1855A, 1855P	B11014E	BN7029C	CB02	TCD-35CA
BCP-B28	—	1855ENH, HD PRO 0.6/2.8 AF	B11015E	BN7052A	CB02	TCD-35CA
BCP-B3F	L-3CFB, V*-3CFB	—	B11015E	BN7003A	CB03	TCD-35CA
BCP-B31F	L-3CFW, V*-3CFW	—	B11015E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-B4F	L-4CHD, L-4CFB, V*-4CFB	1505A, 1505ANH, VPM2000, HD PRO 0.8/3.7 AF	B11016E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-B45HW	L-4.5CHWS	1694F	B11020D	BN7016	CB05A	TCD-35CA
BCP-B53	L-4.5CHD	1694A	B11020D	BN7046	CB05A	TCD-35CA
BCP-B56	—	HD PRO 1.0/4.8 AF	B11020D	BN7046	CB05A	TCD-35CA
BCP-B5F	L-5CFB, V*-5CFB	—	B11020D	B75004A	CB05A	TCD-5CF, TCD-55FA
BCP-B51F	L-5CFW, V*-5CFW	—	B11020D	B75004A	CB05A	TCD-5CF, TCD-55FA

• Standard package (20pcs/100pcs)



BCP-B5F



Return loss for BCP-B53

■ BCP-A Series


VSWR 1.1 @ 2GHz, VSWR 1.2 @ 3GHz(*1)

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Others				
BCP-A25	L-2.5C2V	—	BN1018A	BN7029C	CB02	TCD-35CA
BCP-A25F	L-2.5CFB	1855A, 8218, 1417B, 1418B	B11014E	BN7029C	CB02	TCD-35CA
BCP-A3	L-3C2VS, L-3C2V, V*-3C	—	B11014E	BN7003A	CB03	TCD-35CA
BCP-A31	L-3C2W	—	B11014E	BN7011	CB04	TCD-31C
BCP-A32	—	1506A, 1824A, 1825A, 1826A, 643948	B11016E	BN7026A	CB03	TCD-35CA
BCP-A3F	L-3CFB, V*-3CFB	—	B11015E	BN7003A	CB03	TCD-35CA
BCP-A4	LV-61S	8241, 8279, RG-59B/U	B11015E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-A42	—	1505F	B11016E	BN7011	CB04	TCD-31C
BCP-A4F	L-4CHD, L-4CFB, V*-4CFB	1505A, 1505ANH, 8212, 8241F, 9167, 9259, 9659, VPM2000, HD PRO 0.8/3.7 AF	B11016E	BN7015A	CB04	TCD-4CA, TCD-451CA
BCP-A5	L-5C2VS, L-5C2V, V*-5C	—	B11016E	BN7016	CB05A	TCD-35CA
BCP-A52	L-5C2W	—	B11016E	BN7014	—	TCD-451CA
BCP-A55	—	1695A, VSD2001TS	B11020D	BN7045A	CB04	TCD-35CA
BCP-A5F	L-5CFB, V*-5CFB	—	B11020D	B75004A	CB05A	TCD-35CA
BCP-A77	LV-77S	8281F	B11016E	B75004A	CB05A	TCD-5CF-TCD-55FA
BCP-VA3	V*-3C	—	B11014E	BN7052A	CB03	TCD-35CA
BCP-VA5	V*-5C	—	B11016E	BN7045A	CB05A	TCD-35CA

• Standard package (20pcs/100pcs).

*1: Excluding BCP-A25, BCP-A25F, BCP-A4

Note: Suitable die set for BCP-A5F is TCD-35CA; do not use TCD-5CF/TCD-55FA for BCP-A5F.



Return loss for BCP-A3



BCP-A3

■ BCP-C Series

VSWR 1.1 @ 2GHz (*2)


Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Others				
BCP-C1	L-1.5C2VS, V*-1.5C	83264, 83267	Solder	BN7022	CB01	TCD-1DB
BCP-C5HD	L-5CHD	—	BN1139	B75004A	CB05A	TCD-5HD
BCP-C6HD	L-6CHD	—	BN1083A	BN7074A	—	TCD-67HD
BCP-C71A	—	7731A, 9064, 9292, 1617A, 9011	BN1043A	BN7021A	—	TCD-7CA
BCP-C7FA	L-7CFB	—	BN1012B	BN7021A	—	TCD-7CA
BCP-C7HD	L-7CHD	—	BN1082A	BN7021A	—	TCD-67HD

• Standard package (20pcs/100pcs).

*2: Excluding BCP-C1

- Canare crimp design ensures quick and reliable installation.
- Gold plated “snap locks” center pin and beryllium copper outer contact.
- Elongated body design enables stable finger grip (excluding BCP-C1).
- Position mark on the BCP-B/A series body makes it easier to check if the connector is locked.

Note: Die set for BCP-A5F is TCD-35CA



Return loss for BCP-C6HD

Be sure to use the Canare crimping tool for installing connectors on cables.

75Ω BNC Connectors

75 Ω BNC Crimp Plugs (Right Angle Type)

■ BCP-LC Series

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set	VSWR 1.1@ 2GHz
	Canare	Others					
BCP-LC3	L-3C2VS, L-3C2V, V*-3C	—	B11014E	BN7003A	—	TCD-35CA	
BCP-LC3F	L-3CFB, V*-3CFB	—	B11015E	BN7003A	—	TCD-35CA	
BCP-LC5	L-5C2VS, L-5C2V, V*-5C	—	B11016E	BN7016	—	TCD-35CA	
BCP-LC5F	L-5CFB, V*-5CFB	—	B11020D	B75004A	—	TCD-5CF, TCD-55FA	

- Standard package (20pcs)

- Canare crimp design ensures quick and reliable installation.
- Gold plated “snap locks” center pin and beryllium copper outer contact.

Be sure to use the Canare crimping tool for installing connectors on cables.



BCP-LC3

75 Ω Slim BNC Crimp Plugs



■ MBCP-C Series

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set	VSWR 1.1@ 1.5GHz
	Canare	Others					
MBCP-C25F	L-2.5CFB	1855A, 8218, 1417B, 1418B	B11014E	BN7029C	—	TCD-35CA	
MBCP-C3F	L-3CFB, V*-3CFB	—	B11015E	BN7003A	CB24	TCD-35CA	
MBCP-C4	LV-61S	8241, 8279, RG-59B/U	B11015E	BN7015A	CB25	TCD-4CA, TCD-451CA	
MBCP-C4F	L-4CFB, V*-4CFB	1505A, 1505ANH, 8212, 8241F, 9167, 9259	B11016E	BN7015A	CB25	TCD-4CA, TCD-451CA	
MBCP-C53	L-4.5CHD	1694A, 9066, 9116, 9118, 9248	B11020D	BN7046	CB26	TCD-35CA	
MBCP-C5F	L-5CFB, V*-5CFB	—	B11020D	B75004A	CB26	TCD-5CF, TCD-55FA	


- Standard package (20pcs/100pcs)

- Slim design: OD 12 mm
- Compatible with 75 Ω BNC receptacles.
- Canare crimp design ensures quick and reliable installation.
- Gold plated “snap locks” center pin and beryllium copper outer contact.

Be sure to use Canare crimping tool for installing connectors on cables.



MBCP-C3F



Return loss for MBCP-C3F

Technical Note

Voltage Standing-wave Ratio (VSWR) and Return Loss

Terminating the receiving end of a limited length coaxial cable using a resistance value not equal to its characteristic impedance creates a reflected wave that returns back down the cable to the sending end. The result is interference developing between the travelling wave and the return wave which results in a standing wave that causes voltage levels to fluctuate. The degree to which terminating resistance matches the characteristic impedance is indicated using the VSWR or voltage standing-wave ratio standard shown in Fig. 1. Going hand in hand with the VSWR ratio is the return loss factor which measures the size of the reflected wave current in relation to the travelling wave current. (See Fig. 2)




Fig. 1 Voltage Distribution Over Coaxial Cable

VSWR	Return Loss (dB)
2	9.5
1.5	14
1.2	20
1.1	26
1.05	32
1.02	40
1.01	46.1

Fig. 2 VSWR to Return Loss Conversion Table

Connectors

75Ω BNC Connectors

75Ω BNC Solder Plugs

■ BCP-H Series

VSWR 1.1@ 1GHz


Model	Suitable Cable	
	Canare	Others
BCP-H3B	L-3C2VS, L-3C2V, L-3CFB	—
BCP-H31F	L-3CFW	—
BCP-H45HW	L-4.5CHWS	1694F
BCP-H5B	L-5C2VS, L-5C2V, L-5CFB	—
BCP-H51F	L-5CFW, L-5CFB	—
BCP-H5/1	L-3C2VS, L-3C2V, L-3CFB L-5C2VS, L-5C2V, L-5CFB	—

• Standard package (20pcs)

- The tubular (ferrule) section is silver plated to make soldering easier.
- Cable stripper TS100E can be used. (Excluding BCP-H31F, BCP-H51F)




BCP-H3B




Return loss for BCP-H3B



BCJ-C4



BCJ-C4



BCJ-J



BCJ-J




Fig.1 Return loss for BCJ-J



BCP-TB




Fig.2 Return loss for BCP-TB and previous model BCP-TA

75Ω BNC Extension Adapter

Model	Description
BCJ-J	Jack to Jack

• Standard package (20pcs/100pcs)

- Beryllium copper is used on the center contact for its superior spring characteristics.
- 1.1 or less VSWR up to 2GHz. <Fig. 1>

75Ω BNC Termination Plugs

Designed for true 75Ω termination

Model	Description
BCP-TB	True 75Ω Termination
BCP-TB-CH	True 75Ω Termination with String

• Standard package (20pcs/100pcs)

- Includes 1/4 watt resistance.
- 1.1 or less VSWR up to 3GHz. <Fig. 2>

Connector Boots

■ CBOx Series


Our best selling connector boots for Canare BNC, TNC crimp plugs.

Model	Colors Available	BCP-xx	BP-xx	TNP-xx
CBO1	BLK, BLU, GRN, RED, YEL, WHT	C1		
CBO2		B25HD, B25HW, B26, B28, A25, A25F		
CBO3	BLK, BLU, BRN, GRN, GRY,	B3F, B31F, A3, A32, A3F, VA3	C3, C4	C3, C4
CBO4	ORN, PPL, RED, YEL, WHT	B4F, A31, A4, A42, A4F, A55	C31	C31
CBO5A		B53, B56, B5F, B51F, A5, A5F, A77, VA5, C5HD	C5, C5FA	C5


■ CB2x Series

Thinner type of CBOx series. Best fit for Canare Slim BNC, RCA, and F crimp plugs.


Model	Colors Available	Typical Connectors		
		MBCP-xx	RCAP-xx	FP-xx
CB24		C3F	C3A, C3F	C3, C3F
CB25	BLK, BLU, GRN, RED, YEL, WHT	C4, C4F	C3GS, C4A, C4F	C31, C4, C4F
CB26		C5F	C53, C5A, C5F	C5, C53A, C5F



CB03, CB04, CB05A



CB01, CB02



CB24, CB25, CB26

75Ω BNC Connectors


75Ω BNC Receptacles

BNC Receptacles emphasizing true 75Ω impedance.

Standoff Receptacles

Model	Description	Suitable Cable	Die Set
BCJ-R	Jack to Solder	—	—
BCJ-R/1	Jack to Solder w/Ground Lug	—	—
BCJ-FC1	Panel Jack (1/2")	1.5C-2V	TCD-1DB
BCJ-FC1-7/16	Panel Jack (7/16")	—	—
BCJ-JR	Jack to Jack	—	—

• Standard package (20pcs/100pcs)





Flush-mount Receptacles

Model	Description	Flange Type	Suitable Cable	Die Set
BCJ-RU	Jack to Solder	ITT XLR-F77	—	—
BCJ-RUD		Neutrik D	1.5C-2V	TCD-1DB
BCJ-RUDB		Neutrik D (Black)	—	—
BCJ-RUC1	Panel Jack	ITT XLR-F77	—	—
BCJ-JRU	Jack to Jack	ITT XLR-F77	—	—
BCJ-JRUD		Neutrik D	—	—
BCJ-JRUDB		Neutrik D (Black)	—	—

• Standard package : 20pcs

- VSWR 1.1 @ 2GHz (Panel Jack: 1.1 @ 1GHz)
- Gold plated beryllium copper center contact
- Flush-mount receptacle prevents damage on the jack.



Panel Hole Dimensions

BCJ-R	★BCJ-R/1 ★BCJ-JR	BCJ-FC1	★BCJ-FC1-7/16	BCJ-RUC1 BCJ-RU BCJ-JRU	BCJ-RUD BCJ-RUDB BCJ-JRUD BCJ-JRUDB

* Indicate connectors that accept insulation bushing. Mounting hole for insulation bushing IU 7/16 should be adopted.

Insulation Bushing

Model	Description
IU-7/16	ABS plastic

• Standard package: 20pcs

- Insulate a connector from a panel.
- 5 colors available (white, black, blue, green, red, or yellow)

Note: Please remove washers from a connector before using IU-7/16.


Mountable panel thickness:

1.2~1.5mm: BCJ-FPLVA, BCJ-FPLHA, BCJ-R/1

1.2~3.0mm: BCJ-FPC, BCJ-FPC02, BCJ-JR, BCJ-FPLV01




IU-7/16



Panel Hole Dimensions

ITT XLR-F77 Compatible	Neutrik D Compatible



75Ω BNC Connectors

75Ω BNC PCB Mount Receptacles (Screw Type)




■ BCJ-BP Series

Model	Description	Stud Position	Panel Mount	Standard Package
BCJ-BPLHA	Right Angle	Horizontal	Front: M.2.6 screw	20 pcs/100pcs
BCJ-BPLH2PA	Right Angle, Dual Jack			10 pcs
BCJ-BPLH3PA	Right Angle, Triple Jack			10 pcs
BCJ-BPC2P	Straight, Dual Jack	—	—	10pcs/100pcs



* Screws are not included.

Key Features and Benefits



- True 75Ω PC board mount receptacle.
- VSWR 1.1 or less up to 1.5GHz, 1.2 or less up to 3GHz.
(1.1 or less up to 1GHz, 1.2 or less up to 2.5GHz for BCJ-BPC2P.)
- Gold plated beryllium copper center contact.
- Can be fixed on the PC board with M2.6 screw for efficient soldering.
(excluding BCJ-BPC2P)
- Space-saving design allows high-density mounting.
- Eliminates wiring material and cost.





BCJ-BPLHA BCJ-BPLH2PA BCJ-BPLH3PA




BCJ-BPLHA



BCJ-BPLH2PA






BCJ-BPC2P



BCJ-BPLH3PA

Note: Any cleaning solvents cannot be used. This leads to insulation problems.

Insulation material: m-PPO (m-PPE)



Comparison with the previous model

	BCJ-BPLHA	BCJ-BPLH2PA	BCJ-BPLH3PA	BCJ-BPC2P
Panel Hole Dim.				
PCB Hole Dim.				

75Ω BNC Connectors

75Ω BNC PCB Mount Receptacles (Hex Nut Type)

■ BCJ-FP Series

Model	Description	Stud Position	Panel Mount
BCJ-FPLVA	Right Angle		
BCJ-FPLV01	Right Angle, Low-cost Model	Vertical	
BCJ-FPLV-L	Right Angle (10pcs)		Front: Hex nut and lock washer
BCJ-FPLHA	Right Angle	Horizontal	
BCJ-FPC	Straight		
BCJ-FPC02	Straight, Low-cost Model	—	

• Standard package (20pcs/100pcs)

■ BCJ-RP Series

Model	Description	Stud Position	Panel Mount
BCJ-RPLV	Right Angle	Vertical	
BCJ-RPLH	Right Angle	Horizontal	
BCJ-RPC	Straight, Through Hole Mount	—	Rear: Hex nut and lock washer
BCJ-RPC/1	Straight, Surface Mount	—	



• Standard package (20pcs/100pcs)

- VSWR 1.1 or less up to 1GHz, 1.2 or less up to 2.5GHz.
(1.1 up to 3GHz for BCJ-FPLV-L)


- Gold plated beryllium copper center contact.

Note: Any cleaning solvents cannot be used. This leads to insulation problems.


Insulation material: m-PPO (m-PPE)




BCJ-FPLV01




BCJ-FPC02




BCJ-RPC/1




BCJ-FPLVA




Return loss for BCJ-FPLVA, BCJ-RPLH




BCJ-FPLV01




Return loss for BCJ-FPLV01, BCJ-FPLV-L




BCJ-FPLV-L




Return loss for BCJ-FPC, BCJ-FPC02, BCJ-RPC



BCJ-FPC



BCJ-FPLV-L can be stacked over BCJ-FPLVA on a PCB as shown.



BCJ-FPC02


<Panel Hole Dimensions>

BCJ-FPLVA*	BCJ-FPLV01*	BCJ-FPLHA*	BCJ-FPC*	BCJ-RPC/1 BCJ-RPC BCJ-RPLV BCJ-RPLH

* BCJ-FP series accept insulation bushing IU-7/16. Mounting hole for IU-7/16 should be adopted. (See page 33)

<PC Board Hole Dimensions>

BCJ-FPLVA BCJ-FPLV01 BCJ-FPLHA	BCJ-FPLV-L	BCJ-FPC BCJ-FPC02	BCJ-RPLV BCJ-RPLH	BCJ-RPC



BCJ-RPC

Connectors

75Ω BNC, 75Ω N

BNC Dust Caps

Model	Description
BCJ-DC	Polyethylene (Black)
BCJ-DC-CH	Polyethylene (Black) with string



BCJ-DC

• Standard package (20pcs/100pcs)


- Protects unused BNC receptacles from dirt and dust.

BNC - RCA Adapter


Model	Description
BCP-RCAJ	RCA Jack (F) to BNC Plug (M)
BCJ-RCAP	BNC Jack (F) to RCA Plug (M)



BCP-RCAJ



BCJ-RCAP



• Standard package (1pc)


- Gold plated center contact
- Secure finger grip and reliable mating

75Ω N Solder Plug

Model	Suitable Cable
NCP-H8HD	L-8CHD



NCP-H8HD



• Standard package (1pc)

- Gold plating on the contact pin prevents deterioration, even after years of use.
- 1.1 or less VSWR up to 2GHz. <Fig. 3>
- Solder type

Tools required: 17mm and 21mm wrenches

Caution: The connecting section of the N connector uses a shape that conforms to the IEC169-16's 75Ω impedance standard. Note that the 50Ω N and other connectors that do not conform to this specification cannot be connected.

75Ω N to BNC Adapter

Model	Description
NCJ-BCJR	N (F) - BNC (F)



NCJ-BCJR

• Standard package (1pc)

- Beryllium copper (gold plated) is used on the center contact for its superior spring characteristics.
- 1.1 or less VSWR up to 2GHz. <Fig. 4>
- Panel mountable as well. For isolation from the panel, use Canare isolation bushing IU-7/16.(See page 33)





Fig.4 Return loss for NCJ-BCJR



Panel Hole Dimensions

75Ω Triaxial Connectors

75Ω Triaxial Connectors

Canare CC series cover global triaxial interconnection. CC-F series are ideal for interconnecting European triax system and CC-K series for American triax system.


Key Features and Benefits

- True 75Ω, DC 1.5GHz; ≥20dB return loss (≤ 1.2 VSWR)
- Push-lock mechanism
 - no cable stress when detaching to prevent cable break
- Reliable crimp system
- Rugged and durable construction

CC-F Series

Cable compatibility meets European interconnecting requirements.


Model	Description	Suitable Cable		Boot/Cap	Center contact	Sleeve A	Sleeve B	Crimp Tool
		Canare	Others					
CCF5-JFC	Crimp type, Female cable mount	L-5CFTX	Belden: 7783A	CB31	BN9194	BN7120	BN7121	TC-1 + TCD-65C
CCM5-PFC	Crimp type, Male cable mount		Klotz: TRIAX8	CB32	BN1135	BN7120	BN7121	
CCF5-JFRC	Crimp type, Female panel mount		Fujikura: 4.8/1.0 EFTXF	DCF02	BN9194	BN7120	BN7121	
CCM5-PFRC	Crimp type, Male panel mount			DCM02	BN1135	BN7120	BN7121	
CCF7-JFC	Crimp type, Female cable mount	L-7CFTX	Belden: 7784AS	CB31	BN9182A	BN7113	BN7114	TC-2 + TCD-96C
CCM7-PFC	Crimp type, Male cable mount		Klotz: TRIAX11	CB32	BN1131	BN7113	BN7114	
CCF7-JFRC	Crimp type, Female panel mount		Fujikura: SUPERFLEX11	DCF02	BN9182A	BN7113	BN7114	
CCM7-PFRC	Crimp type, Male panel mount			DCM02	BN1131	BN7113	BN7114	



CC-K Series

Cable compatibility meets American interconnecting requirements.

Model	Description	Suitable Cable		Retrofit Kit	Boot/Cap	Crimp Tool
		Canare	Others			
CCF4-JK	Crimp type, Female cable mount	L-4CFTX	Belden: 1856A, 1857A, 9267	BN9127A	CB23	TC-1 + TCD-316C
CCM4-PK	Crimp type, Male cable mount		Gepco: LVT61859, VT61859	BN9128B	CB22	
CCF4-JKR	Crimp type, Female panel mount			BN9127A	DCM02	
CCM4-PKR	Crimp type, Male panel mount			BN9128B	DCM03	



RCA Pin Connectors

■ RCAP-C Series (Crimp Plugs)

Model	Suitable Cable		Center Pin	Sleeve	Boot	Die Set
	Canare	Others				
RCAP-C25F	L-2.5CFB	1855A, 8218, 1417B, 1418B	B11014E	BN7029C	—	TCD-35CA
RCAP-C25HD	L-2.5CHD	—	B11015E	BN7129	—	TCD-35CA
RCAP-C3A	L-3C2VS, L-3C2V, V*-3C	—	B11014E	BN7003A	CB24	TCD-35CA
RCAP-C3GS	GS-6	—	BN1093	BN7079	CB25	TCD-35D
RCAP-C3F	L-3CFB, V*-3CFB	—	B11015E	BN7003A	CB24	TCD-35CA
RCAP-C42	—	1505F	B11016E	BN7011	—	TCD-31C
RCAP-C4A	LV-61S	8241, 8279, RG-59B/U	B11015E	BN7015A	CB25	TCD-4CA, TCD-451CA
RCAP-C4F	L-4CFB, V*-4CFB	1505A, 1505ANH, 8212, 8241F, 9167, 9259, 9659	B11016E	BN7015A	CB25	TCD-4CA, TCD-451CA
RCAP-C53	L-4.5CHD	1694A, 9066, 9116, 9118, 9248	B11020D	BN7016	CB26	TCD-35CA
RCAP-C5A	L-5C2VS, L-5C2V, V*-5C	—	B11016E	BN7016	CB26	TCD-35CA
RCAP-C5F	L-5CFB, V*-5CFB	—	B11020D	B75004A	CB26	TCD-5CF, TCD-55FA
RCAP-C77	LV-77S	8281F	B11016E	B75004A	CB26	TCD-5CF, TCD-55FA

• Standard package (20pcs/100pcs)

- Canare crimp design ensures quick and reliable installation.
- The crimp tool for the RCAP-C can be used for the Canare crimp BNC plugs as well, thus saving on extra equipment.

Be sure to use the Canare crimping tool for installing connectors on cables.




RCAP-C3A



F-09




F-10



RJ-JR




RJ-JR



RJ-RU




RJ-RU



RJ-RUD




RJ-JRUD



RJ-BCJRUD



RJ-BCJRU



RJ-BCJRU

• Standard package (10 pcs)

- Robust metal shell
- Comfortable grip
- Cable OD up to 6.0 mm.

■ Standoff Receptacle

Model	Description
RJ-JR	Jack to Jack

• Standard package: 20 pcs by insulation color

- Insulation color is available in 5 colors (red, green, blue, yellow, white).
- VSWR 1.2 @ 100Mhz

■ Flush-mount Receptacles

Model	Description	Flange Type
RJ-RU	RCA - Solder	ITT XLR-F77
RJ-RUD		Neutrik D
RJ-RUDB		Neutrik D (Black)
RJ-JRU	RCA - RCA	ITT XLR-F77
RJ-JRUD		Neutrik D
RJ-JRUDB		Neutrik D (Black)
RJ-BCJRU	RCA - BNC	ITT XLR-F77
RJ-BCJRUD		Neutrik D
RJ-BCJRUDB		Neutrik D (Black)

• Standard package: 20 pcs by insulation color

- Three types of flanges are available.
- Insulation color is available in 5 colors (red, green, blue, yellow, white).
- VSWR 1.2 @ 100Mhz

<Panel Hole Dimensions>

RJ-JR (*)	ITT XLR-F77 Flange	Neutrik D Flange

(*) RJ-JR accepts insulation bushing IU-7/16; in this case, panel hole for IU-7/16 should be adopted (see page 33)

50Ω BNC Crimp Plugs

VSWR of 1.1 or less up to 2GHz, 1.2 or less up to 4GHz.

■ BP-C Series

Model	Suitable Cable	Center Pin	Sleeve	Boot	Die Set (Model: TCD-***)		
					55FA	35D	3151D
BP-C3	L-3D2V, 3D-2V	BN1023A	BN7003A	CB03		●	
BP-C31	L-3D2W, 3D-2W	BN1023A	BN7011	CB04			●
BP-C4	RG-58C/U, RG-58A/U	BN1024A	BN7030A	CB03		●	
BP-C5	L-5D2V, 5D-2V	BN1025B	BN7016	CB05A		●	
BP-C5FA	L-5DFB, 5D-FB	BN1016C	B75004A	CB05A	●		
BP-C51	L-5D2W, 5D-2W	BN1025B	BN7002	—			●

• Standard package (20pcs)



BP-C5




BP-LC31

■ BP-LC Series (Right Angle Type)

Model	Suitable Cable	Center Pin	Sleeve	Die Set
BP-LC31	L-3D2W, 3D-2W	BN1023A	BN7011	TCD-3151D
BP-LC51	L-5D2W, 5D-2W	BN1025B	BN7002	

• Standard package (20pcs)

- Lock mechanism used on insulation improves reliability by preventing shifting or detaching of the contact pins.
- Elongated body design for straight type enables easy attachment and removal.
- Gold plating on the contact pin prevents deterioration, even after years of use.
- Use of crimping to attach the connectors ensures quick, reliable installation.



Be sure to use the Canare crimping tool for installing connectors on cables.


50Ω BNC Receptacles

■ Standoff

Model	Description
BJ-JR	Jack to Jack

• Standard package (20pcs)

- Mounting hole size is same as that for BCJ-R/1 connector.




BJ-JR

■ Flush-mount Receptacles

Model	Description	Flange Type
BJ-JRU	Jack to Jack	ITT XLR-F77
		Neutrik D

• Standard package (20pcs)

- Two types of flanges are available.
- Flush-mount receptacle prevents damage on the jack.




BJ-JRU

50Ω BNC Extension Adapter


Model	Description
BJ-J	Jack to Jack

• Standard package (20pcs)

- VSWR of 1.1 or less up to 4GHz.



BJ-J




50Ω TNC, 50Ω N, 50Ω SMA Connectors

50Ω TNC Crimp Plugs

■ TNP-C Series

Model	Suitable Cable	Boot	Die Set
TNP-C3	L-3D2V, 3D-2V	CB03	TCD-35D
TNP-C31	L-3D2W, 3D-2W	CB04	TCD-3151D
TNP-C4	RG-58C/U, RG-58A/U	CB03	
TNP-C5	L-5D2V, 5D-2V	CB05A	TCD-35D
TNP-C51	L-5D2W, 5D-2W	—	TCD-3151D
TNP-C5F	L-5DFB, 5D-FB	CB05A	TCD-35DF TCD-55FA

• Standard package (20pcs)



TNP-C3

■ TNP-LC Series (Right Angle Type)

Model	Suitable Cable	Die Set
TNP-LC31	L-3D2W, 3D-2W	
TNP-LC51	L-5D2W, 5D-2W	TCD-3151D

• Standard package (20pcs)

- VSWR of 1.1 or less up to 2GHz, 1.2 or less up to 4GHz.
- Use of crimping to attach the connectors ensures quick, reliable installation.
- Crimping tool can be used for the Canare crimp BNC plugs as well, thus saving on extra equipment.
- Elongated body design for straight type enables easy attachment and removal.

Be sure to use the Canare crimping tool for installing connectors on cables.



NP-C51

50Ω N Crimp Plugs

■ NP-C Series

Model	Suitable Cable	Boot	Die Set
NP-C31	L-3D2W, 3D-2W	CB04	
NP-C51	L-5D2W, 5D-2W	—	TCD-3151D

• Standard package (20pcs)

■ NP-LC Series (Right Angle Type)

Model	Suitable Cable	Die Set
NP-LC31	L-3D2W, 3D-2W	
NP-LC51	L-5D2W, 5D-2W	TCD-3151D

• Standard package (20pcs)

- VSWR of 1.1 or less up to 2GHz, 1.2 or less up to 4GHz.
- Lock mechanism used on insulation prevents shifting or detaching of the contact pins.
- Use of crimping to attach the connectors ensures quick, reliable installation.

Be sure to use the Canare crimping tool for installing connectors on cables.

50Ω SMA Crimp Plugs

■ SMAP-C Series

Model	Suitable Cable	Die Set
SMAP-C1	1.5D-QEW	TCD-1DB
SMAP-C3F	L-3DFB	TCD-35DF
SMAP-C31A	L-3D2W, 3D-2W	
SMAP-C51	L-5D2W, 5D-2W	TCD-3151D
SMAP-C5F	L-5DFB, 5D-FB	TCD-35DF TCD-55FA

• Standard package (20pcs)

■ SMAJ-C Series

Model	Suitable Cable	Die Set
SMAJ-C3F	L-3DFB	TCD-35DF
SMAJ-C51	L-5D2W, 5D-2W	TCD-3151D
SMAJ-C5F	L-5DFB, 5D-FB	TCD-35DF TCD-55FA


• Standard package (20pcs)

- Center contact for SMAP-C1 is of solder type.
- VSWR of 1.1 or less up to 2GHz, 1.2 or less up to 4GHz.
(SMAP-C1: VSWR of 1.2 or less up to 2GHz.)

Be sure to use the Canare crimping tool for installing connectors on cables.




SMAP-C1




SMAP-C1



SMAP-C31A



SMAJ-C3F



SMAJ-C3F

Connectors

Cable Stripper, Crimp Tools

Coaxial Cable Stripper

Three internal circular steel blades perform precise, extremely clean and easy stripping.

Model	Preset to
TS100E	LV-77S-L-5CFB, V*-5CFB, V*-5C, LV-61S-L-4CFB, V*-3C
TS100U	L-2.5CHD, 1855A, 1505A, 1694A

- For most Canare BNC, DIN, RCA and F crimp plugs.
- Rotary knob to select 5 different cable setups.
- Make your own cable setting within cable O.D. 4mm~11mm
- Hex wrench is attached on the lid top for quick adjustment.
- One replacement blade included, and also sold separately.
Replacement blade: TSC (1pc)

Note:



The following types of cables may not be accurately processed by

Canare's TS100 Cable Stripper, owing to their construction.

1. Cables employing such hard jacket material as polyethylene.
2. Cables employing such particularly soft insulator material as high-foam polyethylene.
3. Cables employing steel wire and semirigid pipe for outer conductor.



TS100E



Crimp Tools

Canare crimp tool offers reliable high-quality crimping performance in an easy-to-use design.


■ Die Sets

Model	Model
TCD-1DB	
TCD-31C	
TCD-315ID	
TCD-316C	
TCD-35CA	
TCD-35D	
TCD-35DF	
TCD-4CA	
TCD-451CA	
TCD-55FA	
TCD-5CF	
TCD-5HD	
TCD-65C	
TCD-67HD	
TCD-7CA	
TCD-96C	TC-2
TCD-D253F	TC-1
TCD-D534F	TC-1

TC-1


■ Hand Crimp Tools

Model	Description	Length
TB-2A	Tool case	—
BET-12	Extraction tool for BNC straight plug	12 inch
BET-MBNC	Extraction tool for MBCP-C series	30 cm
BET-DIN	Insertion / extraction tool for DCP-C series	30 cm



TB-2A
(tools and connectors not included)


- Select the appropriate die set to suit the individual connector
- Hand crimp tool is required for die set, and sold separately
- Die set are interchangeable



TC-1



Crimp Connector Assembly Instructions



Confirm compatibility of the connector and cable prior to assembly.

- Slide the crimp sleeve over the cable and strip the jacket, braided shield, and insulation of the coaxial cable as shown at left.
- For cables with stranded inner conductor, twist the strands in the same direction as plied after removing the insulation.
- For a crimp sleeve with steps, slip it over the cable from the stepped end, as in the diagram.
- If any aluminum foil shield is left on the cable, it may get stuck in the mouth of connector, making insertion impossible.
- Remove all stray strands and offcuts of the aluminum foil shield to avoid possible short circuiting.
- Make sure the inner conductor is free of all insulation debris and offcuts to ensure complete crimping.

- Place the center contact pin of the connector on the inner conductor of the cable and crimp the center contact pin at the correct position (without remaining a gap) as shown at left, using the specified crimp tool and die set.

- To confirm the crimping properly, measure the crimp height after removing burrs with a knife. If it is not within the ideal value range, adjust the crimp tool.
- Do not crimp the center contact pin at the stepped root end.
- Confirm the center contact pin is crimped straight to the inner conductor. If the center contact pin is slanted, align it gently.

- Hold the cable and push it into the connector body until the center contact is locked in place. You may feel a click sound when the center contact pin is locked.

- Pull the cable gently (less than 4.5lbs or 19.6N) to confirm that is locked.

- Slide crimp sleeve up against connector body over the braided shield until it butts against the connector body. Center the die over the crimp sleeve and crimp in place, using the specified crimp tool and die set.

- Do not pull the cable while crimping is executed.


Adjusting Crimp Tool

1. Measuring Crimping height

Crimp height is measured after the crimp is made. As shown in the figure, the sum of the measured values for both directions is divided by two to arrive at the crimp height. The ideal value range for the BCP-A3 connector, for example, is 1.4mm to 1.5mm. When this value is lower (overcrimping occurs) than the recommended crimp height, the crimp becomes very hard. A value higher (undercrimping occurs) than the recommended value can result in increased electrical resistance and a physically weaker crimp. Either digital calipers or a micrometer should be used for measuring crimp height.

2. Measuring Frequency

Crimp height is measured prior to commencing use of the crimp tool and always when changing the crimping die. After this, the crimp height is regularly measured after about each 1,000 crimps.



$$\text{Crimp height value} = (A+B)/2$$

Refer to the separately included manual for the appropriate crimp height values for individual connectors.

3. Tool Measuring Procedures

Crimp force increases and crimp height decreases when the tool's adjuster dial is turned in the direction of the 9. The dial is adjusted by first releasing it using a screw driver.



F A Q

Q Does it matter in which direction crimp sleeves are attached?

A For BCP-A3—use and other non-stepped (straight type) crimp sleeves, it does not matter in which direction the crimp sleeve is attached. The attachment direction also does not matter for BCP-A5F—use and other specific-use types that have a chamfer (groove) at one end of the crimp sleeve.

However, stepped crimp sleeves such as those for BCP-C1, etc. are directional and must be attached in the direction shown in the diagram below, with the cable threaded through the sleeve starting from the end with the step (that is, the end with smaller-diameter hole).



Q What should be done with an aluminum foil shield?


A Strip the aluminum foil shield to the root of the braided shield (to the edge of the jacket).

If any aluminum foil shield is left on the cable, it may get stuck in the mouth of connector, making insertion impossible.

Q Why do some BNC plugs made by other companies have a sharp point at the tip of the central contact? Are these compatible with Canare's BNC receptacles?

A The central contact is pointed in conformance with the JIS standard for 50Ω BNC connectors. The central contacts on Canare's connectors conform to the MIL standard, and therefore are not pointed. These two different shapes simply offer different ways to guide the plug into the female receptacle and have no direct effect on contact quality.

The actual contact surfaces on Canare's BNC connectors are designed in conformance with JIS standards and therefore pose no compatibility problems.



Canare BCP plug

MIL

JIS

Q Is it possible to use cables not listed in the connector compatibility table as long as they are close to the dimensions of those listed?

A No. While connection may be possible, performance may be adversely affected.

Even if the connection appears to work, factors such as electrical instability, weak cable contact strength and others may cause problems during actual use.

Therefore, it is necessary to test and evaluate whether it is actually possible to use the configuration in question. Particular caution should be used when crimping is involved.

Q What is meant by "cable contact strength"?

A Cable contact strength refers to the maximum load borne by the cable when exerting tensile force to remove it from the connector. For Canare products, "cable contact strength" refers to the contact strength of a cable's outer conductor, not including the pull-out strength of the central contact or the contact strength of the inner conductor.

Q What is the approximate insertion loss associated with connectors?

A The value varies depending on the connector, but for BNC plugs the value is approximately 0.1dB per plug (DC-2GHz).

Connectors

Crimp Tools

Cables to Connector Cross-Reference

BNC, F, RCA, etc.

See page 43, for more information about the crimp height.

Model	BNC							F	RCA	Others	Suitable Die Set (*1)	Crimp Height					
	Crimp Plug						Jack										
	BCP-B	BCP-A	BCP-C	MBCP-C	BCP-LC	BCP-H											
L-1.5C2VS/V*-1.5C																	
1.5C-2V			BCP-C1				BCJ-FC1(-7/16) BCJ-RUC1				TCD-1DB	—					
L-2.5C2V		BCP-A25										1.40 - 1.47					
L-2.5CFB		BCP-A25F		MBCP-C25F					RCAP-C25F								
1855A	BCP-B26																
1855P																	
L-2.5CHD/L-2.5CHLT	BCP-B25HD							FP-C25HD	RCAP-C25HD								
VDM230																	
1855ENH		BCP-B28															
HD PRO 0.6/2.8 AF																	
1506A		BCP-A32															
V4-2.5CHW	BCP-B25HW																
L-3C2V/L-3C2VS		BCP-A3					BCP-H3B BCP-H5/1			MCM-V5C3 MCF-V5C3							
V3-3C/V4-3C		BCP-A3 BCP-VA3						FP-C3	RCAP-C3A								
V5-3C										MCM-V5C3 MCF-V5C3							
L-3CFB	BCP-B3F	BCP-A3F		MBCP-C3F	BCP-LC3F	BCP-H3B BCP-H5/1		FP-C3F	RCAP-C3F								
V*-3CFB																	
1695A		BCP-A55						FP-C55A									
VSD2001TS																	
L-3C2W		BCP-A31						FP-C31			TCD-31C						
L-3CFW	BCP-B31F					BCP-H31F											
V*-3CFW																	
LV-61S		BCP-A4		MBCP-C4			BCJ-C4	FP-C4	RCAP-C4A	VWP-G4A MVP-C4							
RG-59B/U								FP-C4F	RCAP-C4F		TCD-4CA or TCD-451CA						
L-4CFB/V*-4CFB				MBCP-C4F													
1505A, 1505ANH																	
HD PRO 0.8/3.7 AF																	
VPM2000																	
L-4CHD																	
1505F		BCP-A42							RCAP-C42		TCD-31C						
L-4.5CHD	BCP-B53			MBCP-C53				FP-C53A	RCAP-C53								
1694A																	
HD PRO 1.0/4.8 AF	BCP-B56																
L-4.5CHWS	BCP-B45HW					BCP-H45HW					TCD-35CA						
L-5C2V/L-5C2VS		BCP-A5				BCP-H5B BCP-H5/1		FP-C5	RCAP-C5A								
V*-5C		BCP-A5 BCP-VA5															
LV-77S		BCP-A77							RCAP-C77								
L-5CFB	BCP-B5F	BCP-A5F (*2)		MBCP-C5F	BCP-LC5F	BCP-H5B BCP-H5/1 BCP-H51F		FP-C5F	RCAP-C5F								
V*-5CFB						BCP-H51F											
L-5CFW	BCP-B51F																
V*-5CFW																	
8281F		BCP-A77							RCAP-C77								
L-5C2W		BCP-A52						FP-C52			TCD-451CA						
L-5CHD			BCP-C5HD								TCD-5HD	1.90 - 2.00					
L-6CHD			BCP-C6HD								TCD-67HD	2.15 - 2.25					
L-7CHD			BCP-C7HD														
L-7CFB			BCP-C7FA					FP-C7FA									
7731A											TCD-7CA	1.90 - 2.00					
9292			BCP-C71A					FP-C71A									
L-8CHD										NCP-H8HD	—	—					
GS-6									RCAP-C3GS		TCD-35D	2.01 - 2.20					

*1: Die set is not required for BCP-H series and NCP-H8HD *2: Suitable die set for BCP-A5F is TCD-35CA

See page 40-41, for 50 ohm cables and connectors.

Belden: 1505A, 1505ANH, 1505F, 1506A, 1694A, 1695A, 1855A, 1855ENH, 1855P, 7731A, 8281F, 9292

Draka: HD PRO 0.6/2.8 AF, HD PRO 0.8/3.7 AF, HD PRO 1.0/4.8 AF

Gepco: VDM230, VPM2000, VSD2001, VSD2001TS

DIN 1.0/2.3, 4K-DIN

Model	DIN	4K-DIN	Suitable Die Set	Crimp height
	DCP-C	MD		
L-2.5CHD/L-2.5CHLT				
1855A				
VDM230	DCP-C25HD			
V4-2.5CHW		MDM-V4C25HW MDF-V4C25HW	TCD-D253F	1.08 - 1.16
L-3CFB	DCP-C3F			
L-4CFB	DCP-C4F			
1505A				
VPM2000				
L-4.5CHD				
1694A				
VSD2001	DCP-C53		TCD-D534F	1.25 - 1.33

Note: Be sure to use the right combination of cable, connector and die set for proper connection

Impedance Transformers

110Ω-75Ω Impedance Transformers

Passively convert AES/EBU digital audio signals from 110Ω/XLR3 output to a 75Ω BNC coaxial cable and then back again to a 110Ω/XLR3 input.

■ Adapter Type

Model	Description
BCJ-XJ-TRC	XLR3 (F) - BNC Jack
BCJ-XP-TRC	XLR3 (M) - BNC Jack
BCJ-XJ-A10TRC	XLR3 (F) - BNC Jack, 10dB Attenuation Pad



BCJ-XJ-TRC



BCJ-XP-TRC



BCJ-XJ-A10TRC



XJ3F-TRC-BCJ




BCJ-TRC-XP3M

BCJ-XJ-TRC / BCJ-XP-TRC

75Ω BNC (unbalanced)


110Ω XLR3 (balanced)



BCJ-XJ-A10TRC

75Ω BNC (unbalanced)

110Ω XLR3 (balanced)



110Ω-75Ω Impedance Transformer: Input/Output Level Performance


AES/EBU Transmitter (V)	Transformer Out (V)
2.0	1.60
3.0	2.39
4.0	3.18
4.5	3.60
5.0	3.98
6.0	4.78
7.0	5.58
8.0	6.38
9.0	7.18
10.0	7.98

BCJ-XJ-TRC/BCJ-XP-TRC


AES/EBU Transmitter (V)	Transformer Out -10dB Pad (V)
2.0	0.50
3.0	0.75
4.0	1.01
4.5	1.13
5.0	1.26
6.0	1.51
7.0	1.76
8.0	2.02
9.0	2.27
10.0	2.52

BCJ-XJ-A10TRC


Panel Hole Dimensions




BCJ-XJ-TRC



BCJ-XP-TRC



XJ3F-TRC-BCJ



BCJ-TRC-XP3M

Considerations When Configuring and Selecting Cables for Microphone Systems

With the growing demand of recent years for both greater physical comfort and savings in energy consumption, systems incorporating digital control based on the latest advances in electronics are coming into wider use for air conditioning and lighting systems. As all these systems come on line, we cannot help but be reminded of the fact that the wiring used for these digital control systems generates pulse-based electromagnetic noise of the kind that affects the very delicate signals used in microphone lines.

Microphone cables are designed to carry a range of signals that span the spectrum from 1/100 of a volt (1mV) to 1/1,000,000 (1µV). One small error in wiring procedure or cable selection and the entire microphone system turns into an antenna collecting the surrounding noise.

The following section uses a question and answer format to cover a list of the essential points for configuring microphone systems.

Q1 Under what sort of conditions should a two-conductor microphone cable be used?

The two-conductor microphone cable is suited to environments where noise is not such a great factor and the audio signals are in the comparatively high -20dB to 0dB level range. In such cases, the two-conductor cable offers the advantages of smaller diameter and lower cost. Of course if microphone level, rather than line level, is the criterion being used, star quad cable should be used instead.

Q2 Under what conditions should star quad microphone cable be used?

This type is used for environments with a higher noise factor and where audio signals are in the low -50dB or less range. This type of cable performs well under noise conditions that exceed the capacity of the two-conductor shielded cable, effectively shielding out over ninety percent more noise. (See Figs. 1, 2)

However, should this type be routed alongside a power cable of any significant capacity it should probably be encased in metal conduit just to be safe.

Q3 Isn't star quad cable expensive?

The cost for this type of cable has fallen significantly in recent years. Several decades ago, cost was so prohibitive a factor that only large musical auditoriums and broadcasting facilities could afford them. Canare succeeded in developing a low-cost star quad cable using aluminum foil in 1981. In addition to traditional professional facilities, this type gained wide use in such non-traditional areas as wedding halls and school lecture rooms.




Fig. 1 Noise induced in star quad cable (Canare L-4E5AT)




Fig. 2 Noise induced in two-conductor shielded cable (MVVS)

<Test conditions>

1. Flush along power cables for 20m distance
2. Power cable connected to lighting fixture dimmed to 50% capacity with load of 1kW.
3. The noise induced in the audio cable was boosted by 50dB in the head amplifier and viewed on a spectrum analyzer.



Star quad cable with aluminum foil shield

Q4 When avoiding use of metal conduit, how far away should microphone cable be from power cables?

When foregoing the use of protective metal conduit, use the graph shown in Fig. 3 as a general guide for distancing cables. Note that ignoring basic guidelines for positioning cables can easily result in noise induction problems which are very difficult to deal with later. Encasing microphone cables in metal conduits is highly recommended for applications that utilize the delicate signal range.




Fig. 3 Distances for positioning microphone and power cables

- <Requisite conditions>
1. Cables are the star quad type.
 2. Power cables are in the circular cab tire configuration.

Q7 What are the criteria for choosing between the many different types of microphone cables?

As all are designed to provide electromagnetic shielding there is not that much basic difference in shielding performance. However, they do differ in various specific characteristics. Cable type should be selected according to specific requirements. (See Fig. 5)




Fig. 5 Types of star quad microphone cables

• Braided Shield

The braided copper shield is designed to maintain effective shielding performance, regardless of how many times the cable is unwound, bent, twisted or rewound. It is ideal for use as handheld microphone cables or extension cables. This type is more expensive than other types as it is braided very finely to ensure a highly impenetrable shield. Cable termination requires seasoned expertise.

• Spiral Shield

The spiral shield consists of several copper wires wound tightly around the cable in a spiral wind. The shielding effect is heightened by winding the shield on twice, each time from different directions in what is referred to as the "double-spiral shield." The cost range for the spiral shield cable lies roughly mid way between the braided shield and the aluminum foil shield cable. Although cable termination operations are comparatively simple, the spiral shield tends to deteriorate when flexed too frequently. It is designed for stationary installation.

• Aluminum Foil Shield

The aluminum foil shield cable consists of aluminum foil fused onto a polyester film and wound around the cable in the form of a tape. Cable termination involves a simple operation and the cable is relatively inexpensive. The aluminum foil cable is recommended for use as stationary cabling.

Aluminum foil cable with a Kevlar cable filler is highly recommended for areas where cables will be routed through metal conduit. The Kevlar filler protects the cable as it passes through the conduit, preventing cable breakage or shorting, even when intense stress is applied to the cable. The aluminum foil cable is currently widely used in function halls and multipurpose track and field stadiums.

Q5 What considerations are required when using a rack for strong electric current?

The same as for the preceding question when metal conduit is not used.

Q6 Would there be any problem with routing the cables through a flexible metal conduit?

The flexible conduit would certainly help to reduce noise but would not be as effective as a rigid metal conduit. Use the graph in Fig. 4 as a guide for distancing cables.




Fig. 4 Distances for positioning microphone and power cables when routing microphone cables via flexible metal conduit

- <Requisite conditions>
1. Cables are the star quad type routed through flexible metal conduit.
 2. Metal conduit is grounded using appropriate level of resistance.
 3. Power cables are in the circular cab tire configuration.

AWG is for Indicating conductor size

AWG is the abbreviation for American Wire Gauge. For solid center conductor, numbers are decided by conductor O.D. and for stranded center conductor, numbers are decided by conductor cross sectional area. The AWG numbers for conductors used at Canare are listed in Table 1.

AWG	Conductor cross sec. area (mm ²)
13	2.81
14	2.18
15	1.75
16	1.27
18	1.0
20	0.51, 0.56
22	0.34, 0.37, 0.39
23	0.29, 0.30, 0.31
24	0.20, 0.22, 0.23
25	0.18
26	0.14, 0.15
28	0.08, 0.09
31	0.04

Table 1: AWG Numbers for Cables Used by Canare

Star Quad Cables

The Star Quad Story

Canare Star Quad obtains its name from the 4-conductor style construction that minimizes the "loop area" between twists of the conductors. This "double balanced" pairing, reduces susceptibility to electromagnetically induced noise. The improvement in noise rejection is so noticeable, that even SCR dimmer noise (stage lighting consoles), is reduced to less than 1/10 the level found in other 2-conductor microphone cables.

Canare Star Quad is designed for use with microphones but is also excellent for all line-level signals (e.g. mixer to power amps). The 4-conductor Star Quad arrangement, cancels electromagnetically induced

noise from SCR dimmer packs, fluorescent lighting ballasts and AC power transformers. Handling noise is prevented by use of cotton filler material. Excellent frequency response is maintained due to special irradiated polyethylene insulation which provides a low capacitance dielectric.


Canare Star Quad cable with braided shields is super flexible. We use large numbers of thin wire strands in the copper conductors and overall braided shield. We extrude a special compound PVC outer jacket that remains pliant at extremely low temperatures with no wait between cold shipping and installation.

Filler


Canare selects cotton, jute and /or exotic polyester fibers for packing. These fillers prevent stretching and twisting of the inner conductors which can cause noise. Additionally, paper, Mylar and/or cloth tape, bind conductors so cables hold their shape.

Jacket


Canare uses specially formulated PVC compounds that combine to make a tough, strong and durable outer jacket with excellent flexibility. These qualities are retained even at very low temperatures, so Canare cables will not stiffen or crack. Available in 10 attractive colors.



In order to maximize noise rejection, Star Quad must be properly wired to the XLR-3 connector (or terminal block).



Because the shield density on Canare Cable is very high, it is somewhat difficult to push back the braid and pull the inner conductors through. Instead, we strongly recommend unbraiding the shield by "combing" it out with a pointed tool, beginning at the end of the cable.



Star Quad Cables

Star Quad Microphone Cables (Single)



Effectively reduce noise levels to 1/10 that of general-purpose, 2-conductor shielded cables.

■ Aluminum Foil Shield

Type	Model	Sales units	Nom. O.D.	Weight	Composition			Electrical characteristics			
					No. of cond.	Cross sec area (AWG) and cond. comp.	Twist pitch	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
		m	mm	kg/100m		mm ² /(AWG) Q'ty/mm	mm	Ω/100m	Ω/100m	pF/m	pF/m
L-4E3AT Jacket color: gray	L-4E3AT	200 500	3.0 1.2	4		0.08(28) 7/0.12A	16	24.6	—	—	—
L-4E5AT Jacket colors L-4E5AT, L-4E6AT: gray, black	L-4E5AT	100 200	5.0 3.3	4		0.18(25) 16/0.12A	21	10.7	—	164	222
	L-4E6AT	400	6.2 5.0	4		0.31(23) 12/0.18A	25	6.4	—	150	210
L-4E5ATG Jacket color: gray, black	L-4E5ATG	100 200	5.0 3.3	4		0.18(25) 1/0.18(OFC)+30/0.08(OFC)	21	11.0	—	164	222
	L-4E6ATG	400	5.8 4.6	4		0.34(22) 1/0.18(OFC)+63/0.08(OFC)	35	5.5	—	150	210

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.



L-4E3AT

- Slim design for internal cabling connection on racks.

L-4E5AT, L-4E6AT

- The Kevlar* cable filler prevents damage due to excess stretching and stress that may occur when pulling the cable through conduits.
- Drain wire included

* Kevlar is the registered trademark of Dupont Corporation.

L-4E5ATG, L-4E6ATG

- OFC types of L-4E5AT/L-4E6AT

■ Braided Shield

Type	Model	Sales units	Nom. O.D.	Weight	Composition			Electrical characteristics				
					No. of cond.	Cross sec area (AWG) and cond. comp.	Twist pitch	Shield Coverage (braid)	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
		m	mm	kg/100m		mm ² /(AWG) Q'ty/mm	mm	%	Ω/100m	Ω/100m	pF/m	pF/m
L-4E6S Jacket colors L-4E6S: black, brown, red, orange, yellow, green, blue, purple, gray, white L-4E5C: black, red, orange, yellow, green, blue, gray	L-4E5C	100 200	4.8	3.4	4	0.15(26) 30/0.08A	18	96%	13.0	2.4	162	200
	L-4E6S		6.0	4.8	4	0.20(24) 40/0.08A	20	94%	9.8	3.0	150	185
L-4E5 Jacket colors L-4E5: gray, black L-4E6: gray	L-4E5	100 200	4.8	3.5	4	0.15(26) 30/0.08A	18	96%	13.0	1.9	162	200
	L-4E6	100 200 400	6.5	6.1	4	0.23(24) 20/0.12A	25	96%	8.6	1.6	144	187
L-4E6-WBS Jacket colors: gray	L-4E6-WBS	100 200	7.0	8.4	4	0.23 (24) 20/0.12A	25	96% & 95%	8.6	1.0	144	185

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors. **Capacitance between conductor and shield.

L-4E5, L-4E6


- Bend resistant design: the conductor consists of ultra-fine 0.08 mm strands offers excellent durability.
- High-density braided shield

L-4E5C, L-4E6S

- High-density braided shield
- Drain wire included

L-4E6-WBS



- High-density double-braided shiled
- Drain wire included



Star Quad Cables

Multichannel Star Quad Microphone Cables

■ Aluminum Foil Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition			Electrical characteristics					
							Cross sec area (AWG) and cond. comp.		Twist pitch	Ch. O. D.	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**	
				m	mm	kg/100m		mm ² /(AWG) Q'ty/mm	mm	mm	Ω/100m	Ω/100m	pF/m	pF/m	
 L-4E4-8AT ◆ L-4E4-2AT 2	L-4E3-2AT	2	 ◆ L-4E3-4AT 4	8.5	7.5	8	<div style="border: 1px solid black; padding: 2px; margin-bottom: 5px;"> 4E3AT Unit </div> <div style="display: flex; justify-content: space-between;"> <small>0.08(28)</small> <small>7/0.12A</small> </div>	<div style="border: 1px solid black; padding: 2px; margin-bottom: 5px;"> 4E4AT Unit </div> <div style="display: flex; justify-content: space-between;"> <small>0.18(25)</small> <small>16/0.12A</small> </div>	16	3.0	24.8	—	—	—	—
	L-4E3-4AT	4		10.0	11	16									
	L-4E3-8AT	8		13.8	19	32									
	L-4E3-12AT	12		15.6	26	48									
	L-4E3-16AT	16		17.2	32	64									
	L-4E3-24AT	24		21.3	47	96									
	L-4E4-2AT	2		10.5	12	8									
	L-4E4-4AT	4		12.3	17	16									
	L-4E4-8AT	8		16.9	31	32									
	L-4E4-12AT	12		18.9	41	48									
	L-4E4-16AT	16		20.9	50	64									
	L-4E4-24AT	24		26.1	76	96									

Insulation: Cross-linked PE (blue-blue, white-white) Jacket, inner jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

L-4E3-**AT, L-4E4-**AT

- The multichannel microphone cable is the cable of choice for music auditorium and studio facilities where noise prevention and audio quality are the prime considerations.
- Each unit contains the highly pull-resistant Kevlar cable filler.
- Drain wire included in each unit.






Fig. 1 Crosstalk Characteristics for L-4E4-4AT (100m)

■ Braided Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition			Electrical characteristics					
							Cross sec area (AWG) and cond. comp.		Twist pitch	Shield coverage (braid)	Ch. O. D.	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
				m	mm	kg/100m		mm ² /(AWG) Q'ty/mm	mm	%	mm	Ω/100m	Ω/100m	pF/m	pF/m
 L-4E3-8P ◆ L-4E3-2H 2	L-4E3-2H	2	 ◆ L-4E3-2P 2	8.9	9.5	8	<div style="border: 1px solid black; padding: 2px; margin-bottom: 5px;"> 0.08(28) </div> <div style="display: flex; justify-content: space-between;"> <small>7/0.12A</small> </div>	<div style="border: 1px solid black; padding: 2px; margin-bottom: 5px;"> 0.15(26) </div> <div style="display: flex; justify-content: space-between;"> <small>30/0.08A</small> </div>	16	93%	3.4	24.9	3.4	145	170
	L-4E3-2P	2		8.9	8.2	8									
	L-4E3-4P	4		10.9	14	16									
	L-4E3-8P	8		15.3	26	32									
	L-4E3-12P	12		17.4	36	48									
	L-4E3-16P	16		18.9	43	64									
	L-4E3-24P	24		24.0	70	96									
	L-4E4-2P	2		11.1	13	8									
	L-4E4-4P	4		13.4	21	16									
	L-4E4-8P	8		18.2	37	32									

Insulation: Cross-linked PE (blue-blue, white-white) Jacket, inner jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

L-4E3-2H, L-4E3-**P, L-4E4-**P

- Ideal multichannel cable for PA and live events where cables are laid down and taken back up on a regular basis.
- Each unit of L-4E3-*P and L-4E3-2H contains the highly pull-resistant Kevlar cable filler.
- The L-4E3-2H is the reinforced version containing a stainless steel wire support.






Fig. 1 Crosstalk Characteristics for L-4E4-4P (100m)

■ Cross-sectional View



■ Channel color code: Spiral marks on inner jacket (gray).

Unit no.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24
Spiral mark	RED	BLU	YEL	GRN	BRN	-	BLU/ BLK	YEL/ BLK	GRN/ BLK	BRN/ BLK	BLK	BLU/ ORN	YEL/ ORN	GRN/ ORN	BRN/ ORN	BLU/ PNK	YEL/ PNK	GRN/ PNK	BRN/ PNK	PNK	BLU/ WHT	YEL/ WHT	GRN/ WHT	

Two-Conductor Shielded Cables

Two-Conductor Shielded Cables (Single)

■ Aluminum Foil Shield

Type	Model	Sales units	Composition						Electrical characteristics				
			Nom. O.D.	Weight	No. of cond.	Cross sec area (AWG) and cond. comp.			Twist pitch	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
			m	mm	kg/100m	mm ² /(AWG) Q'ty/mm			mm	Ω/100m	Ω/100m	pF/m	pF/m
L-2B2AT Jacket colors: gray, black	L-2B2AT	200 500	3.2	1.3	2	0.18(25) 16/0.12A			25	10.5	—	73	120
L-2B2AL Jacket color: gray	L-2B2AL	200	3.2	1.2	2	0.18(25) 7/0.18TA Overall tin coated			20	11.3	—	—	—
L-2E5AT Jacket colors: gray, black, sepia	L-2E5AT	200	5.0	3.3	2	0.31(23) 12/0.18A			30	6.2	—	79	140
L-2E5AL Jacket color: gray	L-2E5AL	200 500	5.0	3.3	2	0.29(23) 7/0.23TA Overall tin coated			30	6.8	—	—	—

Insulation: Cross-linked PE (polyethylene for L-2E5AL and L-2B2AL) Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

L-2B2AT, L-2E5AT

- Ideal for internal rack wiring.
- Drain wire included.
- The L-2E5AT contains the Teflon cable filler reinforcement material. <Fig. 1>

L-2B2AL, L-2E5AL

- Cables for connecting devices with which wrapping tools can be used.
- Drain wire included.




Fig. 1 Pull Load and Stretch Ratio for Cable




Fig. 2 Frequency Characteristics for L-2B2AT (100m)

■ Braided Shield

Type	Model	Sales units	Composition							Electrical characteristics				
			Nom. O.D.	Weight	No. of cond.	Cross sec area (AWG) and cond. comp.			Twist pitch	Shield coverage (braid)	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
m	mm	kg/100m	mm ² /(AWG) Q'ty/mm			mm	%	Ω/100m	Ω/100m	pF/m	pF/m			
L-2T2S Jacket colors for L-2T2S: black, red, orange, yellow, blue, gray for L-2E5: black	L-2T2S	100 200	6.0	4.6	2	0.30(23) 60/0.08A			20	94%	6.4	3.1	70	106
		200	4.6	3.0	2	0.15(26) 30/0.08A			18	97%	12.7	2.2	—	—

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

L-2T2S, L-2E5

- Braid coverage of 94% and above provides dense shielding that blocks out electromagnetic noise.
- L-2T2S consists of 60 ultra-fine 0.08mm strands (30 for L-2E5) in a stranded format that offers excellent durability.
- Highly pliable and durable PVC used for jacket. (Brittle temp. -49°C)

Two-Conductor Shielded Cables

Spiral Shield

Type	Model	Sales units	Composition						Electrical characteristics			
			Nom. O.D.	Weight	No. of cond.	Cross sec area (AWG) and cond. comp.	Twist pitch	Shield coverage	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
			m	mm	kg/100m	mm ² /(AWG) Q'ty/mm	mm	%	Ω/100m	Ω/100m	pF/m	pF/m
	MS202	200	2.8	1.4	2	0.18 (25) 1/0.18TA + 30/0.08TA	25	91% (spiral)	11.0	3.2	74	145
MS202 Jacket color: black												
	MS203	200	3.5	2.1	2	0.31(23) 12/0.18TA	30	91% (spiral)	6.5	2.3	—	—
MS203 Jacket color: gray												

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

MS202

- Ideal for analog audio internal rack wiring.
- Composite conductors with 1 of 0.18mm and 30 of 0.08mm strands.
- Drain wire included.

MS203

- Ideal for internal rack wiring.
- Drain wire included.

Two-Conductor Shielded Multichannel Cables

Aluminum Foil Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition				Electrical characteristics					
							Cross sec area (AWG) and cond. comp.		Twist pitch	Ch. O. D.	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**		
							m	mm	kg/100m	mm ² /(AWG) Q'ty/mm	mm	mm	Ω/100m	Ω/100m	pF/m	pF/m
	L-2E4-2AL	2					8.6	7.6	4	0.29(23) 7/0.23TA Overall tin coated						
L-2E4-2AL Jacket color : gray	L-2E4-4AL	4	100				10.8	13	8							
	L-2E4-8AL	8	200				14.9	24	16							
	L-2E4-12AL	12	500				16.9	32	24							
	L-2E4-16AL	16					18.8	40	32							

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

L-2E4-AL Series

- Used as cables for connecting devices with which wrapping tools can be used.
- Drain wire included in each unit.

No.	Dot line markings
1	—
2	— —
3	— — —
4	— — — —
5	— — — — —
6	— — — — — —
7	— — — — — — —
8	— — — — — — — —
9	— — — — — — — — —
0	— — — — — — — — — —

Cross-sectional View




■ Channel color code: color-coded insulation and dot line makings (ch 1 to 10: red, ch 11 to 16: blue) on inner jacket (gray).

Unit no.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Insulation color	RED/ WHT	BLU/ WHT	YEL/ WHT	GRN/ WHT	BRN/ WHT	GRY/ WHT	BLU/ BLK	YEL/ BLK	GRN/ BLK	BRN/ BLK	GRY/ BLK	BLU/ ORN	YEL/ ORN	GRN/ ORN	BRN/ ORN	GRY/ ORN

Two-Conductor Shielded Cables

■ Aluminum Foil Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition			Electrical characteristics			
							mm	kg/100m		mm	mm	Ω/100m	Ω/100m
	M202-2AT	2	100 200 500	6.5	4.6	4	0.18(25) 16/0.12A	30	—	10.5	—	75	135
	M202-4AT	4		8.1	7.5	8							
	M202-8AT	8		11.1	13	16							
	M202-12AT	12		12.5	18	24							
	M202-16AT	16		13.8	22	32							
	M202-24AT	24		17.0	32	48							
	M202-32AT	32		18.6	40	64							
	MR202-2AT	2	100 200 500	6.7	4.5	4	0.18(25) 7/0.18A	25	2.7	10.7	—	76	142
	MR202-4AT	4		7.6	6.2	8							
	MR202-8AT	8		11.0	13	16							
	MR202-12AT	12		12.7	19	24							
	MR202-16AT	16		14.0	23	32							
	MR202-24AT	24		17.4	34	48							
	MR202-32AT	32		19.1	44	64							

Insulation: Cross-linked PE Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

M202-AT Series

- Multichannel cable featuring light weight and slim form. At only 16kg for a 50m length of 24 channel cable, the M202-AT achieves a 47% weight reduction over previous Canare cables.
- Each channel is individually isolated using insulated (PET) aluminum foil shield. <Fig. 1>
- Contains the highly pull-resistant Kevlar cable filler.
- Drain wire included.

Note:

This series does not have inner jacket, so it cannot be used for fantails.





Fig. 1 Aluminum Foil Shield



■ Cross-sectional View



■ Channel color code:

Unit no.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32
Insulation color	RED/ WHT	BLU/ WHT	YEL/ WHT	GRN/ WHT	BRN/ WHT	GRY/ BLK	BLU/ BLK	YEL/ BLK	GRN/ BLK	BRN/ BLK	GRY/ ORN	BLU/ ORN	YEL/ ORN	GRN/ ORN	BRN/ ORN	GRY/ PNK	BLU/ PNK	YEL/ PNK	GRN/ PNK	BRN/ PNK	GRY/ RED	BLU/ RED	YEL/ RED	GRN/ RED	BRN/ RED	GRY/ BLU	WHT/ BLU	YEL/ BLU	GRN/ YEL	BRN/ YEL	GRY/ YEL	


MR202-AT Series

Our bestselling two-conductor multichannel cable featuring AWG25 stranded conductor, 100% shielding by aluminum foil, and drain wire.


- Studio interconnect, portable snake system
- Each channel identified per resistor color-coding
- Aluminum foil shield and drain wire for easy terminate

Note:

Not appropriate for heavy-duty applications.



■ Cross-sectional View



■ Channel color code: Inner jacket color coding and spiral markings.* Insulation inside units: one is clear and the other bears the same color as the spiral markings.

Unit no.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32
Insulation color	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED
Spiral markings	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	—	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	—	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED
Inner jacket color	BLK								BRN								RED								ORN							

Two-Conductor Shielded Cables

Spiral Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition				Electrical characteristics			
							Cross sec area (AWG) and cond. comp.	Twist pitch	Shield coverage	Unit O.D.	Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
		mm	m	mm	kg/100m		mm ² /(AWG Q'ty/mm)	mm	%	mm	Ω/100m	Ω/100m	pF/m	pF/m
	MS202-2P	2	100 200 500	7.1	5.9	4	0.18 (25) 1/0.18TA + 30/0.08TA	25	91% (spiral)	2.8	11.0	3.2	74	145
	MS202-4P	4		8.2	9.2	8								
	MS202-8P	8		10.9	16.0	16								
	MS202-12P	12		13.6	24.2	24								


Jacket color: black

*Capacitance between conductors

**Capacitance between conductor and shield.

MS202-P Series

- Multichannel cable for analog audio.
- Composite conductors with 1 of 0.18 mm and 30 of 0.08 mm strands.
- Easy-to-use color-coded units and spiral shield.
- Drain wire included in each unit.

■ Cross-sectional View																																																																					
Single unit config.																																																																					
■ Channel color code:																																																																					
<table border="1"> <tr> <td>Unit no.</td> <td>1</td> <td>2</td> <td>3</td> <td>4</td> <td>5</td> <td>6</td> <td>7</td> <td>8</td> <td>9</td> <td>10</td> <td>11</td> <td>12</td> <td></td> </tr> <tr> <td>Insulation color</td> <td>BRN</td> <td>RED</td> <td>ORN</td> <td>YEL</td> <td>GRN</td> <td>BLU</td> <td>PPL</td> <td>GRY</td> <td>WHT</td> <td>BLK</td> <td>BRN</td> <td>RED</td> <td></td> </tr> <tr> <td>Spiral markings</td> <td>BRN</td> <td>RED</td> <td>ORN</td> <td>YEL</td> <td>GRN</td> <td>BLU</td> <td>PPL</td> <td>GRY</td> <td>WHT</td> <td>BLK</td> <td>-</td> <td>RED</td> <td></td> </tr> <tr> <td>Inner jacket color</td> <td colspan="6">BLK</td><td colspan="7">BRN</td> </tr> </table>														Unit no.	1	2	3	4	5	6	7	8	9	10	11	12		Insulation color	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED		Spiral markings	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	-	RED		Inner jacket color	BLK						BRN						
Unit no.	1	2	3	4	5	6	7	8	9	10	11	12																																																									
Insulation color	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED																																																									
Spiral markings	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	-	RED																																																									
Inner jacket color	BLK						BRN																																																														

Spiral Shield

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition				Overall shield coverage (braid)	Electrical characteristics			
							Cross sec area (AWG) and cond. comp.	Twist pitch	Shield coverage	Unit O.D.		Cond. D.C.R.	Shield D.C.R.	Nom. cap.*	Nom. cap.**
		mm	m	mm	kg/100m		mm ² /(AWG Q'ty/mm)	mm	%	mm		Ω/100m	Ω/100m	pF/m	pF/m
	MS203-2BS	2	100 200 500	8.9	11.0	4	0.31(23) 12/0.18TA	30	91% (spiral)	3.5	79%	6.6	2.3	—	—
	MS203-4BS	4		10.3	15.8	8									
	MS203-8BS	8		13.5	27.0	16									

Jacket color: gray

*Capacitance between conductors


**Capacitance between conductor and shield.

MS203-BS Series

- Multichannel version of MS203. (See page 52)
- Overall braided shield enables robust shielding performance.
- Drain wire included in each unit.

No.	Dot line markings
1	-
2	- -
3	- - -
4	- - - -
5	- - - - -
6	---
7	---
8	---
9	---
0	---

Cross-sectional View



Unit ID: by dot line markings

AES/EBU Digital Audio Cables

AES/EBU Digital Audio Cables

Ideal for conveying digital audio signals in conformance with AES/EBU and IEC standards.

Type	No. of ch.	Model	Sales units	Nom. O.D.	Weight	Unit composition			Electrical characteristics				Characteristic impedance	Attenuation	
						Cross sec area (AWG) and cond. comp.	Twist pitch	Shield coverage (braid)	Unit O.D.	Cond. D.C.R	Shield D.C.R.	Nom. cap.*	Nom. cap.**		
			m	mm	kg/100m	mm ² (AWG) Q'ty/mm	mm	%	mm	Ω/100m	Ω/100m	pF/m	pF/m	Ω	dB/100m (3MHz)
	1	DA206	100 200	7.3	7.5	0.56(20) 7/0.32A	60	95%	—	3.3	1.4	48	73	110	2.6
DA206 Jacket color: blue															
	1	DA202	100 200	5.0	3.7	0.18(25) 7/0.18A	32	95%	—	10.6	2.2	45	—	110	5.1
DA202 Jacket color: blue															
	1	DA202AT	100 200	4.0	1.6	0.18(25) 7/0.18A	38	—	—	10.6	—	45	—	110	6.7
DA202AT Jacket color: blue															
	1	DA203AL	100 200	6.0	4.2	0.29(23) 7/0.23TA Overall tin coated	45	—	—	6.8	—	48	95	110	5.4
DA203AL Jacket color: blue															
	2	DA202F-2P	100 200 500	7.7	6.7	0.18(25) 7/0.18TA	25	91% Spiral shield	3.0	11.3	3.0	47	95	110	5.6
DA202F-8P Jacket color: blue	4	DA202F-4P		8.8	10										
DA202F-8P Jacket color: blue	8	DA202F-8P		11.5	17										
	2	DA203-2AL	100 200 500	11.8	12	0.29(23) 7/0.23TA Overall tin coated	42	—	4.9	6.9	—	48	95	110	5.4
DA203-2AL Jacket color: blue	4	DA203-4AL		13.8	18										
DA203-4AL Jacket color: blue	8	DA203-8AL		19.3	33										
DA203-8AL Jacket color: blue	12	DA203-12AL		21.9	44										

Insulation: Cross-linked PE (DA202F-P: Cross-linked foam PE) Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors **Capacitance between conductor and shield.

DA206, DA202

- PE rod configuration ensures consistent 110Ω impedance with large or small bends in cable during installation.
- DA206 ideal for digital audio paths up to 360m*.
DA202 ideal for digital audio paths up to 180m*.
- DA202 contains a drain wire.

DA202AT

- Designed for internal cabling connections on racks.
- Ideal for digital audio paths up to 140m*.
- Drain wire included.

*Condition: AES3 SR48kHz

DA203-AL Series

- Wrapping tool can be used.
- Ideal for digital audio paths up to 170m*.
- Drain wire included in each unit.

DA202F Series

- Slim and lightweight.
- DA202F-8P designed to fit snugly with D-sub 25 pin connector.
- Cross-linked foam PE insulation.
- Ideal for digital audio paths up to 140m*.
- Drain wire included in each unit.

Channel Color Coding

DA202F-P: by the insulator color & the spiral markings on the inner jacket (blue).

Unit no.	1	2	3	4	5	6	7	8
Insulator Color	BRN, WHT	RED, WHT	ORG, WHT	YEL, WHT	GRN, WHT	BLU, WHT	PUR, WHT	GRY, WHT
Spiral Markings	BRN	RED	ORG	YEL	GRN	—	PUR	GRY


DA203-AL: by the insulator color & the spiral markings on the inner jacket (gray).

Unit no.	1	2	3	4	5	6	7	8	9	10	11	12
Insulator Color	RED, WHT	BLU, WHT	YEL, WHT	GRN, WHT	BRN, WHT	GRY, WHT	BLU, BLK	YEL, BLK	GRN, BLK	BRN, BLK	GRY, BLK	BLU, ORG
Spiral Markings	RED	BLU	YEL	GRN	BRN	—	BLU, BLK	YEL, BLK	GRN, BLK	BRN, BLK	BLK	BLU, ORG

Cross-sectional View for DA202F-P & DA203-AL

Single Unit Config.

DA202F-P, DA203-AL




Speaker Cables

Speaker Cables (Single)

Four-conductor configuration minimizes noise and polyethylene insulation reduces induction rate to boost frequency characteristics

■ 4-conductor Speaker Cable

Type	Model	Pair cross-sec	Sales units	Nom. O.D.	Weight	Composition				Electrical characteristics	
						No. of cond.	Cross sec area (AWG) mm ² /(AWG)	Cond. comp Q'ty/mm	Twist pitch mm	Cond. D.C.R.	Nom. capacitance*
										Ω/100m	pF/m
 4S8 Jacket color for 4S6: gray, black, red, blue, cream for 4S8, 4S11, 4S6G: gray, black for 4S8G, 4S11G: gray	 4S6	1.0	100 200 400	6.4	5.4	4	0.51(20)	20/0.18A	45	3.7	125
	 4S8	2.5		8.3	9.5	4	1.27(16)	50/0.18A	70	1.5	145
	 4S11	4.3		10.7	16	4	2.18(14)	41/0.26A	100	0.9	146
	4S6G	1.0		6.4	5.4	4	0.51(20)	20/0.18(OFC)	45	3.7	125
	4S8G	2.5		8.3	9.5	4	1.27(16)	50/0.18(OFC)	70	1.5	145
	4S11G	4.3		10.7	16	4	2.18(14)	41/0.26(OFC)	100	0.9	146

Insulation: polyethylene (red, translucent red, white, translucent white) Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors.

4S6, 4S8, 4S11

- High-performance PVC jacket, resistant to bending and twisting.
- 4S6 designed to fit snugly with Cannon XLR.

4S6G, 4S8G, 4S11G

- The G versions feature oxygen-free copper (OFC, JIS H3510) conductors.

■ 4-conductor Speaker Cable for Fixed Installation

Type	Model	Pair cross-sec	Sales units	Nom. O.D.	Weight	Composition				Electrical characteristics	
						No. of cond.	Cross sec area (AWG) mm ² /(AWG)	Cond. comp Q'ty/mm	Twist pitch mm	Cond. D.C.R.	Nom. capacitance*
										Ω/100m	pF/m
 4S10F Jacket color for 4S10F, 4S12F, 4S14F, 4S18F: gray, black for 4S10FG, 4S12FG: gray	 4S10F	3.5	100 200 400 1000	9.6	15	4	1.75(15)	33/0.26A	100	1.1	144
	 4S12F	5.6		11.6	22	4	2.81(13)	35/0.32A	120	0.7	152
	4S14F	8.0		14.0	32	4	4.0(12)	50/0.32A	120	0.5	—
	4S18F	14.2		17.5	53	4	7.08(9)	88/0.32A	150	0.3	—
	4S10FG	3.5		9.6	15	4	1.75(15)	33/0.26(OFC)	100	1.1	144
	4S12FG	5.6		11.6	22	4	2.8(13)	35/0.32(OFC)	120	0.7	152

Insulation: polyethylene (red, translucent red, white, translucent white) Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors.

4S10F, 4S12F, 4S14F, 4S18F

- Special supple jacket designed for use in building conduits.

4S10FG, 4S12FG

- The G versions feature oxygen-free copper (OFC, JIS H3510) conductors.

Multichannel Speaker Cables


Type	Model	Pair cross-sec	Sales units	Nom. O.D.	Weight	Unit composition				Electrical characteristics	
						No. of cond.	Cross sec area (AWG) and cond. comp.	Twist pitch	Ch. O. D.	Cond. D.C.R.	Nom. cap.*
										Ω/100m	pF/m
 S410-4P Jacket color: gray	S410-4P	2.0	100 200 500	15.0	26	16	1.0(18) 127/0.10(OFC)	50	5.1	1.9	165
	S410-6P	2.0		18.3	39	24					
	S410-8P	2.0		21.6	53	32					

Insulation: Polyethylene Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors.

S410-P Series

- Low crosstalk performance
- Ideal for use in multi-way speaker systems.
- Oxygen-free copper (OFC, JIS H3510) conductors.




■ Cross-sectional View of S410-4P and Channel color coding

Unit no.	1	2	3	4	5	6	7	8
Insulation color	RED/WHT	BLU/WHT	YEL/WHT	GRN/WHT	BRN/WHT	GRY/WHT	BLU/BLK	YEL/BLK

Speaker Cables (Single)

■ 2-conductor Speaker Cable for Fixed Installation

Type	Model	Sales units	Nom. O.D.	Weight	Composition		Electrical characteristics		
					No. of cond.	Cross sec area(AWG) Cond. comp.	Twist pitch	Cond. D.C.R.	Nom. capacitance*
						mm ² (AWG) Q'ty/mm			
 2S11F	2S7F	100 200 400	6.8	5.2	2	1.27(16) 50/0.18A	50	1.5	—
	2S9F		8.9	8.7	2	2.18(14) 41/0.26A	60	0.9	—
	2S11F		11.1	14	2	3.62(12) 45/0.32A	80	0.5	—
	2S14F		13.8	21	2	5.63(10) 70/0.32A	90	0.3	—
	2S7FG		6.8	5.2	2	1.27(16) 50/0.18(OFC)	50	1.5	—
	2S9FG		8.9	8.7	2	2.18(14) 41/0.26(OFC)	60	0.9	—
	2S11FG		11.1	14	2	3.62(12) 45/0.32(OFC)	80	0.5	—
	2S14FG		13.8	21	2	5.63(10) 70/0.32(OFC)	90	0.3	—

Insulation: polyethylene (orange, white) Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductors.

2S7F, 2S9F, 2S11F, 2S14F

- Special supple jacket designed for use in building conduits.

2S7FG, 2S9FG, 2S11FG, 2S14FG

- The G versions feature oxygen-free copper (OFC, JIS H3510) conductors.

Technical Note

Four-conductor Configuration Minimizes Noise

Because speaker cables are used to transmit comparatively high frequency signals, there is always the danger of electromagnetic noise affecting microphone cables that are used to transmit signals in the very delicate range. To overcome this problem, Canare has adopted a four-conductor configuration for all of its speaker cables. As shown in Fig. 2, the centers of the four conductors are positioned equidistantly in a configuration where the magnetic fields of adjoining cables are designed to cancel each other out. This distance factor significantly enhances the attenuation effect over that of the two-conductor configuration illustrated in Fig. 3. The result is a speaker cable design with a significantly lower noise emission factor.




Fig.2 Electromagnetic Field Generated by Four-Conductor Cable




Fig.3 Electromagnetic Field Generated by Two-Conductor Cable

Selecting the Right Speaker Cable

The goal when using speaker cables is to keep them as short as possible. A rather lofty ideal, however, given the real demands of large facilities. Power amplifiers are in one location, power lines must be drawn and various other electrical systems for maintenance and safety are also in place. Economic considerations preclude splurging on the thicker, more expensive cabling. The following section describes an example for selecting speaker cables using the damping factor as the criterion.

The damping factor is the damping effect on the speaker that is determined by power amplifier performance. It is expressed using the formula shown below.

$$\text{damping factor} = \frac{\text{speaker impedance}}{\text{power amp. output impedance} + \text{speaker cable conductor resistance}}$$

The greater the damping factor the better the ability to control the speaker and create sharp, clear quality in low range output.

As the formula shows, a high conductor resistance in the speaker

cable, the lower the damping factor, which prevents even quality amplifiers from performing at their best.

When selecting cables, users should aim for a higher damping factor in the range of 20 to 50 for music facilities, and a lower factor of 10 to 20 for sports stadiums, where output is mainly speech. The table below shows the damping factors (DF) for various lengths of Canare cable for use as a quick reference.

Table 1 Values calculated assuming power amplifier output impedance is 0.05Ω

Model	Pair cond. resist. (Ω/100m) & cross-sec (mm ²)	Cond. resist. (Ω/100m) for return path	Cable length/damping factor	
			DF=20	DF=50
4S6	1.87/1.0mm ² AWG 17	3.7	9.5m	3.0m
4S8	0.75/2.5mm ² 14	1.5	23.3	7.3
4S10F	0.54/3.5mm ² 12	1.1	31.8	10.0
4S11	0.43/4.3mm ² 11	0.87	40.2	12.6
4S12F	0.33/5.6mm ² 10	0.66	53.0	16.7
4S14F	0.24/8.0mm ² 9	0.47	74.5	23.4
4S18F	0.13/14.2mm ² 6	0.27	129.6	40.7

OFC Line, DMX, RS422 Cables

OFC Line Cables

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation	Outer conductors	Electrical characteristics		
					Cross sec area (AWG) and cond. comp.	mm ² /(AWG) Q'ty/mm			Nom. O.D.	Nom. O.D.	Chan. D.C.R.
		m	mm	kg/100m		mm	mm	mm/ends/carriers	Ω/100m	Ω/100m	pF/m
GS-6 Jacket color for GS-4: black GS-6: black, red, orange, yellow, green, blue	GS-4	200	4.0	2.7	0.39(22) 50/0.1(OFC)	0.82	1.82	Carbon plastic shield + 0.1 (OFC)/6/16 93%	4.7	3.1	—
	GS-6	100 200	5.8	5.0	1.0(18) 127/0.1(OFC)	1.3	3.0	Carbon plastic shield + 0.1 (OFC)/8/16 92%	1.8	2.5	160

Insulation: polyethylene Jacket: PVC Dielectric strength: 500V AC/min.

*Capacitance between conductor to shield.

GS-4, GS-6

- Outer conductor of fine 0.1mmØ OFC strands provide a highly flexible braided configuration. (See photographs A and B)



Photo A: Canare GS-6

Photo B: Typical shielded line

- Center conductor with 127 fine 0.1mmØ strands (50 for GS-4) increases durability.

* Note:
The GS-4 and GS-6 have a layer of carbon plastic shield underneath the braided shield (see Fig. 1) to block out noise. Shorting will result if this shield contacts the center conductor line, so special care must be taken when connecting the cable.



Fig. 1




Fig. 2 Frequency Characteristics for GS-6
(100m, 100Ω → 1MΩ load)

DMX Cable

Cable conforms to DMX512 standards for a use of stage lighting control.

Type	Model	Sales units	Nom. O.D.	Weight	No. of cond.	Unit composition			Overall shield coverage (braid)	Cond. D.C.R.	Characteristic impedance
						Cross sec area (AWG) and cond. comp.	Twist pitch	Twist O.D.			
						mm ² /(AWG) Q'ty/mm	mm	mm			
DMX203-2P Jacket color: black, gray, white	DMX203-2P	100 200 500	7.9	7.9	4	0.35(22) 44/0.10TA	25	3.3	94%	5.9	110

Insulation: Cross-linked PE Jacket: Frame retardant PVC Dielectric strength: 500V AC/min.

DMX203-2P

- PE rod ensures consistent 110Ω impedance with large or small bends in cable during installation.
- Ideal for Neutrik NC5 connectors.

RS422 Cables

Type	Cross-section view	Model	Sales units	Nom. O.D.	Weight	Unit type	Unit composition			Overall Shield coverage	Conductor resistance	Characteristic impedance	Attenuation	
							Cross sec area (AWG) and cond. comp.	Shield coverage	Unit O.D.					
			m	mm	kg/100m		mm ² /(AWG) Q'ty/mm	%	mm	%	Ω/100m	Ω	dB/100m (-)	
A2C3 Jacket color: black	A2C3	100 200 500	6.5	5.2		A	Digital lines two conductor shielded x 2	0.09(28) 7/0.127TA	90% Spiral shield	2.5	—	25.2	110	—
							Control lines 0.2mm ² x 3	0.22(24) 11/0.16TA	—	1.24		8.9	—	—
A2C3-SS Jacket color: black	A2C3-SS	100 200 500	7.0	7.2		A	Digital lines two conductor shielded x 2	0.09(28) 7/0.127TA	90% Spiral shield	2.5	91% Spiral shield	25.2	110	—
							Control lines 0.2mm ² x 3	0.22(24) 11/0.16TA	—	1.24		8.9	—	—

Insulation: Cross-linked foam PE Jacket: Frame retardant PVC Dielectric strength: 500V AC/min.

A2C3


- Short distance version of the RS422 class cables.
- Irradiated foam core PE used for the insulation in the digital signal unit.

A2C3-SS

- Created by adding an overall spiral shield to the A2C3 to heighten shielding performance.

Ethernet Cables

Category 6 Cables

Type	Model	Shield type	Sales units	Nom. O.D.	Weight	Conductors		Impedance	Insertion loss
						Cross sec. area & composition	DCR		
			m	mm	kg/100m	mm ² (AWG) Q'ty/mm	Ω/100m	Ω	dB/100m
	RJC6-4P-F <small>NEW</small>	Overall foil (F/UTP)	100 200	7.0	5.0	0.22 (24) 1/0.54A	9.4	100	32.8 @250MHz
Jacket color: black, light blue									
	RJC6-4P+	N/A (U/UTP)	305	6.1	4.0	0.23 (23) 1/0.55A	8.2	100	32.8 @250MHz
Jacket color: black, gray									

Insulation: polyethylene, Jacket: PVC Dielectric strength: 350V AC/min.

RJC6-4P-F

- Standard CAT6 STP (F/UTP) cable
- 100% overall foil shield reject EMI.
- Solid conductor
- Length markings on the cable jacket
- Drain wire included.

RJC6-4P+

- Standard CAT6 UTP cable
- Solid conductor
- Length markings on the cable jacket
- UL 444 type CM
- Packaged in REELEX* tangle-free cable dispenser

*REELEX is the registered trademark of REELEX Packaging Solutions, Inc.

Category 5e Cable

Type	Model	Shield type	Sales units	Nom. O.D.	Weight	Conductors		Impedance	Insertion loss
						Cross sec. area & composition	DCR		
			m	mm	kg/100m	mm ² (AWG) Q'ty/mm	Ω/100m	Ω	dB/100m
	RJC5E-4P+	N/A (U/UTP)	305	5.0	3.0	0.20 (24) 1/0.50A	9.4	100	22.0 @100MHz
Jacket color: light blue									

Insulation: polyethylene, Jacket: PVC Dielectric strength: 350V AC/min.

RJC5E-4P+

- Standard CAT5e UTP cable
- Solid conductor
- Length markings on the cable jacket

UL 444 type CM

- Packaged in REELEX* tangle-free cable dispenser

*REELEX is the registered trademark of REELEX Packaging Solutions, Inc.

Flex and Rugged Category 5e Cables

Type	Model	Shield type	Sales units	Nom. O.D.	Weight	Conductors		Impedance	Insertion loss
						Cross sec. area & composition	DCR		
			m	mm	kg/100m	mm ² (AWG) Q'ty/mm	Ω/100m	Ω	dB/100m
	RJC5ES-4P-BS	Overall braid (S/UTP)	100 200	6.7	6.1	0.22(24) 7/0.20A	9.5	100	44.0 @100MHz
Jacket color: black									
	RJC5E-4P-WJ	N/A (U/UTP)	100 200	7.4	5.4	0.22(24) 1/0.53A	8.8	100	22.0 @100MHz
Jacket color: black									

Insulation: polyethylene (RJC5ES-4P-BS: Cross-linked polyethylene.) Jacket: PVC Dielectric strength: 350V AC/min.

RJC5ES-4P-BS

- Flexible and durable CAT5e STP cable for short distance.
- Stranded conductor and a overall braided shield
- Superior flexibility for easy routing and repeated bending

RJC5ES-4P-WJ

- Rugged CAT5e UTP cable
- Solid conductor and double jacket
- Rugged and flexible double jacket offers easy routing.

Note: Maximum allowed length of RJC5ES-4P-BS is 50m.

75Ω Coaxial Cables

75Ω Coaxial Cables

A wide variety of 75Ω coaxial cables support full-range of video formats. Our cutting-edge Super Low Loss Coax and Low Loss Coax are ideal for 3G-SDI/HD-SDI distribution.

■ Super Low Loss Coax (Highly-Foamed PE Insulation)

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation	Outer conductors	Shield coverage & comp.	Inner cond. resistance	Outer cond. resistance	Static capacity	Characteristic impedance	Attenuation
					Conductor comp.	O.D.								
	L-2.5CHD	100 200	4.2	2.6	(23) 1/0.59A	0.59	2.59	0.12TA/7/16 (95%)	66.9	16.9	53	75	30.2	
	L-4CHD		6.1	5.2	(20) 1/0.82A	0.82	3.68	0.14TA/8/16 (95%)	36.4	11.4	53	75	21.3	
	L-4.5CHD		7.0	6.2	(18) 1/1.02A	1.02	4.57	0.14TA/6/24 (91%)	23.3	9.9	53	75	17.4	
	L-5CHD		7.7	7.4	(17) 1/1.20A	1.20	4.9	0.14TA/7/24 (93%)	16.1	8.2	50	75	15.6	
	L-6CHD		8.9	10	(15) 1/1.50A	1.50	6.1	0.14TA/8/24 (92%)	10.3	7.7	50	75	12.9	
	L-7CHD		10.2	13	(13) 1/1.80A	1.80	7.3	0.16TA/8/24 (92%)	7.1	6.1	50	75	10.9	
	L-8CHD		11.1	14	(12) 1/2.10A	2.10	8.2	0.16TA/8/24 (89%)	5.8	6.3	50	75	9.6	
	L-2.5CHLT	100 200	4.2	1.8	(23) 1/0.59A	0.59	2.59	0.14TCCA/6/16 (95%)	66.9	21.5	53	75	30.2	

Jacket colors: black, red, yellow, green, blue and others.

Jacket: PVC Dielectric strength: 1000V AC/min.

L-CHD Series

- Best suited to 3G-SDI/HD-SDI transmission.
- Highly-foamed PE insulation allows further improvement in the attenuation characteristics.
- Multi-layer insulation in which to each layer is given a different foaming ratio is used to increase strength.
- High-density tinned copper braided shield with aluminum foil brings excellent shielding.
- Solid conductor
- Flame resistance UL 1666 Riser (excluding L-6CHD, L-7CHD, and L-8CHD).

Note 1: Designed for fixed installation, and do not tolerate repeated bending or external pressure well.

Note 2: Cable strippers (TS100 series) cannot be used for L-CHD series other than L-2.5CHD.

Note 3: L-2.5CHLT has less connection strength with the connector BCP-B25HD compared with L-2.5CHD.

L-2.5CHLT

- Ideal for an O.B. van installation.
- Tinned copper-clad aluminum (CCA) braided shield brings an advantage in weight-saving.
- 30% lighter than L-2.5CHD, yet the same attenuation.
- Space-saving slim design: O.D. 4.2 mm
- High-density braided shield with aluminum foil
- Highly-foamed PE insulation
- Solid conductor

■ Low Loss Coax for Mobile (Highly-Foamed/Foamed PE Insulation)

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation	Outer conductors	Shield inner/outer coverage & comp.	Electrical characteristics			Characteristic impedance	Attenuation
					Conductor comp.	O.D.				mm/ends/carriers	Ω/100m	Ω/100m	pF/m	Ω
 L-4.5CHWS Jacket color: black and others	L-4.5CHWS	100 200	7.2	6.6	(18) 7/0.34A	1.02	4.57	0.10A/8/24 (93%) 0.10A/9/24 (95%)		3.3	0.8	53	75	22.8
 L-3CFW Jacket colors: black, red, green and others	L-3CFW	100 200	5.8	5.1	(22) 1/0.65A	0.65	3.1	0.12A/5/24 (94%) 0.12A/6/24 (94%)		5.5	0.7	55	75	33.1
	L-5CFW		7.7	8.1	(18) 1/1.05A	1.05	5.0	0.12A/7/24 (93%) 0.12A/9/24 (96%)		2.3	0.5	55	75	19.4

Jacket: PVC Dielectric strength: 1000V AC/min.

L-CHWS Series

- Flexible and durable: Best suited to mobile HD application.
- Designed for withstanding repeated bending.
- Stranded center conductor
- High-density double-braided shield
- Highly-foamed insulation

Note: Cable strippers (TS100 series) cannot be used.


L-CFW Series

- Suited to mobile HD application.
- Achieve a good balance between durability and transmission distance.
- Solid center conductor
- High-density double-braided shield
- Foamed insulation

Note: Cable strippers (TS100 series) cannot be used.

75Ω Coaxial Cables, Triaxial Cables

■ Low Loss Coax (Foamed PE Insulation)

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation	Outer conductors		Electrical characteristics			Characteristic impedance	Attenuation
					Conductor comp.	O.D.		O.D.	Shield coverage & comp.	Inner cond. resistance	Outer cond. resistance	Static capacity		
		m	mm	kg/100m	(AWG) Q'ty/mm	mm	mm	mm	mm/ends/carriers	Ω/100m	Ω/100m	pF/m	Ω	dB/100m 750MHz
 L-5CFB	L-2.5CFB	100 200	4.0	2.4	(25) 1/0.50A	0.50	2.4	0.12TA/6/16 (92%)	9.3	2.0	55	75	37.0	
	L-3CFB		5.5	4.0	(22) 1/0.65A	0.65	3.1	0.14TA/6/16 (91%)	5.5	1.6			29.1	
	L-4CFB		6.1	4.9	(20) 1/0.80A	0.80	3.7	0.14TA/8/16 (93%)	3.6	1.1			23.6	
	L-5CFB		7.7	7.3	(18) 1/1.05A	1.05	5.0	0.14TA/7/24 (93%)	2.3	0.8			17.7	
	L-7CFB		10.2	13	(15) 1/1.50A	1.50	7.3	0.18TA/8/24 (95%)	1.0	0.5			13.4	

Jacket: PVC Dielectric strength: 1000V AC/min.

L-CFB Series

- Foamed insulation; suited to HD video signals.
- High-density tinned copper braided shield with aluminum foil brings excellent shielding.

Note: Designed for fixed installation, and do not tolerate repeated bending or external pressure well.

■ Standard Coax (Solid PE Insulation)

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation	Outer conductors		Electrical characteristics			Characteristic impedance	Attenuation
					Conductor comp.	O.D.		O.D.	Shield inner/outer coverage & comp.	Inner cond. resistance	Outer cond. resistance	Static capacity		
		m	mm	kg/100m	(AWG) Q'ty/mm	mm	mm	mm	mm/ends/carriers	Ω/100m	Ω/100m	pF/m	Ω	dB/100m (10MHz)
 L-3C2VS	L-1.5C2VS	200	2.9	1.3	(31) 7/0.09A	0.27	1.6	0.10A/5/16 (94%)	41.9	3.3	69	75	8.7	
	L-3C2VS	100 200	5.5	4.5	(25) 7/0.18A	0.54	3.1	0.12A/7/16 (94%)	10.5	1.9	4.5			
	LV-61S	153	6.1	5.0	(24) 7/0.20A	0.60	3.6	0.12A/6/24 (95%)	8.5	1.3	3.8			
	L-5C2VS	100 200	7.4	6.8	(22) 7/0.26A	0.78	4.8	0.12A/7/24 (93%)	5.0	1.2	2.9			
	L-2.5C2V	100 200	4.0	2.4	(26) 1/0.40A	0.40	2.4	0.12TA/6/16 (94%)	19.2	2.1	69		5.2	
	L-3C2V		5.4	4.3	(25) 1/0.50A	0.50	3.1	0.14TA/5/24 (97%)	9.3	1.2	4.1			
	L-5C2V		7.4	7.2	(21) 1/0.80A	0.80	4.9	0.14TA/7/24 (94%)	3.6	0.8	2.5			
 L-3C2W	L-3C2W	100 200	6.5	7.0	(25) 1/0.50A	0.50	3.1	0.14TA/5/24 (97%) 0.14TA/5/24 (93%)	9.3	0.6	67	75	4.1	
	L-5C2W	200	8.3	11.0	(20) 1/0.80A	0.80	4.9	0.14TA/7/24 (94%) 0.14TA/7/24 (95%)	3.6	0.4			2.5	
	LV-77S	153	7.7	9.0	(22) 7/0.26A	0.78	4.8	0.12A/7/24 (92%) 0.12A/8/24 (95%)	5.0	0.6			3.4	

Jacket: PVC Dielectric strength: 1000V AC/min. *100m/200m/500m/1000m

L-1.5C2VS, L-3C2VS, L-5C2VS, LV-61S

- Stranded center conductor ideal for locations requiring cable bending.

L-3C2W, L-5C2W, LV-77S

- Double-braided shield enhances shielding performance.

L-2.5C2V, L-3C2V, L-5C2V

- Solid center conductor

75Ω Triaxial Cables

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond.		Insulation 1	Outer cond.1	Insulation 2	Outer cond.2	Electrical characteristics			Characteristic impedance	Attenuation
					Cross sec. (AWG) & comp.	O.D.					Braid coverage and comp.	O.D.	Braid coverage and comp.	Inner cond. resistance	Outer cond. resistance
		m	mm	kg/100m	mm ² /(AWG) Q'ty/mm	mm	mm	mm/ends /carriers	mm	mm	mm/ends /carriers	Ω/100m	Ω/100m	pF/m	Ω
 L-5CFTX	L-5CFTX	100 200	8.8	12.0	0.79(19) 1/1.0A	1.0	4.8	0.14A/6/24 (91%)	6.4	0.16A/8/24 (95%)	2.3	—	55	75	2.2
	L-4CFTX		9.1	10.5	0.50(20) 1/0.80A	0.80	3.7	0.14A/7/16 (93%)	5.5	0.14A/7/24 (94%)	3.64	—	55	75	3.0
	L-7CFTX	100 200	11.0	15.4	1.54(16) 1/1.40A	1.40	6.5	0.14A/8/24 (93%)	8.7	0.14A/8/24 (88%)	1.18	—	55	75	1.7
	10CFTX-SC	500	14.5	27.0	3.01(13) 7/0.74A	2.22	9.6	0.14A/10/24 (95%)	11.4	0.16A/10/24 (94%)	0.62	—	55	75	1.1

Jacket colors: black, red, green

- Abrasion-resistance PVC jacket.

75Ω Multichannel Coaxial Cables

75Ω Multichannel Coaxial Cables


■ Low Loss Multichannel Coax (Foamed PE Insulation)

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	Unit composition						Electrical characteristics					
						Inner cond.		Insulation	Outer cond.		Unit O.D.	Inner cond. resistance	Outer cond. resistance	Characteristic impedance	Attenuation		
						Cross sec. area	conductor comp.		O.D.	O.D.							
				m	mm	kg/100m	mm ² /(AWG) Q'ty/mm	mm	mm	%	mm	Ω/100m	Ω/100m	Ω	dB/100m (750MHz)		
	V3-3CFB	3	100 500	11.5	14							Refer to L-3CFB (P61)	4.4	5.6	1.6	75	29.1
	V4-3CFB	4		13.0	19												
	V5-3CFB	5		14.2	23												
	V3-4CFB	3		12.9	18							Refer to L-4CFB (P61)	5.0	3.7	1.0	75	24.3
	V4-4CFB	4		14.4	23												
	V5-4CFB	5		16.1	29												
	V3-5CFB	3		17.1	29							Refer to L-5CFB (P61)	6.5	2.3	0.8	75	17.7
	V4-5CFB	4		18.8	36												
	V5-5CFB	5		21.1	46												
	V4-2.5CHW	4	100 500	13.0	21		0.27 (23) 1/0.59A	0.59	2.59	0.10TA/8/16 (95%) 0.10TA/9/16 (94%)		Refer to L-3CFW (P60)	4.2	6.7	1	75	35.7
	V3-3CFW	3		13.0	22												
	V4-3CFW	4		14.6	28												
	V5-3CFW	5		16.2	34							Refer to L-5CFW (P60)	4.9	5.6	0.7	75	33.1
	V3-5CFW	3		18.4	36												
	V4-5CFW	4		20.4	47												
	V5-5CFW	5		22.4	58												

Jacket PVC Dieritic strength: 1000V AC/min.

V-CFB Series

- Bundled thinner jacket type of Canare L-CFB Series: solid conductor and foamed PE insulation wrapped with aluminum foil.
- Excellent low attenuation performance will fit for digital video in fixed installations.
- Distinguishable RGB color-coded.




V4-2.5CHW, V-CFW Series

- Developed for digital video mobile application with flexible double braided shield.

Note: Cable strippers (TS100 series) cannot be used for V4-2.5CHW and V-CFW series.


■ Standard Multichannel Coax (Solid PE Insulation)

Type	Model	No. of ch.	Sales units	Nom. O.D.	Weight	Unit composition						Electrical characteristics					
						Inner cond.		Insulation	Outer cond.		Unit O.D.	Inner cond. resistance	Outer cond. resistance	Characteristic impedance	Attenuation		
						Cross sec. area	conductor comp.		O.D.	O.D.							
				m	mm	kg/100m	mm ² /(AWG) Q'ty/mm	mm	mm	%	mm	Ω/100m	Ω/100m	Ω	dB/100m (10MHz)		
	V3-1.5C	3	100 500	7.4	7.3							Refer to L-1.5C2VS (P61)	2.6	42.3	3.3	75	8.7
	V4-1.5C	4		8.4	9.4												
	V5-1.5C	5		9.2	11												
	V3-3C	3		11.5	15							Refer to L-5C2VS (P61)	4.4	10.6	1.1	75	4.5
	V4-3C	4		13.0	20		0.18 (25) 7/0.18A	0.54	3.1	0.14A/5/24 (97%)							
	V5-3C	5		14.2	24												
	V3-5C	3		15.5	26												
	V4-5C	4		17.1	33												
	V5-5C	5		19.2	39												

Jacket PVC Dieritic strength: 1000V AC/min.

V-C Series

- Our long-selling multichannel coax, ideal for component video.
- Bundled thinner jacket type of Canare L-C2VS series: flexible stranded conductor and solid PE insulation.
- Distinguishable RGB color-coded.



A/V Composite Cables, 50Ω Coaxial Cables

A/V Composite Cables

Used for linking audio video equipment and as extensions for video cameras.

Type	Model	Sales units	Nom. O.D.	Weight	Unit type V: Video A: Audio C: Control line	Unit composition			Electrical characteristics			
						Cross sec. area Conductor comp.	Shield coverage	Unit O.D.	Characteristic impedance	Attenuation		
						mm ² /(AWG) Q'ty/mm	%	mm	Ω	dB/100m (10MHz)		
		100 200	9.7	11	V	Video 3C-2V×1	0.20(24) 1/0.5A	97% (braid)	4.4	75	4.1	
					A	Audio L-2B2AT×2	Refer to L-2B2AT	Alminum foil shield	3.2	—	—	
			11.0	16	V	Video 3C-2V×2	0.20(24) 1/0.5A	97% (braid)	4.4	75	4.1	
					A	Audio L-2B2AT×2	Refer to L-2B2AT	Alminum foil shield	3.2	—	—	
					C	Control lines 0.2mm ² ×4	0.20(24) 18/0.12A	—	1.3	—	—	
			11.1	13	V	Video 3C-2VS×1	0.18(25) 7/0.18A	97% (braid)	4.4	75	4.5	
					A	Audio 4E3 Unit×2	0.08(29) 7/0.12A	93% (braid)	3.4	—	—	
			12.3	17	V	Video 3C-2VS×2	0.18(25) 7/0.18A	97% (braid)	4.4	75	4.5	
					A	Audio 4E3 Unit×2	0.08(29) 7/0.12A	93% (braid)	3.4	—	—	
			12.4	17	V	Video 3CFB Unit×2	0.33(22) 1/0.65A	91% (braid) + Alminum foil	4.4	75	3.7	
					A	Audio L-2B2AT×3	Refer to L-2B2AT	Alminum foil shield	3.2	—	—	

Jacket color: black

Jacket: PVC Dielectric strength: 500V AC/min.

A2V1, A2V2-L

- Designed for fixed installation.

A2V1B, A2V2B

- Ideal for locations requiring cable bending.

A3V2-FB

- 3 balanced audio channels and 2 video coax channels for ENG, EFP, or OB applications.

50Ω Coaxial Cables

Type	Model	Sales units	Nom. O.D.	Weight	Inner cond		Insulation	Outer conductors		Electrical characteristics			Characteristic impedance	Attenuation
					Cross sec. (AWG) & comp.	O.D.		Shield inner/outer coverage & comp.	Inner cond. re- sistance	Outer cond. re- sistance	Static capacity			
					m	mm	kg/100m	mm ² (AWG) Q'ty/mm	mm	mm	mm/ends/carriers	Ω/100m	Ω/100m	pF/m
 L-3D2V Jacket color: gray	 L-3D2V	100 200	5.3	4.5	0.56(20) 7/0.32A	0.96	3.0	0.14TA/5/24 (98%)	3.3	1.2	100	50	4.5	
					1.54(15) 1/1.40A	1.40	4.8	0.14TA/7/24 (95%)	1.2	0.8				2.5
 L-3D2W Jacket color: gray	 L-3D2W	100 200	6.4	7.3	0.56(20) 7/0.32A	0.96	3.0	0.14TA/5/24 (98%) 0.14TA/5/24 (96%)	3.3	0.6	100	50	4.5	
					1.54(15) 1/1.40A	1.40	4.8	0.14TA/7/24 (95%) 0.14TA/7/24 (96%)	1.2	0.4				2.5
 L-5DFB Jacket color: black	L-5DFB	100 200	7.6	8.5	2.55(13) 1/1.80A	1.80	5.0	0.14TA/6/24 (90%)	0.7	1.1	84			2.5

Insulation: polyethylene Jaket: PVC Dielectric strength 1000V AC/min.

L-3D2V, L-3D2W, L-5D2V and L-5D2W

- Tinned annealed copper used on outer conductors.

L-5DFB

- Low-loss foamed PE used for insulation.

Technical Note

Many types of video coax. What're the differences and how select?

In brief, there are three of essential factors: 1) center conductor, 2) insulation, and 3) shield. Each factor has its advantage and disadvantage as described below:

- 1) Center Conductor: two types existing, "Solid" and "Stranded". Stranded conductor is more flexible and therefore the best choice for mobile and stage use.
- 2) Insulation: includes "Solid", "Foamed", and "Highly-foamed" types. Foamed and highly-foamed insulation would perform better attenuation, compared to the solid type thus they are often selected for hi-def video. However, since foamed and high-foamed insulation contain the air physically, they are weak to external pressure. You should pay attention to where and how the cables are installed.
- 3) Shield: we have "Braided" and "Braided with aluminum foil" type. Braided shields include single, double, or triple layers as well as bare copper or tinned copper. Braided with aluminum foil offers perfect screening, but they are not suitable for repeated bending and mobile applications due to the foil's lack of strength. In that case, it's better to choose "Braided".

What is Propagation Delay?

Propagation delay refers to the time required for a signal to be transmitted from one end of connection to another. In the case of cable transmission, this greatly depends on the materials and construction of the actual cable, and large differences in delay can cause transmission errors if they exceed the receiver delay tolerance.

The following table shows the differences in coaxial cable propagation delay time relative to the insulation type.

Propagation Delay Caused by Coaxial Cable Insulation (reference)

Insulation	Propagation Delay
Solid PE	5.0 ns/m
Foamed PE	4.2 ns/m
Highly-Foamed PE	3.7 ns/m

■ Maximum Transmission Distance by Video Format (reference)


Standard	SMPTE ST 259	ITU-R BT. 601	SMPTE ST 259	SMPTE ST 259	SMPTE ST 344	SMPTE ST 292	SMPTE ST 424
Video Format	Composite NTSC	Composite PAL	Component 4:2:2	Component 4:2:2 16x9	SDI	HD-SDI	3G-SDI
Bit Rate	143 Mb/s	177 Mb/s	270 Mb/s	360 Mb/s	540 Mb/s	1.5 Gb/s	3.0 Gb/s
Model	m	m	m	m	m	m	m
L-2.5CFB	265	242	199	172	139	54	55 (36)
L-2.5CHD	314	287	237	206	168	66	69 (46)
L-2.5CHLT	314	287	237	206	168	66	69 (46)
L-3CFB	344	314	257	222	179	68	69 (46)
L-4CFB	422	314	315	272	220	84	86 (57)
L-4CHD	447	410	337	294	238	93	98 (65)
L-5CFB	563	513	420	364	294	112	114 (76)
L-4.5CHD	551	504	415	361	293	115	119 (79)
L-5CHD	614	562	464	403	327	128	133 (88)
L-6CHD	766	700	575	499	403	154	158 (105)
L-7CHD	902	824	678	589	476	184	188 (125)
L-8CHD	1035	945	777	674	544	208	212 (141)
V4-2.5CHW	288	258	208	178	144	56	57 (38)
L-3CFW	319	288	230	197	158	60	60 (40)
L-4.5CHWS	447	405	322	280	225	87	90 (60)
L-5CFW	535	483	384	333	267	103	105 (70)

The above values are based on SMPTE standards. Our criteria is as follows:

ST 292 & 424M : The listed coaxial cable's attenuation value does not exceed 20 dB loss at one-half the clock frequency (bit rate).

ST 424 & others : The listed coaxial cable's attenuation value does not exceed 30 dB loss at one-half the clock frequency (bit rate).

Recommended margin: 2 or 3 dB. See page 65 for the nominal attenuation.




(SMPTE 424M)

Nominal Attenuation

Nominal Attenuation

		dB/100m															
		Frequency		10MHz	30MHz	72.0MHz	SMPTE 259M Composite NTSC	ITU-R BT.601 Composite PAL	SMPTE 259M Composite 4:2:2	SMPTE 259M Composite 4:2:16x9	SMPTE 344M 540Mb/s SDI		SMPTE 292M HD-SDI		SMPTE ST 424 3G-SDI		SMPTE ST 2082-1 12G-SDI
Model				10MHz	30MHz	72.0MHz	88.0MHz	135MHz	180MHz	270MHz	440MHz	750MHz	1.3GHz	1.5GHz	2.4GHz	3GHz	6GHz
75Ω	L-1.5C2VS/V*-1.5C	8.7	15.2	23.8	26.4	32.9	38.1	47.1	60.8	—	—	—	—	—	—	—	
	L-2.5CFB	4.8	7.6	11.3	12.4	15.1	17.4	21.5	27.8	37.0	50.0	54.1	70.5	80.2	121.8		
	L-2.5CHD/L-2.5CHLT	4.1	6.5	9.5	10.4	12.6	14.5	17.8	22.9	30.2	40.0	43.1	55.1	62.0	91.7		
	V4-2.5CHW	3.8	6.7	10.4	11.6	14.4	16.8	20.7	26.9	35.7	48.3	52.3	68.1	77.4	115.9		
	L-3C2V/L-3C2W	4.1	7.2	11.3	12.5	15.7	18.3	22.8	29.7	40.0	—	—	—	—	—		
	L-3C2VS/V*-3C	4.5	7.9	12.4	13.7	17.2	20.0	24.8	32.3	43.2	—	—	—	—	—		
	L-3CFB/V*-3CFB	3.7	5.9	8.7	9.5	11.7	13.5	16.7	21.7	29.1	39.6	43.0	56.5	64.5	93.5		
	L-3CFW/V*-3CFW	3.4	5.9	9.4	10.4	13.0	15.2	18.9	24.6	33.1	45.4	49.4	65.3	74.8	114.2		
	L-4CFB	3.0	4.8	7.1	7.8	9.5	11.0	13.6	17.7	23.6	31.9	34.6	45.2	51.5	76.9		
	V*-4CFB	3.0	4.9	7.2	7.9	9.7	11.2	13.9	18.1	24.3	33.2	36.0	47.5	54.3	83.8		
	L-4CHD	2.9	4.6	6.7	7.3	8.9	10.2	12.6	16.1	21.3	28.4	30.6	39.3	44.3	65.1		
	L-4.5CHD	2.3	3.7	5.4	6.0	7.2	8.3	10.2	13.2	17.4	23.2	25.1	32.3	36.5	53.6		
	L-4.5CHWS	2.5	4.3	6.7	7.4	9.3	10.7	13.3	17.2	22.8	30.8	33.3	43.3	49.1	79.3		
	L-5C2V/L-5C2W	2.5	4.5	7.1	7.9	9.9	11.6	14.4	19.0	25.7	35.6	38.9	52.0	59.9	—		
	L-5C2VS/V*-5C	2.9	5.2	8.1	9.0	11.4	13.3	16.5	21.7	29.2	40.5	44.1	58.7	67.5	—		
	L-5CFB/V*-5CFB	2.2	3.6	5.3	5.8	7.1	8.2	10.2	13.2	17.7	24.1	26.1	34.3	39.1	58.6		
	L-5CFW/V*-5CFW	2.1	3.6	5.6	6.2	7.8	9.0	11.2	14.5	19.4	26.2	28.4	37.1	42.2	70.5		
	L-5CHD	2.1	3.3	4.9	5.3	6.5	7.4	9.1	11.8	15.6	20.8	22.5	29.0	32.8	48.7		
	L-6CHD	1.7	2.7	3.9	4.3	5.2	6.0	7.4	9.7	12.9	17.5	19.0	24.8	28.3	42.0		
	L-7CFB	1.6	2.5	3.8	4.2	5.1	6.0	7.5	9.8	13.4	18.8	20.5	27.6	32.0	53.6		
	L-7CHD	1.4	2.3	3.3	3.6	4.4	5.1	6.3	8.2	10.9	14.7	15.9	20.7	23.5	34.4		
	L-8CHD	1.2	2.0	2.9	3.2	3.9	4.4	5.5	7.2	9.6	13.0	14.1	18.5	21.1	30.4		
50Ω	LV-61S	3.8	6.6	10.4	11.6	14.5	16.9	20.9	27.3	36.6	49.9	54.2	71.5	81.7	126.0		
	LV-77S	2.9	5.2	8.1	9.0	11.3	13.1	16.3	21.3	28.6	—	—	—	—	—		
	L-3D2V/L-3D2W	4.5	8.0	12.6	14.1	17.7	20.7	25.9	34.1	46.4	64.5	70.4	94.6	109.2	—		
50Ω	L-5D2V/L-5D2W	2.5	4.4	7.0	7.7	9.7	11.4	14.2	18.7	25.5	35.4	38.6	51.8	59.7	—		
	L-5DFB	2.5	3.9	5.7	6.2	7.5	8.6	10.8	14.1	19.0	26.1	28.4	37.7	43.2	—		

75 Ω Low Loss Coax Cable Attenuation Chart



Panels and Patchbays



75Ω Video Patchbays

75Ω Video Patchbays


3G-ready HD-SDI video patchbays featuring Canare's uniquely-developed rotary switches.

Model	Panel Size	Loaded Video Jacks
20DV	1RU	20 x DVJB-W
20DVS	1RU	20 x DVJB-S
20DV-2U	2RU	20 x DVJB-W
20DVS-2U	2RU	20 x DVJB-S
24DV	1RU	24 x DVJB-W
24DVS	1RU	24 x DVJB-S
24DV-2U	2RU	24 x DVJB-W
24DVS-2U	2RU	24 x DVJB-S
26DV	1RU	26 x DVJB-W
26DVS	1RU	26 x DVJB-S
26DV-2U	2RU	26 x DVJB-W
26DVS-2U	2RU	26 x DVJB-S

*Colors other than black are available on custom-made basis. (See page 69)



Return loss for DVJB-W



Isolation

75Ω Dual Video Jacks

Model	Description
DVJB-W	Normal Through
DVJB-S	Straight Through
VJ-DC	Dust Cap for Video Jack (color: black 40pcs)

Key Features and Benefits

- Rotary switch has been improved for superior isolation.
- Also usable as digital audio patchbay.
- Can be recessed 25mm.
- Wide designation strip (2RU type).
- Lightweight aluminum alloy video jacks.

Return Loss & Isolation

Model	Return Loss			Isolation
	BNC-BNC: Normal Through	BNC-VIDEO: Patch Through	BNC-Self Termination	
DVJB-W	26dB or greater (~750MHz)			35dB or greater (~1.5GHz) 20dB or greater (~3.0GHz)
	20dB or greater (~2.4GHz)			
	10dB or greater (~3.0GHz)			
DVJB-S	N/A	26dB or greater (~750MHz)	26dB or greater (~750MHz)	35dB or greater (~1.5GHz) 20dB or greater (~3.0GHz)
		20dB or greater (~2.4GHz)	20dB or greater (~1.5GHz)	
		10dB or greater (~3.0GHz)	10dB or greater (~3.0GHz)	

Technical Note

Rotary Switch Technology and Signal Routing Chart

At the heart of the video jack is an independently-developed rotary switch which has been specially designed for use with high frequency signals.

It features dual-contact construction for improved contact stability.



W Series (Normal Through)			
Video Port: No Patch		BNC Port: Signal thru as Arrowed	Signal routes between top and bottom BNC without the use of Video plugs.
Video Port: Patch Upper		BNC Port: Lower Terminated	Inserting a Video Patch Cord into front "upper" port automatically terminates signal path into the lower 75Ω load.
Video Port: Patch Lower		BNC Port: Upper Terminated	Inserting a Video Patch Cord into front "lower" port automatically terminates signal path into the upper 75Ω load.
Video Port: Patch Both		BNC Port: Signal thru as Arrowed	Inserting Video Patch Cords into both front ports inputs and/or outputs signal.

S Series (Straight Through)			
Video Port: No Patch		BNC Port: Both Signal Terminated	Two independent single jacks in a dual housing.
Video Port: Patch Upper		BNC Port: Lower Terminated	Inserting a Video Patch Cord into front "upper" port automatically terminates signal path into the lower 75Ω load.
Video Port: Patch Lower		BNC Port: Upper Terminated	Inserting a Video Patch Cord into front "lower" port automatically terminates signal path into the upper 75Ω load.
Video Port: Patch Both		BNC Port: Signal thru as Arrowed	Inserting Video Patch Cords into both front ports inputs and/or outputs signal.

75Ω Mid-size Video Patchbays

75Ω Staggered Mid-size Video Patchbays

3G-ready mid-size video jacks allow for more efficient use of rack space.

Model	Panel Size	Loaded Video Jacks
32MD-ST	1RU	32 x MDVJ-STW
32MD-STS	1RU	32 x MDVJ-STS
32MD-ST-2U	2RU	32 x MDVJ-STW
32MD-STS-2U	2RU	32 x MDVJ-STS
32MD-ST-4U	4RU	96 x MDVJ-STW
32MD-STS-4U	4RU	96 x MDVJ-STS

*Colors other than black are available on custom model basis except 4RU type (See page 69).


75Ω Staggered Mid-size Video Jacks

Model	Description
MDVJ-STW	Staggered Mid-size Video Jack, Normal Through
MDVJ-STS	Staggered Mid-size Video Jack, Straight Through
MVJ-DC	Dust cap for Mid-size video Jack (color: black 40pcs)



Key Features and Benefits

- 32 channels of I/O into 1RU or 2RU, 96 channels of I/O into 4RU.
- Rotary switch has been improved for superior isolation.
- Can be recessed 25mm (1RU, 2RU type).
- Wide designation strip (2RU, 4RU type).
- Lightweight aluminum alloy video jacks.
- Industry standard BNC plugs can be used.


Note : Be sure to use with Mini-Weco video plug.



32MD-STS



32MD-ST-4U



Return loss for MDVJ-STW

Return Loss & Isolation

Model	Return Loss			Isolation	
	BNC-BNC: Normal Through	BNC-VIDEO: Patch Through	BNC-Self Termination		
MDVJ-STW	26dB or greater (~750MHz) 20dB or greater (~2.4GHz) 10dB or greater (~3.0GHz)			35dB or greater (~1.5GHz) 20dB or greater (~3.0GHz)	
MDVJ-STS	N/A	26dB or greater (~750MHz)	26dB or greater (~750MHz)	35dB or greater (~1.5GHz) 20dB or greater (~3.0GHz)	
		20dB or greater (~2.4GHz)	20dB or greater (~1.5GHz)		
		10dB or greater (~3.0GHz)	10dB or greater (~3.0GHz)		

Panels and Patchbays

Video Plugs

Video Plug (W.E.Standard)

Model	Suitable Cable	Boot	Die Set
VWP-C4A	LV-61S, RG-59B/U, Belden 8241, 8279, 88241	CB04	TCD-451CA TCD-4CA


• Standard Package (20pcs)

- Gold-plated center contact resists deterioration over years of use.
- Solder center contact and crimp sleeve.

Be sure to use Canare crimping tool for installing connectors on cables.



VWP-C4A



VWP-C4A



Video Patch Cord
(see page 77)

Mini-WECO Video Plug

Model	Suitable Cable	Boot	Die Set
MVP-C4	LV-61S, RG-59B/U, Belden 8241, 8279, 88241	CB25	TCD-451CA TCD-4CA


• Standard Package (20pcs)

- Return loss: 26 dB or greater (DC - 1.5GHz), 20dB or greater (DC - 2.4GHz).
- Gold-plated center contact resists deterioration over years of use.
- Solder center contact and crimp sleeve.

Be sure to use Canare crimping tool for installing connectors on cables.



MVP-C4



MVP-C4



Mini-Weco Video Patch Cord
(see page 77)

Video Conversion Connectors


Model	Description
BCJ-VWP	BNC (female) - Video plug (W.E.Standard)
BCJ-MVP	BNC (female) - Mini-WECO Video plug

• Standard Package: BCJ-VWP (1pcs), BCJ-MVP (10pcs)

Note: BCJ-MVP is recommended to use with Slim BNC plug.




BCJ-VWP



BCJ-VWP



BCJ-MVP




BCJ-MVP


Ordering Information

Ordering Information

Standard Video Patchbays



Mid-size Video Patchbays




Note:

- 1) 4RU type is available in black color only
- 2) 4RU type can not be recessed.


Designation Strip Dimensions

1RU: 426mm x 6.2mm
 2RU: 420mm x 18.4mm
 4RU: 431.8mm x 13.2mm


32MD-ST-2U




20DV (1RU)




24DV (1RU)





26DV-2U (2RU)



32MD-ST



32MD-ST-4U



Panels and Patchbays


Unloaded Video Jack Panels, RS422 Patchbays

Unloaded Video Jack Panels


Model	Panel Size	Description
VJ2-V20-1U-***	1RU	20ch (40 holes), for DVJB
VJ2-V20-2U-***	2RU	20ch (40 holes), for DVJB
VJ2-V24-1U-***	1RU	24ch (48 holes), for DVJB
VJ2-V24-2U-***	2RU	24ch (48 holes), for DVJB
VJ2-V26-1U-***	1RU	26ch (52 holes), for DVJB
VJ2-V26-2U-***	2RU	26ch (52 holes), for DVJB
MJ2-M32-1U-***	1RU	32ch (64 holes), for MDVJ
MJ2-M32-2U-***	2RU	32ch (64 holes), for MDVJ
VJ2-M32-4U	4RU	96ch (3 x 32ch, 192 holes), for MDVJ (Color: Black)

*** : Please see the following ordering information for complete model number.


<Ordering Information>




VJ2-V24-1U-BLK



MJ2-M32-2U-BLK



VJ2-M32-4U



RS422 Patchbays

Model	Panel Size	Connectors	
		Front Panel	Rear Panel
RS-422-1U-16	1RU	Bantam	D sub 9P(F)×16
RS-422-1U-24	1RU	Bantam	D sub 9P(F)×24
RS-422-2U-32	2RU	Bantam	D sub 9P(F)×32
RS-422-2U-48	2RU	Bantam	D sub 9P(F)×48




● The RS422 serial signal used for VTR remote applications can now be switched with Bantam patchbay ease.

● D sub screws are M2.6


* Listed above items are other manufacturer's products.



RS-422-2U-48



RS-422-1U-24



RS-422-2U-48



RS422 Patch Cord
(See page 81)

Connector Panels

Pre-Loaded A/V Connector Panels

Key Features and Benefits

- Isolated BNC, RCA, F, XLR on same panel
- Clear plastic cover, full screen desi-strip
- Variety of panel options
- Most popular panel holes XLR F-77 and Neutrik D available

XLR Connector Panels

Type	Panel Size	Model	Loaded Connector	Panel P/N	Dimensions (mm)
161U-X12F	1RU	161U-X1F	XLR3-31F77 (16pcs)	1U-AS1	44 x 482.6 x 39.7
		161U-X2F	XLR3-32F77 (16pcs)		44 x 482.6 x 26.6
		161U-X12F	XLR3-31F77 (8pcs, Left) XLR3-32F77 (8pcs, Right)		44 x 482.6 x 39.7
		161U-B1	NC3FD-LX-B (16pcs)	1U-AS1D	44 x 482.6 x 31.3
		161U-B2	NC3MD-LX-B (16pcs)		44 x 482.6 x 23.6
162U-X21	2RU	162U-X21	XJ3M-P3FA (16pcs, Upper Row) XJ3F-P3MA (16pcs, Lower Row)	2U-AS7	88.1 x 482.6 x 217
		162U-X22	XJ3M-P3FA (32pcs, 2rows)		


BNC Connector Panels

Type	Panel Size	Model	Loaded Connector	Panel P/N	Dimensions (mm)
161U-JRU	1RU	161U-JRU	BCJ-JRU (16pcs)	1U-AS1	44 x 482.6 x 31.4
		161U-JRUDB	BCJ-JRUDB (16pcs)	1U-AS1D	44 x 482.6 x 29.1
	2RU	162U-JRU	BCJ-JRU (32pcs, 2rows)	2U-AS7	88.1 x 482.6 x 217


XLR3 Panel Mount Adapters

Model	Description		Flange Type
	Front	Rear	
XJ3M-P3FA	XLR 3pin (M)	XLR 3pin (F)	ITT XLR-F77
XJ3M-P3MA	XLR 3pin (M)	XLR 3pin (M)	
XJ3F-P3FA	XLR 3pin (F)	XLR 3pin (F)	
XJ3F-P3MA	XLR 3pin (F)	XLR 3pin (M)	


- XJ3 series are XLR3 full compatible.
- XLR jack to jack extremely reduce installation hours.




XJ3F-P3MA




XJ3M-P3MA




XJ3M-P3FA



XJ3M-P3MA



XJ3F-P3FA



XJ3F-P3MA

Blank Panels

Model	Description
BP-DXF (20pcs)	Snap-on blank panels for both ITT XLR-F77/Neutrik D holes
BP-XF (10pcs)	Blank panels for ITT XLR-F77 hole with screws
BP-D (10pcs)	Blank panels for Neutrik D hole with screws


BP-DXF

- Easy and quick snap-on mounting without any tools
- Can be used for both ITT XLR-F77 and Neutrik D holes

Note: Panel thickness range: t1.2 to t2.3 mm



BP-DXF



BP-XF

Panels and Patchbays

Connector Panels

Unloaded A/V Connector Panels

Panel Type	AS1 (D)	AS3 (D)	AS5 (D)	AS7 (D)
Description	Flat panel	Flat panel w/cable tie bar	Variable panel w/cable tie bar short type	Variable panel w/cable tie bar Long type
1RU 16 holes x 1 row	1U-AS1 (D)	1U-AS3 (D)	1U-AS5 (D)	1U-AS7 (D)
Depth (mm)	—	64.8	100	217
2RU 16 holes x 2 rows	2U-AS1 (D)	2U-AS3 (D)	2U-AS5 (D)	2U-AS7 (D)
Depth (mm)	—	64.8	100	217
3RU 16 holes x 3 rows	3U-AS1 (D)	3U-AS3 (D)	3U-AS5 (D)	3U-AS7 (D)
Depth (mm)	—	64.8	100	217

Variable panel can be recessed 25 mm.

Ordering Information

**Panel Height,
Number of holes and Rows**

1U	1RU, 16holes, 1row
2U	2RU, 32holes, 2rows
3U	3RU, 48holes, 3rows

1U - AS3 D

Hole Type

Blank	ITT XLR-F77 Type
D	Neutrik D Type

Panel Type

AS1	Flat panel
AS3	Flat panel w/cable tie bar
AS5	Variable panel w/ cable tie bar - short depth
AS7	Variable panel w/ cable tie bar - long depth


NOTE:

- Depending on their length, some connectors can not be mounted on the panel with a cable tie bar installed.


Related Products

Model	Description
M-MA1U02	1RU mounting brackets for a Variable panel, 2 pcs. (left and right)
M-MA2U02	2RU mounting brackets for a Variable panel, 2 pcs. (left and right)
M-MA3U02	3RU mounting brackets for a Variable panel, 2 pcs. (left and right)
DS10-AS4	Designation strip for Canare A/V connector panels, 2 pcs.


Examples of Custom-Made Connector Panels



1U-AS3 + XLR3-31F77 × 16



2U-AS7 + XLR3-32F77 × 16
XLR3-31F77 × 16



2U-AS7 (box type)
Connectors can be mounted on the both side.

■ Connectors

Canare Flush-mount BNC, F, RCA and XLR (ITT XLR-F77 or Neutrik D type) are available.

■ Options


- A) Rear Panel A connector panel can be mounted on the rear.
- B) Box Type A connector panel, top plate and bottom plate can be mounted on the rear.
- C) Recessed Variable panel can be recessed 25mm by changing the screw positions of the mounting brackets and can be recessed either 50mm or 75mm by changing the mounting brackets to M-MA*U02.

Options	AS1 (D)	AS3 (D)	AS5 (D)	AS7 (D)
A) Rear Panel	N/A	N/A	Available	Available
B) Box Type	N/A	N/A	N/A	Available
C) Recesed	N/A	N/A	Available	Available

Audio Patchbays

Audio Patchbays

The gold alloy cross bar contact, which features a low faulty contact rate, is used for the jacks.



- 481U patchbay can be recessed 25mm by changing the screw positions on the mounting brackets.



Model	Description	Connector
481U-820AQ	Bantam Patchbay	820AQ×96

Model	Description	Connector
48-12A/820AQ/EIA	Bantam Patchbay	820AQ×96
32-12A/620A/EIA	Skin Patchbay	620A×64
612A/320A/EIA	Maxi Patchbay	320A×52

* Listed above items are other manufacturer's products.

Audio Patchbays Related Products

Model	Description
320A	Maxi Jack
620A	Skin Jack
820AQ	Bantam Jack
ABJ-DC	Bantam Jack Dust Cap (100pcs/pkg)
NP3TMC-B	Maxi/Skin Plug
PJ743	Bantam Termination Plug (600Ω)
PJ748	Bantam Dummy Plug
6000AQ	Polysand for PJ743
PH50-A	Maxi/Skin/Video Patch Cord Holder
PH50-B	Bantam Patch Cord Holder
DS10-AS1	Designation Strip for Bantam (2pcs.)
DS10-AS2	Designation Strip for Skin (2pcs.)
DS10-AS3	Designation Strip for Maxi (2pcs.)

* Listed above items are other manufacturer's products.


Technical Note

Audio Patchbay Normaling Descriptions

Output from a device is obtained from the upper row, while input to a device is normally connected to the lower row.
Users can select from the following three types of connecting functions.

<Wiring formats connecting upper and lower connectors>


F: Full normal connection



Full Normal Format (series)

The upper (output) row is connected to the lower row (input) in the state when a plug is not inserted.
When a plug is inserted in the upper jack to obtain a signal, the signal is not connected to the lower jack. A signal can be entered by inserting a plug in the lower jack. In this case the signal is not connected to the upper jack.


H: Half normal connection



Half Normal Format (half-parallel)

The upper (output) row is connected to the lower row (input) in the state when a plug is not inserted.
When a plug is inserted in the upper jack to obtain a signal, the signal is connected to the lower jack. This format allows the signal to be obtained in parallel. The signal can be prevented from going to the lower jack by inserting a dummy plug.
Signals are input by inserting a plug in the lower jack. In this case the signal is not connected to the upper jack.

W: Double normal connection



Double Normal Format (series-parallel)

The upper (output) row is connected to the lower row (input) in the state when a plug is not inserted.
When a plug is inserted in the upper jack to obtain a signal, the signal is connected to the lower jack. This format allows the signal to be obtained in parallel. The signal can be prevented from going to the lower jack by inserting a dummy plug.
A signal can be entered by inserting another plug in the lower jack. Note that the signal in this case is connected to the upper jack.
This can be prevented by inserting a dummy plug.




Bantam patch panel 481U-820AQ




Bantam patch panel 48-12A/820AQ/EIA




BC * M
(See page 84 for patch cords.)




481U-820AQ



48-12A/820AQ/EIA



32-12A/620A/EIA




612A/320A/EIA

Bantam Jack 820AQ




Panel Hole Dimensions

Skin Jack 620A




Panel Hole Dimensions

Maxi Jack 320A



Panel Hole Dimensions

Patch Cord Holder



Capable up to 50 patch cords.
Easy to install on the wall or side of rack.
PH50-A
for Maxi/Skin, Video cords.
PH50-B
for Bantam cords.

Polysand 6000AQ (for PJ743)

Quickly and effectively removes oxide on brass plugs.
Comes in 286x150mm size.



Panels and Patchbays

Audio Patchbays

■ Wired Box

Type	Model	Size	Connector	
			Front	Rear
Bantam	481U-WBF	1RU	820AQ × 96	90-602 × 4
	481U-WBH	1RU	820AQ × 96	90-602 × 4
	481U-WBW	1RU	820AQ × 96	90-602 × 4
	481U-WBS	1RU	820AQ × 96	90-602 × 4
	48WB-F	1RU	820AQ × 96	90-602 × 4
	48WB-H	1RU	820AQ × 96	90-602 × 4
	48WB-W	1RU	820AQ × 96	90-602 × 4
Skinny	32WB-F	1RU	620A × 64	90-602 × 4
	32WB-H	1RU	620A × 64	90-602 × 4
	32WB-W	1RU	620A × 64	90-602 × 4
Maxi	26WB-F	1RU	320A × 52	90-602 × 4
	26WB-H	1RU	320A × 52	90-602 × 4
	26WB-W	1RU	320A × 52	90-602 × 4

481U-WB can be recessed 25mm

*90-602 connector is identical to
ELCO 00-8016-090-***-702V connector



90-602



Bantam wired box 481U-WB*



Bantam wired box 48WB-*



Maxi wired box 26WB-*



Skinny wired panel 32XP-*

Normalizing Options			
481U-WB*	F: Full normal		
48WB-*	H: Half normal		
48XP-*	W: Double normal		
	S: Single (No normal)		



(See page 84 for patch cords)

90-602 Connector Format (Wired box)

<Rear panel>



Bantam	Lower row 25~48ch	Upper row 25~48ch	Lower row 1~24ch	Upper row 1~24ch
Skinny	Lower row 17~32ch	Upper row 17~32ch	Lower row 1~16ch	Upper row 1~16ch
Maxi	Lower row 14~26ch	Upper row 14~26ch	Lower row 1~13ch	Upper row 1~13ch

90-602 connector is mated with 90-608 connector.

90-608 requires either 125 or 525 contact and 90-T cover for assembling.

<Wired box side>

90-602

(00-8016-090-000-702V)

<Cable side>

90-608 (00-8016-090-000-708V)

- Contact — 125 : Solder type (60-8016-0513-00-339)
- Contact — 525 : Crimp type (60-8016-0313-00-339)
- Cover — 90-T : Top entrance (30-8016-090-T)

*The numbers in parentheses are ELCO ordering codes.

** Contact extraction tool: 06-1877-04.


Crimping pliers for 525: 06-1001-015 (AWG#18), 06-1001-016 (AWG#20-#22), 06-1001-017 (AWG#24-#26).

Wiring Table for 90-602

Channel no.	Maxi		Skinny		Bantam		HOT	COLD	SHIELD
	1	14	1	17	1	25			
1	2	15	2	18	2	26	B	J	S
2	3	16	3	19	3	27	C	K	T
3	4	17	4	20	4	28	D	L	U
4	5	18	5	21	5	29	E	M	V
5	6	19	6	22	6	30	F	N	W
6	7	20	7	23	7	31	X	AE	AM
7	8	21	8	24	8	32	Y	AF	AN
8	9	22	9	25	9	33	Z	AH	AP
9	10	23	10	26	10	34	AA	AJ	AR
10	11	24	11	27	11	35	AB	AK	AS
11	12	25	12	28	12	36	AC	AL	AT
12	13	26	13	29	13	37	BJ	BS	BY
13			14	30	14	38	BK	BT	BZ
			15	31	15	39	BL	BU	CA
			16	32	16	40	BM	BV	CB
					17	41	BN	BW	CC
					18	42	BP	BX	CD
					19	43	CF	CN	CW
					20	44	CH	CP	CX
					21	45	CJ	CR	CY
					22	46	CK	CS	CZ
					23	47	CL	CT	DA
					24	48	CM	CU	DB



■ Snake Trunk



■ Junction Box




■ Fantail



■ Cable Reel Snake

■ System Example




■ Connectors used with Canare multichannel cable system

Cable mount	Panel mount	Cable mount	Panel mount
XLR3-11C (female)	XLR3-32F77 (male)	XLR3-12C (male)	XLR3-31F77 (female)
For multichannel cable	For Junction box	For multichannel cable	For Junction box
NK27-21C-R (female) + NK-AD1-R (barrel extension)	NK27-32S-R (male)	FK37-21C-R (female) + FK-AD2-R (barrel extension)	FK37-32S-R (male)
NK27-22C-R (male) + NK-AD1-R (barrel extension)	NK27-31S-R (female)	FK37-22C-R (male) + FK-AD2-R (barrel extension)	FK37-31S-R (female)
D/MS3106B32A-10S (female) + EB-02 (barrel extension) + D/MS3057-20A (cable clamp)	D/MS3102A32A-10P (male)	D/MS3106B36-73S (female) + EB-03 (barrel extension) + D/MS3057-24A (cable clamp)	D/MS3102A36-73P (male)
8 • 12 ch	24 ch	16 ch	32 ch

8 CH		Snake Trunks			Cable Reel Snakes																																									
L-4E3 Star quad, Braided shield		M2 Two-cord, AT shield																																												
connector : NK27-21C 3/4-R, NK27-22C 3/4-R cable : L-4E3-3P (black) rubber bushing : AN3420-12 + Heat Shrink Tube		connector : NK27-21C 3/4-R, NK27-22C 3/4-R cable : M202-8AT (black) rubber bushing : AN3420-10, 12 + Heat Shrink Tube			connector : NK27-21C-3/4-R cable : L-4E3-8P (black)																																									
<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>8C05-E3</td><td>5m</td><td>1.6kg</td></tr> <tr> <td>8C10-E3</td><td>10m</td><td>3.0kg</td></tr> <tr> <td>8C30-E3</td><td>30m</td><td>8.4kg</td></tr> <tr> <td>8C50-E3</td><td>50m</td><td>13.8kg</td></tr> </tbody> </table>	Model	Length	Weight	8C05-E3	5m	1.6kg	8C10-E3	10m	3.0kg	8C30-E3	30m	8.4kg	8C50-E3	50m	13.8kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>8C10-M2</td><td>10m</td><td>1.7kg</td></tr> <tr> <td>8C30-M2</td><td>30m</td><td>4.5kg</td></tr> <tr> <td>8C50-M2</td><td>50m</td><td>7.3kg</td></tr> </tbody> </table>	Model	Length	Weight	8C10-M2	10m	1.7kg	8C30-M2	30m	4.5kg	8C50-M2	50m	7.3kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th><th>Cable reel</th></tr> </thead> <tbody> <tr> <td>8R30-E3</td><td>30m</td><td>18.1kg</td><td>R380</td></tr> <tr> <td>8R50-E3</td><td>50m</td><td>23.0kg</td><td>R380</td></tr> </tbody> </table>	Model	Length	Weight	Cable reel	8R30-E3	30m	18.1kg	R380	8R50-E3	50m	23.0kg	R380			
Model	Length	Weight																																												
8C05-E3	5m	1.6kg																																												
8C10-E3	10m	3.0kg																																												
8C30-E3	30m	8.4kg																																												
8C50-E3	50m	13.8kg																																												
Model	Length	Weight																																												
8C10-M2	10m	1.7kg																																												
8C30-M2	30m	4.5kg																																												
8C50-M2	50m	7.3kg																																												
Model	Length	Weight	Cable reel																																											
8R30-E3	30m	18.1kg	R380																																											
8R50-E3	50m	23.0kg	R380																																											
12 CH																																														
connector : NK27-21C 7/8-R, NK27-22C 7/8-R cable : L-4E3-12P (black) rubber bushing : AN3420-16		connector : NK27-21C 3/4-R, NK27-22C 3/4-R cable : M202-12AT (black) rubber bushing : AN3420-10, 12 + Heat Shrink Tube		connector : NK27-21C-7/8-R cable : L-4E3-12P (black)																																										
<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>12C05-E3</td><td>5m</td><td>2.1kg</td></tr> <tr> <td>12C10-E3</td><td>10m</td><td>3.9kg</td></tr> <tr> <td>12C30-E3</td><td>30m</td><td>11.1kg</td></tr> <tr> <td>12C50-E3</td><td>50m</td><td>18.3kg</td></tr> </tbody> </table>	Model	Length	Weight	12C05-E3	5m	2.1kg	12C10-E3	10m	3.9kg	12C30-E3	30m	11.1kg	12C50-E3	50m	18.3kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>12C10-M2</td><td>10m</td><td>2.1kg</td></tr> <tr> <td>12C30-M2</td><td>30m</td><td>5.8kg</td></tr> <tr> <td>12C50-M2</td><td>50m</td><td>9.3kg</td></tr> </tbody> </table>	Model	Length	Weight	12C10-M2	10m	2.1kg	12C30-M2	30m	5.8kg	12C50-M2	50m	9.3kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th><th>Cable reel</th></tr> </thead> <tbody> <tr> <td>12R30-E3</td><td>30m</td><td>20.6kg</td><td>R380</td></tr> <tr> <td>12R50-E3</td><td>50m</td><td>30.4kg</td><td>R460</td></tr> </tbody> </table>	Model	Length	Weight	Cable reel	12R30-E3	30m	20.6kg	R380	12R50-E3	50m	30.4kg	R460			
Model	Length	Weight																																												
12C05-E3	5m	2.1kg																																												
12C10-E3	10m	3.9kg																																												
12C30-E3	30m	11.1kg																																												
12C50-E3	50m	18.3kg																																												
Model	Length	Weight																																												
12C10-M2	10m	2.1kg																																												
12C30-M2	30m	5.8kg																																												
12C50-M2	50m	9.3kg																																												
Model	Length	Weight	Cable reel																																											
12R30-E3	30m	20.6kg	R380																																											
12R50-E3	50m	30.4kg	R460																																											
16 CH																																														
connector : FK37-21C 7/8-R, FK37-22C 7/8-R cable : L-4E3-16P (black) rubber bushing : AN3420-16		connector : FK37-21C 7/8-R, FK37-22C 7/8-R cable : M202-16AT (black) rubber bushing : AN3420-10, 12, 16		connector : FK37-21C-7/8-R cable : L-4E3-16P (black)																																										
<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>16C05-E3</td><td>5m</td><td>2.6kg</td></tr> <tr> <td>16C10-E3</td><td>10m</td><td>4.9kg</td></tr> <tr> <td>16C30-E3</td><td>30m</td><td>14.1kg</td></tr> <tr> <td>16C50-E3</td><td>50m</td><td>23.3kg</td></tr> </tbody> </table>	Model	Length	Weight	16C05-E3	5m	2.6kg	16C10-E3	10m	4.9kg	16C30-E3	30m	14.1kg	16C50-E3	50m	23.3kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>16C10-M2</td><td>10m</td><td>2.7kg</td></tr> <tr> <td>16C30-M2</td><td>30m</td><td>7.5kg</td></tr> <tr> <td>16C50-M2</td><td>50m</td><td>12.3kg</td></tr> </tbody> </table>	Model	Length	Weight	16C10-M2	10m	2.7kg	16C30-M2	30m	7.5kg	16C50-M2	50m	12.3kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th><th>Cable reel</th></tr> </thead> <tbody> <tr> <td>16R30-E3</td><td>30m</td><td>24.1kg</td><td>R380</td></tr> <tr> <td>16R50-E3</td><td>50m</td><td>36.1kg</td><td>R460</td></tr> </tbody> </table>	Model	Length	Weight	Cable reel	16R30-E3	30m	24.1kg	R380	16R50-E3	50m	36.1kg	R460			
Model	Length	Weight																																												
16C05-E3	5m	2.6kg																																												
16C10-E3	10m	4.9kg																																												
16C30-E3	30m	14.1kg																																												
16C50-E3	50m	23.3kg																																												
Model	Length	Weight																																												
16C10-M2	10m	2.7kg																																												
16C30-M2	30m	7.5kg																																												
16C50-M2	50m	12.3kg																																												
Model	Length	Weight	Cable reel																																											
16R30-E3	30m	24.1kg	R380																																											
16R50-E3	50m	36.1kg	R460																																											
24 CH																																														
connector : D/MS3106B-32A10S+D/MS3057-20A×2 cable : L-4E3-24P (black) rubber bushing : AN3420-20		connector : D/MS3106B-32A10S+D/MS3057-20A×2 cable : M202-24AT (black) rubber bushing : AN3420-16, 20 + Heat Shrink Tube		connector : D/MS3106B-32A10S cable : L-4E3-24P (black)																																										
<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>24C05-E3</td><td>5m</td><td>4.3kg</td></tr> <tr> <td>24C10-E3</td><td>10m</td><td>7.7kg</td></tr> <tr> <td>24C30-E3</td><td>30m</td><td>21.7kg</td></tr> <tr> <td>24C50-E3</td><td>50m</td><td>35.7kg</td></tr> </tbody> </table> <p>Extension Cord : D/MS3101A32A10P+D/MS3057-20AX2 Cable : L-4E3-24P (black)</p> <p>24C005-E3MS22</p>	Model	Length	Weight	24C05-E3	5m	4.3kg	24C10-E3	10m	7.7kg	24C30-E3	30m	21.7kg	24C50-E3	50m	35.7kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>24C10-M2</td><td>10m</td><td>4.0kg</td></tr> <tr> <td>24C30-M2</td><td>30m</td><td>10.4kg</td></tr> <tr> <td>24C50-M2</td><td>50m</td><td>16.8kg</td></tr> </tbody> </table> <p>24C005-E3MS22</p>	Model	Length	Weight	24C10-M2	10m	4.0kg	24C30-M2	30m	10.4kg	24C50-M2	50m	16.8kg		<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th><th>Cable reel</th></tr> </thead> <tbody> <tr> <td>24R30-E3</td><td>30m</td><td>34.6kg</td><td>R460</td></tr> </tbody> </table>	Model	Length	Weight	Cable reel	24R30-E3	30m	34.6kg	R460							
Model	Length	Weight																																												
24C05-E3	5m	4.3kg																																												
24C10-E3	10m	7.7kg																																												
24C30-E3	30m	21.7kg																																												
24C50-E3	50m	35.7kg																																												
Model	Length	Weight																																												
24C10-M2	10m	4.0kg																																												
24C30-M2	30m	10.4kg																																												
24C50-M2	50m	16.8kg																																												
Model	Length	Weight	Cable reel																																											
24R30-E3	30m	34.6kg	R460																																											
32 CH																																														
connector : D/MS3106B36-73S+D/MS3057-24A×2 cable : M202-32AT (black) rubber bushing : AN3420-16, 20, 24		connector : D/MS3101A36-73P+D/MS3057-24A×2 cable : M202-32AT (black)																																												
<table border="1"> <thead> <tr> <th>Model</th><th>Length</th><th>Weight</th></tr> </thead> <tbody> <tr> <td>32C10-M2</td><td>10m</td><td>4.8kg</td></tr> <tr> <td>32C30-M2</td><td>30m</td><td>13.1kg</td></tr> <tr> <td>32C50-M2</td><td>50m</td><td>21.0kg</td></tr> </tbody> </table> <p>Extension Cord : D/MS3101A36-73P+D/MS3057-24A×2 Cable : M202-32AT (black)</p> <p>32C005-M2MS22</p>	Model	Length	Weight	32C10-M2	10m	4.8kg	32C30-M2	30m	13.1kg	32C50-M2	50m	21.0kg																																		
Model	Length	Weight																																												
32C10-M2	10m	4.8kg																																												
32C30-M2	30m	13.1kg																																												
32C50-M2	50m	21.0kg																																												

Note: Connecting cables 24C005-E3MS22 and 32C005-M2MS22 are to be used to interconnect snake trunks only and they do not mate with our other standard snake system.





Fantails, Junction Boxes

Fantails	Junction Boxes		
8S1N2 Connector : XLR3-11C x8, NK27-22C-3/4-R Cable : L-4E6S (black) 1.5m Weight : 1.1kg	Single XLR per channel 8B1N2 Connector: XLR3-31F77 x8, NK27-32S-R x1 Weight : 0.9kg	Parallel XLR per channel 8J12N2 Connector: XLR3-31F77 x8, XLR3-32F77 x8 NK27-32S-R x1 Weight : 1.5kg	Parallel XLR per channel MultiPin feed through 8J12N12 Connector: XLR3-31F77 x8, XLR3-32F77 x8 NK27-31S-R x1, NK27-32S-R x1 Weight : 1.6kg
8S2N1 Connector : XLR3-12C x8, NK27-21C-3/4-R Cable : L-4E6S (black) 1.5m Weight : 1.0kg	 8B2N1 Connector: XLR3-32F77 x8, NK27-31S-R x1 Weight : 1.1kg	 8J12N1 Connector: XLR3-31F77 x8, XLR3-32F77 x8 NK27-31S-R x1 Weight : 1.5kg	
12S1N2 Connector : XLR3-11C x12, NK27-22C-3/4-R Cable : L-4E5C (black) 1.5m Weight : 1.4kg	 12B1N2 Connector: XLR3-31F77 x12, NK27-32S-R x1 Weight : 1.3kg	 12J12N2 Connector: XLR3-31F77 x12, XLR3-32F77 x12 NK27-32S-R x1 Weight : 2.1kg	 12J12N12 Connector: XLR3-31F77 x12, XLR3-32F77 x12 NK27-31S-R x1, NK27-32S-R x1 Weight : 2.2kg
12S2N1 Connector : XLR3-12C x12, NK27-21C-3/4-R Cable : L-4E5C (black) 1.5m Weight : 1.3kg	 12B2N1 Connector: XLR3-32F77 x12, NK27-31S-R x1 Weight : 1.2kg	 12J12N1 Connector: XLR3-31F77 x12, XLR3-32F77 x12 NK27-31S-R x1 Weight : 2.1kg	
16S1F2 Connector : XLR3-11C x16, FK37-22C-7/8-R Cable : L-4E5C (black) 1.5m Weight : 1.9kg	 16B1F2 Connector: XLR3-31F77 x16, FK37-32S-R x1 Weight : 1.6kg	 16J12F2 Connector: XLR3-31F77 x16, XLR3-32F77 x16 FK37-32S-R x1 Weight : 2.5kg	 16J12F12 Connector: XLR3-31F77 x16, XLR3-32F77 x16 FK37-31S-R x1, FK37-32S-R x1 Weight : 2.6kg
16S2F1 Connector : XLR3-12C x16, FK37-21C-7/8-R Cable : L-4E5C (black) 1.5m Weight : 1.7kg	 16B2F1 Connector: XLR3-32F77 x16, FK37-31S-R x1 Weight : 1.3kg	 16J12F1 Connector: XLR3-31F77 x16, XLR3-32F77 x16 FK37-31S-R x1 Weight : 2.5kg	
24S1MS2 Connector : XLR3-11C x24, D/MS3101A-32A-10P Cable : L-4E5C (black) 2m		 24B12MS Connector: XLR3-31F77 x24 (on top) XLR3-32F77 x24 (12 on each side) D/MS3102A-32A10P Weight : 2.7kg	 24B12MSW Connector: XLR3-31F77 x24 (on top) XLR3-32F77 x24 (12 on each side) D/MS3102A-32A10P x2 Weight : 3.0kg
24S2MS2 Connector : XLR3-12C x24, D/MS3101A-32A-10P Cable : L-4E5C (black) 2m			
32S1MS2 Connector : XLR3-11C x32, D/MS3101A-36-73P Cable : L-4E5C (black) 2m		 32B12MS Connector: XLR3-31F77 x32, XLR3-32F77 x32 D/MS3102A36-73P Weight : 5.3kg	 32B12MSW Connector: XLR3-31F77 x32, XLR3-32F77 x32 D/MS3102A36-73P x2 Weight : 5.5kg
32S2MS2 Connector : XLR3-12C x32, D/MS3101A-36-73P Cable : L-4E5C (black) 2m		 32B12MWF1 Connector: XLR3-31F77 x32, XLR3-32F77 x32 D/MS3102A36-73P x2, FK37-31S-R x2 Weight : 6.0kg	 32B12MF1 Connector: XLR3-31F77 x32, XLR3-32F77 x32 D/MS3102A36-73P x1, FK37-31S-R x2 Weight : 5.7kg

Pin Assignments

Multichannel Connector Pin Assignments

Ch No.	Cable Unit Identification		32ch		24ch		16ch		8ch / 12ch	
	L-4E3	M202	D/MS3102A36-73	D/MS3102A32A-10	D/MS3106B36-73	D/MS3106B32A-10	FK37		NK27	
	Spiral Marker Color	Insulator Color	Identifying Color	Common Identifying Color	HOT	COLD	HOT	COLD	HOT	COLD
1	RED	RED • WHT	A	B	A	B	1	2	1	3
2	BLU	BLU •	C	D	C	D	3	4	4	5
3	YEL	YEL •	F	H	F	G	5	6	6	7
4	GRN	GRN •	J	K	H	J	8	9	8	9
5	BRN	BRN •	L	M	K	L	10	11	11	12
6	N/A	GRY • ▼	N	P	N	O	12	13	13	14
7	BLU • BLK	BLU • BLK	R	S	P	R	14	15	15	16
8	YEL • BLK	YEL •	T	U	S	T	16	17	17	18
9	GRN • BLK	GRN •	V	W	U	V	21	22	19	20
10	BRN • BLK	BRN •	Y	Z	X	Y	23	24	22	23
11	BLK	GRY • ▼	a	b	Z	a	25	26	24	25
12	BLU • ORN	BLU • ORN	c	d	b	c	27	28	26	27
13	YEL • ORN	YEL •	f	g	d	e	29	30	SHIELD	
14	GRN • ORN	GRN •	h	i	g	h	32	33	SHIELD	
15	BRN • ORN	BRN •	j	k	j	k	34	35	SHIELD	
16	ORN	GRY • ▼	m	n	m	n	36	37	SHIELD	
17	BLU • PNK	BLU • PNK	u	v	p	q	SHIELD			19
18	YEL • PNK	YEL •	w	x	s	t	SHIELD			
19	GRN • PNK	GRN •	y	z	u	v	SHIELD			
20	BRN • PNK	BRN •	AA	AB	w	x	SHIELD			
21	PNK	GRY • ▼	AC	AD	AB	z	SHIELD			
22	BLU • WHT	BLU • RED	AE	AF	AA	AC	SHIELD			
23	YEL • WHT	YEL •	AH	AJ	AD	AF	SHIELD			
24	GRN • WHT	GRN •	AL	AM	AG	AE	SHIELD			
25	—	BRN •	AN	AP	SHIELD			SHIELD		
26	—	GRY • ▼	AR	AS	SHIELD			SHIELD		
27	—	YEL • BLU	AT	AU	SHIELD			SHIELD		
28	—	GRN •	AV	AW	SHIELD			SHIELD		
29	—	BRN • ▼	AX	AY	SHIELD			SHIELD		
30	—	GRN • YEL	AZ	BA	SHIELD			SHIELD		
31	—	BRN •	BC	BD	SHIELD			SHIELD		
32	—	GRY • ▼	BE	BF	SHIELD			SHIELD		
		SHIELD		E	q	t	SHIELD			
		SHIELD		X	r	AK	SHIELD			
		SHIELD		p	s	BB	SHIELD			




32ch
24ch
16ch
8-12ch

■ Connection Method

L-4E3 Types:

Identify the channel number by the color of the spiral marker on the inner jacket (gray). The unit is 4-core construction and the insulator colors are blue, blue, white, and white. Connect these with the same colored cores, so that the blue cores are connected to Hot and the white cores to Cold.



M202 Types:

The unit is 2-core construction, with the channel number identified by the insulator color (a combination of the identifying color and common identifying color). Connect the identifying color core to Hot, and the common identifying color core to Cold.

■ Connections to XLR Connectors

Polarity	HOT	COLD	SHIELD
Pin No.	2	3	1

Reels

Cable Reels

Plain reels for winding cable

Model	Weight (kg)	Description	Stackability
R460-S	9.9	Reel unit for cable winding / With caster.	N/A
R380-S	8.3	Reel unit for cable winding / With caster.	N/A
R300-S	4.3	Reel unit for cable winding.	✓
R300	4.3	Front panel can be refurbished to create connector mounting holes.	✓
R300-L	4.3	Both front panel and drum can be refurbished to create connector mounting holes.	✓
R300-CN	4.3	Both panel and drum have 2 XLR connectors (one male, one female) installed.	✓
R300-BN	4.3	Both panel and drum have BNC receptacles (one each).	✓

● 3-speed brake controller. (Lock/Soft/Free)


● Non-lubricated bearings.

● Rugged E frame design.



R460-S

Wiring



R300-CN



R300-BN



3-speed brake controller




R300-S

Reel with Cable Assembly


Cable detachable type.

Model	Description			Weight (kg)	
	Cable reel	Cable Assemblies			
		Inner end	Cable		
CR100-CN	R300-CN	XLR3-12C	L-4E6S(100m)	XLR3-11C	9.6
CR100-S	R300-S	XLR3-12C	L-4E6S(100m)	XLR3-11C	9.6
CR90-BN	R300-BN	BCP-H5B	L-5C2VS(90m)	BCP-H5B	10.5

Dimensions




R460-S




R300

(Connectors can be attached to the front panel)




R380-S



R300-L


(Connectors can be attached to the front panel and the drum)



R300-S

(R300-BN comes with BNC receptacles)

Cable winding length reference chart



<Wind length conversion formula>

$$R300-S \quad L = \frac{8448}{D^2} \times 0.6 \text{ (m)} \quad R460-S \quad L = \frac{33852}{D^2} \times 0.6 \text{ (m)}$$

$$R380-S \quad L = \frac{18207}{D^2} \times 0.6 \text{ (m)} \quad D: \text{cable outer diameter (mm)}$$

Cable Assemblies

BNC, DIN

- High quality and reliable Canare assemblies are ideal for any interconnection including broadcast, professional A/V, and telecommunication.
- Custom assembly configurations can be special ordered at affordable cost and quick lead-time.



BNC

Type	Model	Length (m)
BNC (M) – BNC (M) Crimp	D3C005A-S	0.5
BCP-A3 L-3C2VS BCP-A3	D3C01A-S	1
	D3C02A-S	2
	D3C03A-S	3
	D3C05A-S	5
	D3C10A-S	10
BNC (M) – BNC (M) Crimp	D5C005A-S	0.5
BCP-A5 L-5C2VS BCP-A5	D5C01A-S	1
	D5C015A-S	1.5
	D5C03A-S	3
	D5C05A-S	5
	D5C10A-S	10
	D5C15A-S	15
	D5C20A-S	20
BNC (M) – BNC (M) Crimp	D3FBC005E	0.5
BCP-B3F L-3CFB BCP-B3F	D3FBC01E	1
	D3FBC015E	1.5
	D3FBC02E	2
	D3FBC03E	3
	D3FBC05E	5
	D3FBC10E	10
BNC (M) – BNC (M) Crimp	D2.5HDC005E	0.5
BCP-B25HD L-2.5CHD BCP-B25HD	D2.5HDC01E	1
	D2.5HDC015E	1.5
	D2.5HDC02E	2
	D2.5HDC03E	3
	D2.5HDC05E	5
	D2.5HDC10E	10
BNC (M) – BNC (M) Crimp	D4.5HDC03E	3
BCP-B53 L-4.5CHD BCP-B53	D4.5HDC05E	5
	D4.5HDC10E	10
	D4.5HDC15E	15
	D4.5HDC20E	20

BNC-DIN

Type	Model	Length (m)
BNC (M) – DIN (M) Crimp	D2.5HDC005E-D	0.5
BCP-B25HD L-2.5CHD DCP-C25HD	D2.5HDC01E-D	1
	D2.5HDC015E-D	1.5
	D2.5HDC02E-D	2
	D2.5HDC03E-D	3
	D2.5HDC05E-D	5
	D2.5HDC10E-D	10
BNC (M) – DIN (M) Crimp	D4.5HDC03E-D	3
BCP-B53 L-4.5CHD DCP-C53	D4.5HDC05E-D	5
	D4.5HDC10E-D	10
	D4.5HDC15E-D	15
	D4.5HDC20E-D	20

BNC-RCA

Type	Model	Length (m)
BNC (M) – RCA (M)	D3C01A-SR	1
BCP-A3 L-3C2VS F-09	D3C03A-SR	3
	D3C05A-SR	5

DIN

Type	Model	Length (m)
DIN (M) - DIN (M) Crimp	DN2.5HDC005	0.5
DCP-C25HD L-2.5CHD DCP-C25HD	DN2.5HDC01	1
	DN2.5HDC015	1.5
	DN2.5HDC02	2
	DN2.5HDC03	3
	DN2.5HDC05	5
	DN2.5HDC10	10
BNC (M) - BNC (M) Crimp	DN4.5HDC03	3
DCP-C53 L-4.5CHD DCP-C53	DN4.5HDC05	5
	DN4.5HDC10	10
	DN4.5HDC15	15
	DN4.5HDC20	20



DN2.5HDC

RCA (Video)

Type	Model	Length (m)
RCA (M) – RCA (M) Solder F-09 L-3C2VS F-09  BLK BRN RED ORN YEL GRN BLU GRY WHT	DRC01-S	1
	DRC03-S	3
	DRC05-S	5
RCA (M) – RCA (M) Crimp RCAP-C3F L-3CFB RCAP-C3F  BLK RED YEL GRN BLU WHT	DRC10-F3	10
	DRC15-F3	15
	DRC20-F3	20
	DRC30-F3	30
	DRC40-F3	40

Video Patch (W.E. standard)

Type	Model	Length (m)
Video Patch (M) – Video Patch (M) VWP-C4A LV-61S VWP-C4A  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	VPC003-WC	0.3
	VPC005-WC	0.5
	VPC01-WC	1




VPC003-WC

Triax

Cables used for connections such as those between broadcast cameras and CCUs.

Type	Model	Length (m)
Triaxial (F) – Triaxial (M) U.S. preferred type	TXC10-K	10
CCF4-JK + CB23	TXC20-K	20
	TXC30-K	30
CCM4-PK + CB22	TXC50-K	50
TXC100-K	TXC100-K	100
TXC150-K	TXC150-K	150
TXC200-K	TXC200-K	200
Triaxial (F) – Triaxial (M) EU preferred type	TXC10-F	10
CCF5-JFC + CB31	TXC20-F	20
	TXC30-F	30
CCM5-PFC + CB32	TXC50-F	50
TXC100-F	TXC100-F	100
TXC150-F	TXC150-F	150
TXC200-F	TXC200-F	200

Mini-WECO Video Patch

Type	Model	Length (m)
MVP-C4 LV-61S MVP-C4  BLK RED YEL GRN BLU	MVPC003	0.3
MVP-C4 LV-61S BCP-A4  BLK RED YEL GRN BLU	MVPC005	0.5
BCJ-C4 LV-61S MVP-C4  BLK RED YEL GRN BLU	MVPC01	1
MVPC02A-BP	MVPC02A-BP	2
MVPC05A-BP	MVPC05A-BP	5
MVPC002-BJ	MVPC002-BJ	0.2



MVPC003


RS422

Used for RS422 serial signals that remotely control video cassette recorders.

Type	Model	Length (m)
Dsub9P (M) – Dsub9P (M) 17JE-23090-02 (D8A6)-CG 17JE-23090-02 (D8A6)-CG A2C3-SS	DC01-9JE22	1
 BLK Screws : 2.6	DC03-9JE22	3
DC05-9JE22	DC05-9JE22	5
DC07-9JE22	DC07-9JE22	7
DC10-9JE22	DC10-9JE22	10
DC20-9JE22	DC20-9JE22	20
DC30-9JE22	DC30-9JE22	30
Dual Bantam – Dual Bantam  For RS422 patchbay. (Manufactured by ADC) GRY	PJ762	0.3
	PJ764	0.6

DMX

Used for controlling stage and studio lighting equipment.
(DMX-512 standard compliance)

Type	Model	Length (m)
NC5 (F) – NC5 (M) NC5FXX-B DMX203-2P NC5MXX-B  BLK GRY WHT	DMC01-B	1
DMC03-B	DMC03-B	3
DMC05-B	DMC05-B	5
DMC10-B	DMC10-B	10
DMC20-B	DMC20-B	20
DMC30-B	DMC30-B	30
DMC50-B	DMC50-B	50
DMC100-B	DMC100-B	100


Cable Assemblies

Ethernet

Cat6 (Standard STP)

Type	Model	Length (m)
RJ45 - RJ45	NC6F-01	1
	NC6F-015	1.5
	NC6F-02	2
	NC6F-03	3
	NC6F-05	5
	NC6F-07	7
	NC6F-10	10
	NC6F-15	15
	NC6F-20	20
	NC6F-25	25
	NC6F-30	30
	NC6F-35	35
	NC6F-40	40
	NC6F-45	45
	NC6F-50	50
	NC6F-70	70
	NC6F-100	100

BLK LB



T568B (Straight)


Cat5e (Flexible STP)

Type	Model	Length (m)
etherCON - etherCON	ETC003S-B	0.3
	ETC005S-B	0.5
	ETC01S-B	1
	ETC015S-B	1.5
	ETC02S-B	2
	ETC03S-B	3
	ETC05S-B	5
	ETC07S-B	7
	ETC10S-B	10
	ETC15S-B	15
	ETC20S-B	20
	ETC30S-B	30
	ETC50S-B	50
RJ-45 - RJ45	ETC003S-M	0.3
	ETC005S-M	0.5
	ETC01S-M	1
	ETC015S-M	1.5
	ETC02S-M	2
	ETC03S-M	3
	ETC05S-M	5
	ETC07S-M	7
	ETC10S-M	10
	ETC15S-M	15
	ETC20S-M	20
	ETC30S-M	30
	ETC50S-M	50
etherCON - RJ45	ETC02S-BM	2
	ETC05S-BM	5

Cat6 (Standard UTP)

Type	Model	Length (m)
RJ45 - RJ45	NC6-003	0.3
	NC6-005	0.5
	NC6-01	1
	NC6-015	1.5
	NC6-02	2
	NC6-03	3
	NC6-05	5
	NC6-07	7
	NC6-10	10
	NC6-15	15
	NC6-20	20
	NC6-25	25
	NC6-30	30
	NC6-35	35
	NC6-40	40
	NC6-45	45
	NC6-50	50

BLK GRY



T568B (Straight)

Cat5e (Rugged UTP)


Type	Model	Length (m)
etherCON - etherCON	ETC10L-B	10
	ETC30L-B	30
	ETC50L-B	50
	ETC70L-B	70
	ETC100L-B	100
RJ-45 - RJ45	ETC10L-M	10
	ETC30L-M	30
	ETC50L-M	50
	ETC70L-M	70
	ETC100L-M	100

Easy routing

Cat5e (Standard UTP)







Type	Model	Length (m)
RJ45 - RJ45	NC5E-003	0.3
	NC5E-005	0.5
	NC5E-01	1
	NC5E-015	1.5
	NC5E-02	2
	NC5E-03	3
	NC5E-05	5
	NC5E-07	7
	NC5E-10	10
	NC5E-15	15
	NC5E-20	20
	NC5E-25	25
	NC5E-30	30
	NC5E-35	35
	NC5E-40	40
	NC5E-45	45
	NC5E-50	50

LB









T568B (Straight)

XLR3

Type	Model	Length (m)
XLR3 (F) - XLR3 (M)		
XLR3-11C L-4E6S XLR3-12C	EC003	0.3
	EC005	0.5
	EC01	1
	EC015	1.5
	EC02	2
	EC03	3
	EC05	5
	EC07	7
	EC10	10
	EC15	15
	EC20	20
		
XLR3 (F) - XLR3 (F)		
XLR3-11C L-4E6S XLR3-11C	EC003-X11	0.3
	EC005-X11	0.5
	EC01-X11	1
	EC015-X11	1.5
	EC02-X11	2
	EC03-X11	3
	EC05-X11	5
	EC10-X11	10
		
XLR3 (M) - XLR3 (M)		
XLR3-12C L-4E6S XLR3-12C	EC003-X22	0.3
	EC005-X22	0.5
	EC01-X22	1
	EC015-X22	1.5
	EC02-X22	2
	EC03-X22	3
	EC05-X22	5
	EC10-X22	10
		
NC3 (F) - NC3 (M)		
NC3FXX-B L-4E6S NC3MXX-B	EC003-B	0.3
	EC005-B	0.5
	EC01-B	1
	EC015-B	1.5
	EC02-B	2
	EC03-B	3
	EC05-B	5
	EC07-B	7
	EC10-B	10
	EC15-B	15
	EC20-B	20
		
NC3 (F) - NC3 (F)		
NC3FXX-B L-4E6S NC3FXX-B	EC003-B11	0.3
	EC005-B11	0.5
	EC01-B11	1
	EC015-B11	1.5
	EC02-B11	2
	EC03-B11	3
	EC05-B11	5
	EC10-B11	10
		
NC3 (M) - NC3 (M)		
NC3MXX-B L-4E6S NC3MXX-B	EC003-B22	0.3
	EC005-B22	0.5
	EC01-B22	1
	EC015-B22	1.5
	EC02-B22	2
	EC03-B22	3
	EC05-B22	5
	EC10-B22	10
		


Phone

Type	Model	Length (m)
Mono Phone (M) - Mono Phone (M)		
F-15 GS-6 F-15	LC018	1.8
	LC03	3
	LC05	5
XLR3 (F) - Mono Phone (M)		
XLR3-11C L-4E6S F-15	PC03	3
	PC05	5
	PC07	7
	PC10	10
NC3 (F) - Mono Phone (M)		
NC3FXX-B L-4E6S F-15	PC03-B	3
	PC05-B	5
	PC07-B	7
	PC10-B	10
Stereo Phone (M) - Stereo Phone (M)		
F-16 L-4E6S F-16	SPC01	1
	SPC03	3
	SPC05	5
	SPC07	7
	SPC10	10
NC3 (F) - Stereo Phone (M)		
NC3FXX-B L-4E6S F-16	SPC02-B1	2
	SPC05-B1	5
NC3 (M) - Stereo Phone (M)		
NC3MXX-B L-4E6S F-16	SPC02-B2	2
	SPC05-B2	5



Cable Assemblies

RCA, Speaker, Audio Patch

RCA (Audio)

Type	Model	Length (m)
RCA (M) – RCA (M)  BLK RED ORN YEL GRN BLU	RC018	1.8
	RC03	3
	RC05	5
XLR3 (F) – RCA (M)  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	RC02-X1	2
	RC05-X1	5
XLR3 (M) – RCA (M)  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	RC02-X2	2
	RC05-X2	5
Mono Phone (M) - RCA (M)  BLK RED ORN YEL GRN BLU	QC018	1.8
	QC03	3
	QC05	5


Audio Patch (Bantam)

Type	Model	Length (m)
Bantam (M) – Bantam (M)  BLK RED ORN YEL GRN BLU GRY	BC003M	0.3
	BC006M	0.6
	BC009M	0.9
XLR3 (F) - Bantam (M)  BLK RED ORN YEL GRN BLU GRY	BC02M-X1	2
XLR3 (M) – Bantam (M)  BLK RED ORN YEL GRN BLU GRY	BC02M-X2	2



BC003M

Audio Patch (Skini/Maxi)

Type	Model	Length (m)
Skini/Maxi (M) – Skini/Maxi (M)  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	TC003B	0.3
	TC005B	0.5
	TC01B	1
XLR3 (F) – Skini/Maxi (M)  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	TC02B-X1	2
	TC05B-X1	5
XLR3 (M) – Skini/Maxi (M)  BLK BRN RED ORN YEL GRN BLU PPL GRY WHT	TC02B-X2	2
	TC05B-X2	5



TC003B

Speaker


Types available for either XLR or Neutrik "Speakon" connectors.

Type	Model	Length (m)
XLR4 (F) – XLR4 (M)  BLK RED BLU GRY CRE	SC003	0.3
	SC005	0.5
	SC01	1
	SC05	5
	SC10	10
	SC15	15
XLR4 (F) – XLR4 (M)  BLK GRY	SC05-S8	5
	SC10-S8	10
	SC15-S8	15
NL4 – NL4  BLK GRY	SC05-NL	5
	SC10-NL	10
	SC15-NL	15
	SC20-NL	20
	SC30-NL	30





SC05-NL

AES/EBU Digital Audio

Type	Model	Length (m)
XLR3 (F) – XLR3 (M)	DAC03	3
XLR3-11C DA202 XLR3-12C	DAC05	5
	DAC10	10
	DAC20	20
	DAC30	30

AES/EBU Digital Audio (Multi)

Type	Model	Length (m)
Dsub25P (M) – Dsub25P (M)	8DAC02-xx	2
	8DAC03-xx	3
	8DAC05-xx	5
	8DAC07-xx	7
	8DAC10-xx	10
	8DAC30-xx	30
Dsub25P (M) - NC3 (F/M)	8DACS02-xB12	2
	8DACS03-xB12	3
	8DACS05-xB12	5
	8DACS07-xB12	7
	8DACS10-xB12	10
	8DACS30-xB12	30

* Please use following information to fill in the 'x' in the model above.

Ordering Information

Model	Brands (ref.)	A-side		B-side	
		Screws	Wiring	Screws	Wiring
8DAC**-DD	Digidesign	4-40	Individual-A	4-40	Individual-B
8DAC**-TT	TEAC	M2.6	Individual-A	M2.6	Individual-B
8DAC**-YY	YAMAHA	M2.6	Common-A	M2.6	Common-B
8DAC**-DT	Digidesign - TEAC	4-40	Individual-A	M2.6	Individual-B
8DAC**-DY	Digidesign - YAMAHA	4-40	Individual-A	M2.6	Common-B
8DAC**-TY	TEAC - YAMAHA	M2.6	Individual-A	M2.6	Common-B
8DACS**-DB12	Digidesign	4-40	Individual-A	N/A	2: Hot 3: Cold 1: Shield
8DACS**-TB12	TEAC	M2.6	Individual-A	N/A	
8DACS**-YB12	YAMAHA	M2.6	Common-A	N/A	

<Wiring>

Individual-A

Ch. No.	Color Coding	HOT	COLD	SHIELD	N.C.
1	BLU/BRN	24	12	25	13
2	BLU/RED	10	23	11	
3	BLU/ORG	21	9	22	
4	BLU/YEL	7	20	8	
5	BLU/GRN	18	6	19	
6	BLU/-	4	17	5	
7	BLU/PPL	15	3	16	
8	BLU/GRY	1	14	2	

Individual-B

Ch. No.	Color Coding	HOT	COLD	SHIELD	N.C.
1	BLU/BRN	18	6	19	13
2	BLU/RED	4	17	5	
3	BLU/ORG	15	3	16	
4	BLU/YEL	1	14	2	
5	BLU/GRN	24	12	25	
6	BLU/-	10	23	11	
7	BLU/PPL	21	9	22	
8	BLU/GRY	7	20	8	

Common-A

Ch. No.	Color Coding	HOT	COLD	SHIELD	N.C.
1	BLU/BRN	1	14	10	9
2	BLU/RED	2	15	12	
3	BLU/ORG	3	16	13	
4	BLU/YEL	4	17	22	
5	BLU/GRN	5	18	23	
6	BLU/-	6	19	24	
7	BLU/PPL	7	20	25	
8	BLU/GRY	8	21		

Common-B

Ch. No.	Color Coding	HOT	COLD	SHIELD	N.C.
1	BLU/BRN	5	18	10	9
2	BLU/RED	6	19	12	
3	BLU/ORG	7	20	13	
4	BLU/YEL	8	21	22	
5	BLU/GRN	1	14	23	
6	BLU/-	2	15	24	
7	BLU/PPL	3	16	25	
8	BLU/GRY	4	17		

Analog Audio (Multi)

Type	Model	Length (m)
Dsub25P (M) - Dsub25P (M)	8MC02-x	2
	8MC03-x	3
	8MC05-x	5
	8MC07-x	7
	8MC10-x	10
	8MC30-x	30
Dsub25P (M) - NC3 (F)	8MCS02-xB1	2
	8MCS03-xB1	3
	8MCS05-xB1	5
	8MCS07-xB1	7
	8MCS10-xB1	10
	8MCS30-xB1	30
Dsub25P (M) - NC3 (M)	8MCS02-xB2	2
	8MCS03-xB2	3
	8MCS05-xB2	5
	8MCS07-xB2	7
	8MCS10-xB2	10
	8MCS30-xB2	30
Dsub25P (M) - NC3 (F/M)	8MCS02-CB12	2
	8MCS03-CB12	3
	8MCS05-CB12	5
	8MCS07-CB12	7
	8MCS10-CB12	10
	8MCS30-CB12	30






* Please choose between A: M2.6 and C: #4-40, and fill in the 'x' in the model with A or C.
e.g. 8MC02-A, 8MCS02-CB1

<Wiring for 8MC/8MCS>





Ch. No.	Color Cording	Dsub25P				NC3		
		HOT	COLD	SHIELD	N.C.	HOT	COLD	SHIELD
1	BLK/BRN	24	12	25		2	3	1
2	BLK/RED	10	23	11		2	3	1
3	BLK/ORG	21	9	22		2	3	1
4	BLK/YEL	7	20	8		2	3	1
5	BLK/GRN	18	6	19		2	3	1
6	BLK/BLU	4	17	5		2	3	1
7	BLK/PPL	15	3	16		2	3	1
8	BLK/GRY	1	14	2		2	3	1

HDMI

■ High Speed HDMI Cable with Ethernet




Type	Model	Length (m)	O.D. (mm)
HDMI - HDMI	HDM006E	0.6	6.0
	HDM01E	1	
	HDM015E	1.5	
	HDM02E	2	
	HDM03E	3	
	HDM05E	5	
HDMI - HDMI (Blister Packaged)	HDM009ED	0.9	6.0
	HDM015ED	1.5	
	HDM02ED	2	
	HDM03ED	3	
	HDM05ED	5	
comes in a blister package			
MOQ: 16 pcs (3m or less) 12 pcs (5m)			
BLK			
			

■ Active HDMI Cable

Type	Model	Length (m)	O.D. (mm)
HDMI - HDMI	 Source-side Monitor-side BLK	HDM07E-EQ	7
	HDM10E-EQ	10	7.0
	HDM15E-EQ	15	8.0
HDMI - HDMI	 Source-side Monitor-side BLK	HDM20-EQ	20
			9.0
HDMI Ethernet Channel not supported			

Note: Active HDMI cables are directional. Please pay attention to the plug shapes.

■ High Speed HDMI Cable

Type	Model	Length (m)	O.D. (mm)
HDMI - HDMI	 L BLK	HDM006	0.6
	HDM01	1	
	HDM015	1.5	
	HDM02	2	
	HDM03	3	
	HDM05	5	
HDMI Ethernet Channel not supported			5.5
			6.5



HDE100CP-EX

TX: 115 x 32 x 91 mm, 230g
RX: 115 x 29 x 81 mm, 170g

■ HDMI Extender

Extend uncompressed HDMI signal up to 100 meters over a Cat6 STP cable.

Model	Description
HDE100CP-EX	Package includes TX unit, RX unit, IR cables, AC/DC adapter, and wall mount tabs

Key Features and Benefits

- 100m@1080p, 70m@4K with Cat6 STP 24AWG
- Power over Ethernet (PoE)
- Bi-directional RS-232 and wideband IR extension.
- CEC/HDCP passthrough

Note: Max. lengths may vary depending on cables.

HEC and ARC are not supported.

<Connection Example>




Note: HDE100CP-EX does not include Ethernet/HDMI/RS232 cables.

DVI-D Dual Link

VESA-DDC Plug and Play compliant

Type	Model	Length (m)
DVI-D (M) - DVI-D (M)	DVID01	1
	DVID015	1.5
	DVID02	2
	DVID03	3
	DVID05	5



DVI-HDMI NEW

DVI-D Single Link to HDMI

Type	Model	Length (m)
DVI-D (M) - HDMI	DVI01-HDM	1
	DVI015-HDM	1.5
	DVI02-HDM	2
	DVI03-HDM	3
	DVI05-HDM	5

BLK Screws: #4-40 UNC inch thread

Note: DVI cannot carry audio signal.

VGA

VESA-DDC Plug and Play compliant.
5VDC-1.7CF series are enhanced by low-loss coax unit.

Type	Model	Length (m)
HD-15 (M) - HD-15 (M)	5VDC015-1.7CF	1.5
	5VDC02-1.7CF	2
	5VDC03-1.7CF	3
	5VDC05-1.7CF	5
	5VDC10-1.7CF	10
	5VDC15-1.7CF	15
	5VDC20-1.7CF	20
HD-15 (M) - BNC (F) e-CON (F)	HDR15F-EJ1.5CA	0.13
e-CON male plug and lock nuts included		

• V5D2P-1.7CF is not for sale.

VGA

Not compatible with VESA-DDC Plug and Play.



Type	Model	Length (m)
HD-15 (M) - HD-15 (M)	5VDC015A-1.5C	1.5
Dsub HD15 V5-1.5C+ Dsub HD15		
BLK Screws: #4-40 UNC inch thread		
HD-15 (M) - BNC (M)	5VDS015A-1.5C	1.5
Dsub HD15 V5-1.5C+ BCP-C1		
A: 15cm (5VDS015A-1.5C) 30cm (others)		
BLK Screws: #4-40 UNC inch thread		
HD-15 (M) - BNC (F)	5VDS003A-J1.5C	0.3
Dsub HD15 V5-1.5C+ BNC Jack		
A: 15cm (5VDS015A-1.5C) 30cm (others)		
BLK Screws: #4-40 UNC inch thread		
HD-15 (M) - BNC (F)	5VDS015A-J1.5C	1.5
	5VDS02A-J1.5C	2
	5VDS03A-J1.5C	3
	5VDS05A-J1.5C	5
	5VDS10A-J1.5C	10
Lock nuts included		
	HDR15F-J1.5CA	0.13






5VDS02A-1.5C

VGA with Audio

VESA-DDC Plug and Play compliant

Type	Model	Length (m)
HD-15 (M) – HD-15 (M) 3.5mm TRS – 3.5mm TRS	A1VGA005	0.5
	A1VGA0075	0.75
	A1VGA01	1
	A1VGA015	1.5
	A1VGA02	2
	A1VGA03	3
	A1VGA05	5
	A1VGA10	10

3 RCA Video & Audio NEW

Type	Model	Length (m)
RCA - RCA	3RCS003	0.3
	3RCS005	0.5
	3RCS01	1
	3RCS15	1.5
	3RCS02	2
	3RCS03	3
	3RCS05	5
	3RCS10	10
	3RCS15	15
	3RCS20	20
	3RCS30	30

2 RCA Stereo Audio NEW

Type	Model	Length (m)
RCA - RCA	2RCS003	0.3
	2RCS005	0.5
	2RCS01	1
	2RCS15	1.5
	2RCS02	2
	2RCS03	3
	2RCS05	5
	2RCS10	10
	2RCS15	15
	2RCS20	20
	2RCS30	30

BLK

Screws: #4-40 UNC inch thread



👑 : Bestselling products

0	06-1001-015	74
06-1001-016	74	
06-1001-017	74	
06-1877-04	74	
1	10CFTX-SC	61
10PSC-JP	13	
125	74	
12B1N2	77	
12B2N1	77	
12C**-E3	76	
12C**-M2	76	
12FS**-S	24	
12J12N1	77	
12J12N12	77	
12J12N2	77	
12R**-E3	76	
12S1N2	77	
12S2N1	77	
14347 CLEANER	20	
161U-B1	71	
161U-B2	71	
161U-JRU	71	
161U-JRUDB	71	
161UPSC-**	13	
161U-X12F	71	
161U-X1F	71	
161U-X2F	71	
162U-JRU	71	
162U-X21	71	
162U-X22	71	
16B1F2	77	
16B2F1	77	
16C**-E3	76	
16C**-M2	76	
16FS**-S	24	
16J12F1	77	
16J12F12	77	
16J12F2	77	
16R**-E3	76	
16S1F2	77	
16S2F1	77	
1U-AS*	72	
1U-AS*D	72	
2	20DV	66
20DV-2U	66	
20DVS	66	
20DVS-2U	66	
24B12MS	77	
24B12MSW	77	
24C**-E3	76	
24C**-M2	76	
24C005-E3MS22	76	
24DV	66	
24DV-2U	66	
24DVS	66	
24DVS-2U	66	
24FS**-S	24	
24R30-E3	76	
24S1MS2	77	
24S2MS2	77	
26DV	66	
26DV-2U	66	
26DVS	66	
26DVS-2U	66	
26WB-*	74	

2	2FG5Z3S**-S	24
2FG6Z3S**-S	24	
2FS**-S	24	
2FSZ3S**-S	24	
2PSC	13	
2RCS**	88	
2S11F	57	
2S11FG	57	
2S14F	57	
2S14FG	57	
2S7F	57	
2S7FG	57	
2S9F	57	
2S9FG	57	
2U-AS*	72	
2U-AS*D	72	
3	320A	73
32-12A/620A/EIA	73	
32B12MF11	77	
32B12MS	77	
32B12MSW	77	
32B12MWF11	77	
32C**-M2	76	
32C005-M2MS22	76	
32MD-ST	67	
32MD-ST-*U	67	
32MD-STS	67	
32MD-STS-*U	67	
32S1MS2	77	
32S2MS2	77	
32WB-*	74	
32XP-*	74	
3U-AS*	72	
3U-AS*D	72	
3RC5**	88	
4	48-12A/820AQ/EIA	73
481U-820AQ	73	
481U-WB*	74	
48WB-*	74	
48XP-*	74	
4FS**-S	24	
4FS**T-LS	23	
4FS**T-SS	23	
4FS**T-ST	23	
4S10F	56	
4S10FG	56	
4S11	56	
4S11G	56	
4S12F	56	
4S12FG	56	
4S14F	56	
4S18F	56	
4S6	56	
4S6G	56	
4S8	56	
4S8G	56	
5	525	74
5VDO**-1.7CF	87	
5VDC**A-1.5C	87	
5VDS**A-1.5C	87	
5VDS**A-J1.5C	87	
6	6000AQ	73
612A/320A/EIA	73	
620A	73	
6FS**-S	24	

8	6PSC-**	13
820AQ	73	
8B1N2	77	
8B2N1	77	
8C**-E3	76	
8C**-M2	76	
8DAC**-xx	85	
8DACS**-xB12	85	
8FS**-S	24	
8J12N1	77	
8J12N12	77	
8J12N2	77	
8MC**-x	85	
8MCS**-CB12	85	
8MCS**-xB1	85	
8MCS**-xB2	85	
8R**-E3	76	
8S1N2	77	
8S2N1	77	
9	90-602	74
90-608	74	
90-T	74	
A	A1VGA**	88
A2C3	58	
A2C3-SS	58	
A2V1	63	
A2V1B	63	
A2V2B	63	
A2V2-L	63	
A3V2-FB	63	
ABJ-DC	73	
AN3420-*	76	
ASPT-1	19	
B	B11014E	30, 31, 38
B11015E	30, 31, 38	
B11016E	30, 31, 38	
B11020D	30, 31, 38	
B75004A	30, 31, 38, 39	
BC**M	84	
BC**M-X1	84	
BC**M-X2	84	
BCA-RL	27	
BCA-RS	27	
BCA-TL	27	
BCA-TS	27	
BCJ-A10TRC-XP3F	45	
BCJ-BPC2P	34	
BCJ-BPLH2PA	34	
BCJ-BPLH3PA	34	
BCJ-BPLHA	34	
BCJ-C4	32	
BCJ-DC	36	
BCJ-DC-CH	36	
BCJ-DCJ	28	
BCJ-FC1	33	
BCJ-FC1-7/16	33	
BCJ-FPC	34	
BCJ-FPC02	34	
BCJ-FPLHA	34	
BCJ-FPLV01	34	
BCJ-FPLVA	34	
BCJ-FPLV-L	34	
BCJ-J	32	
BCJ-JR	33	
BCJ-JRU	33	
BCJ-JRUD	33	
BCJ-JRUB	33	
BCJ-MVP	68	
BCJ-R	33	
BCJ-R/1	33	
BCJ-RCAP	36	
BCJ-RPC	35	
BCJ-RPC/1	35	
BCJ-RPLH	35	
BCJ-RPLV	35	
BCJ-RU	33	
BCJ-RUC1	33	
BCJ-RUD	33	
BCJ-RUDB	33	
BCJ-TRC-XP3F	45	
BCJ-TRC-XP3M	45	
BCJ-VWP	68	
BCJ-XJ-A10TRC	45	
BCJ-XJ-TRC	45	
BCJ-XP-TRC	45	
BCP-A25	30	
BCP-A25F	30	
BCP-A3	30	
BCP-A31	30	
BCP-A32	30	
BCP-A3F	30	
BCP-A4	30	
BCP-A42	30	
BCP-A4F	30	
BCP-A5	30	
BCP-A52	30	
BCP-A55	30	
BCP-A5F	30	
BCP-A77	30	
BCP-B25HD	30	
BCP-B25HW	30	
BCP-B26	30	
BCP-B28	30	
BCP-B31F	30	
BCP-B3F	30	
BCP-B45HW	30	
BCP-B4F	30	
BCP-B51F	30	
BCP-B53	30	
BCP-B56	30	
BCP-B5F	30	
BCP-C1	30	
BCP-C5HD	30	
BCP-C6HD	30	
BCP-C71A	30	
BCP-C7FA	30	
BCP-C7HD	30	
BCP-DCJ	28	
BCP-H31F	32	
BCP-H3B	32	
BCP-H45HW	32	
BCP-H5/1	32	
BCP-H51F	32	
BCP-H5B	32	
BCP-LC3	31	
BCP-LC3F	31	
BCP-LC5	31	
BCP-LC5F	31	
BCP-RCAJ	36	
BCP-TB	32	

NEW	BCP-TB-CH	32
	BCP-VA3	28
	BCP-VA5	28
	BET-12	42
	BET-DIN	42
	BET-MBNC	42
	BJ-J	40
	BJ-JR	40
	BJ-JRU	40
	BJ-JRUD	40
	BN1002B	39
	BN1003B	39
	BN1004B	39
	BN1005B	39
	BN1012B	30
	BN1016C	40
	BN1018A	30
	BN1023A	40
	BN1024A	40
	BN1025B	40
	BN1030A	39
	BN1041A	39
	BN1043A	30
	BN1082A	30
	BN1083A	30
	BN1093	38
	BN1131	37
	BN1135	37
	BN1139	30
	BN1148	28
	BN1157	28
	BN1158	28
	BN7002	40
	BN7003A	28, 30, 31, 38, 39
	BN7011	30, 38, 39
	BN7014	30, 39
	BN7015A	28, 30, 31, 38, 39
	BN7016	30, 31, 38, 39
	BN7021A	30, 39
	BN7022	30
	BN7026A	30
	BN7029C	30, 31, 38
	BN7030A	40
	BN7045A	30, 39
	BN7046	30, 31, 39
	BN7052A	30
	BN7074A	30
	BN7079	38
	BN7113	37
	BN7114	37
	BN7120	37
	BN7121	37
	BN7129	30, 38, 39
	BN7136	28
	BN7138	28
	BN7143	30
	BN9078A	29
	BN9079B	29
	BN9127A	37
	BN9128B	37
	BN9182A	37
	BN9194	37
	BP-C3	40
	BP-C31	40
	BP-C4	40

C	BP-C5	40
	BP-C51	40
	BP-C5FA	40
	BP-D	71
	BP-DXF	71
	BP-LC31	40
	BP-LC51	40
	BP-XF	71
	CB01	32
	CB02	32
	CB03	32
	CB04	32
	CB05A	32
	CB22	37
	CB23	37
	CB24	32
	CB25	32
	CB26	32
	CB31	37
	CB32	37
	CCF4-JK	37
	CCF4-JKR	37
	CCF5-JFC	37
	CCF5-JFRC	37
	CCF7-JFC	37
	CCF7-JFRC	37
	CCM4-PK	37
	CCM4-PKR	37
	CCM5-PFC	37
	CCM5-PFRC	37
	CCM7-PFC	37
	CCM7-PFRC	37
	CLETOP 2.5/2.0	20
	COF**	22
	COPS3-FF*	20
	COPS3-FM*	20
	COPS-FF*	20
	COPS-FM*	20
	COU-BP*	21
	COUS-FF*	21
	COUS-FM*	21
	CR100-CN	79
	CR100-S	79
	CR90-BN	79
D	D/MS3057-20A	76
	D/MS3057-24A	76
	D/MS3101A32A10P	76, 77
	D/MS3101A36-73P	76, 77
	D/MS3102A32A10P	76
	D/MS3102A36-73P	76
	D/MS3106B32A-10S	76
	D/MS3106B36-73S	76
	D2.5HDC**E	80
	D2.5HDC**E-D	80
	D3C**A-S	80
	D3C**A-SR	80
	D3FBC**-E	80
	D4.5HDC**E	80
	D4.5HDC**E-D	80
	D5C**A-S	80
	DA202	55
	DA202AT	55
	DA202F-*P	55
	DA203-*AL	55
	DA203AL	55

DA206	55
DAC**	85
DC**-9JE22	81
DCF01	29
DCF02	37
DCJ-C25HW-ML	29
DCJ-FEM	28
DCJ-JR	28
DCJ-LR	28
DCJ-LR/1	28
DCM01	29
DCM02	37
DCM03	37
DCP-C25HD	28
DCP-C25HW-ML	29
DCP-C3F	28
DCP-C4F	28
DCP-C53	28
DMC**-B	81
DMX203-2P	58
DN2.5HDC**	80
DN4.5HDC**	80
DRC**-F3	81
DRC**-S	81
DS10-AS1	73
DS10-AS2	73
DS10-AS3	73
DS10-AS4	72
NEW DVI**-HDM	87
DVID**	87
DVJB-S	66
DVJB-W	66
E EB-02	75
EB-03	75
EC**	83
EC**-B	83
EC**-B11	83
EC**-B22	83
EC**-X11	83
EC**-X22	83
EE3G-100	7
E0-100A-**	8
E0-100B	8
E0-160	8
E03G-100	7
E03G-100A-**	7
E03G-200	7
E0-500-**	9
E0-700	8
E0-700A-**	8
ETC**L-B	82
ETC**L-M	82
ETC**S-B	82
ETC**S-BM	82
ETC**S-M	82
F-09	38
F-10	38
F-11	39
F-12	39
F-15	39
F-16	39
F3-FCC**-7N	17
F5-FCC**-7N	17
NEW FCBA4-FF5W1	14
NEW FCBA4-FF5W1-PV	14
GS-4	58
GS-6	58
H HDE100CP-EX	86
HDM**	86
HDM**E	86
HDM**ED	86
HDM**E-EQ	86
HDM20-EQ	86
HDR15F-EJ1.5CA	87
HDR15F-J1.5CA	87
I IU-7/16	33

L	IU-FCF-SET	19
	IU-FCM-SET	19
L	L-1.5C2VS	61
	L-2.5C2V	61
	L-2.5CFB	61
L	L-2.5CHD	60
	L-2.5CHLT	60
	L-2B2AL	51
L	L-2B2AT	51
	L-2E4-*AL	52
	L-2E5	51
	L-2E5AL	51
L	L-2E5AT	51
	L-2T2S	51
	L-3C2V	61
	L-3C2VS	61
	L-3C2W	61
L	L-3CFB	61
	L-3CFW	61
	L-3D2V	63
	L-3D2W	63
L	L-4.5CHD	60
L	L-4.5CHWS	60
L	L-4CFB	61
	L-4CFX	61
	L-4CHD	60
	L-4E3-*AT	50
L	L-4E3-*P	50
	L-4E3-2H	50
	L-4E3AT	49
L	L-4E4-*AT	50
	L-4E4-*P	50
	L-4E5	49
L	L-4E5AT	49
	L-4E5ATG	49
	L-4E5C	49
	L-4E6	49
L	L-4E6AT	49
	L-4E6ATG	49
L	L-4E6S	49
NEW	L-4E6-WBS	49
	L-5C2V	61
	L-5C2VS	61
	L-5C2W	61
L	L-5CFB	61
	L-5CFX	61
	L-5CFW	60
	L-5CHD	60
	L-5D2V	63
	L-5D2W	63
	L-5DFB	63
	L-6CHD	60
	L-7CFB	61
	L-7CFX	61
L	L-7CHD	60
	L-8CHD	60
	LC**	83
	LF-2SM16	16
	LF-2SM7N	17
	LF-2SM7N-*P	17
NEW	LF-2SM7T	18
	LF-2SM9	16
L	LF-2SM9N	16
NEW	LF-2SM9T	18
	LF-SM2-*C	23
M	NEW LF-SM2T-4C	23
	NEW LV-61S	61
	LV-77S	61
M	M202-*AT	53
	MBCP-C25F	31
	MBCP-C3F	31
	MBCP-C4	31
	MBCP-C4F	31
	MBCP-C53	31
	MBCP-C5F	31
	MCF-V5C3	29
	MCM-V5C3	29
	MDF-V4C25HW	29
	MDF-V4JRU	29
	MDM-V4C25HW	29
	MDVJ-STS	67
	MDVJ-STW	67
	MJ2-M32-1U-***	70
	MJ2-M32-2U-***	70
	M-MA*U02	72
M	MR202-*AT	53
	MS202	52
	MS202-*P	54
	MS203	52
	MS203-*BS	54
	MVJ-DC	67
	MVPC**	81
	MVPC**A-BP	81
	MVPC**-BJ	81
	MVP-C4	68
N	NE5E-**	82
	NC6-**	82
NEW	NC6F-**	82
	NCJ-BCJR	36
	NCP-H8HD	36
	NDT-DIN	28
	NK27-21C3/4-R	76, 77
	NK27-21C7/8-R	76
	NK27-22C3/4-R	76, 77
	NK27-22C7/8-R	76
	NK27-31S-R	77
	NK27-32S-R	77
	NP3TMC-B	73, 84
	NP-C**	41
	NP-LC**	41
O	OE-101B	8
	OE-151	8
	OE3G-101	7
	OE3G-201	7
	OE-501	9
	OE-701	8
	OM6C**	25
	OM6S**-JR	25
	OM6S**-PR	25
P	PC**	83
	PC**-B	83
	PH50-*	73
	PJ743	73
	PJ748	73
	PJ762	81
	PJ764	81
	PSM2-**	13
Q	QC**	84
R	R300	79
	R300-BN	79
	R300-CN	79
	R300-L	79
	R300-S	79
	R380-S	79
	R460-S	79
	RC**	84
	RC**-X1	84
	RC**-X2	84
	RCAP-C25F	38
	RCAP-C25HD	38
	RCAP-C3A	38
	RCAP-C3F	38
	RCAP-C3GS	38
	RCAP-C42	38
	RCAP-C4A	38
	RCAP-C4F	38
	RCAP-C53	38
	RCAP-C5A	38
	RCAP-C5F	38
	RCAP-C77	38
	RJ-BCJRU	38
	RJ-BCJRUD	38
	RJ-BCJRUDB	38
	RJC5E-4P+	59
	RJC5E-4P-WJ	59
	RJC5ES-4P-BS	59
	RJC6-4P+	59
NEW	RJC6-4P-F	59
	RJ-JR	38
	RJ-JRU	38
	RJ-JRUD	38
	RJ-JRUDB	38
	RJ-RU	38
	RJ-RUD	38
	RJ-RUDB	38
	RS-422-1U-**	70
	RS-422-2U-**	70
S	S410-*P	56
	SC**	84
	SC**-NL	84
	SC**-S8	84
	SMAJ-C*	41
	SMAP-C*	41
	SPC**	83
	SPC**-B1	83
	SPC**-B2	83
T	TB-2A	42
	TC**B	84
	TC**B-X1	84
	TC**B-X2	84
	TC-1	42
	TC-2	42
	TCD-1DB	42
	TCD-3151D	42
	TCD-316C	42
	TCD-31C	42
	TCD-35CA	42
	TCD-35D	42
	TCD-35DF	42
	TCD-451CA	42
	TCD-4CA	42
	TCD-55FA	42
	TCD-5CF	42
	TCD-5HD	42
	TCD-65C	42
V	V*-1.5C	62
	V*-3C	62
	V*-3CFB	62
	V*-3CFW	62
	V*-4CFB	62
	V*-5C	62
	V*-5CFB	62
	V*-5CFW	62
	V4-2.5CHW	62
	VJ2-M32-4U	70
	VJ2-V20-1U-***	70
	VJ2-V20-2U-***	70
	VJ2-V24-1U-***	70
	VJ2-V24-2U-***	70
	VJ2-V26-1U-***	70
	VJ2-V26-2U-***	70
	VJ-DC	66
	VPC**-WC	81
	VWP-C4A	68
X	XJ3F-A10TRC-BCJ	45
	XJ3F-P3FA	71
	XJ3F-P3MA	71
	XJ3F-TRC-BCJ	45
	XJ3M-P3FA	71
	XJ3M-P3MA	71
	XJ3M-TRC-BCJ	45
	XLR3-11C	75, 77, 83
	XLR3-12C	75, 77, 83
	XLR3-31F77	75, 77
	XLR3-32F77	75, 77
	XLR4-11C	84
	XLR4-12C	84

GENUINE Canare Products for the Best Quality.

Canare Electric Co., Ltd.

Japan Headquarters (Overseas Department)

4th FL, WN Bldg., 2-4-1 Shin-Yokohama, Kouhoku-ku,
Yokohama-shi, Kanagawa, 222-0033 Japan

Phone: +81-45-470-5674

Fax: +81-45-470-5676

E-mail: overseas@canare.co.jp

www.canare.co.jp/en/

